# FT-ONE TECHNICAL MANUAL

(UNOFFICIAL)





## **FOREWORD**

#### NOTES FROM THE COMPILER

This <u>unofficial</u> manual has been compiled from various sources, being the main one the PDF file which is freely available from various sites on the internet. Some pages were sent to me from FT-ONE manual owners, with a special mention to N5NH. The pictures are also from internet and my own units.

The main problem with the referred manual is in the schematics and other double page drawings, because there are gaps between the left and right pages so after stitching them it was necessary to draw and edit the missing parts.

Most pages have been subject to deskewing, general cleaning, contrast enhancement and sharpening. Also the detected errors in the schematics and text were corrected.

Finally, the black and white pictures have been replaced by color ones. This makes the resulting file bulky but I wanted to use high resolution photos so they can be zoomed in to see the details.

I focused in versions after S/N 06xxxxx but the material covering early versions has been kept. Information about the Power Supply was added to the original material and also the fan thermal control kit and the diagram of the chassis wiring. The same was done for a small board, not mentioned in the manual, which is in the bottom of the chassis near the remote control circuit. It is a kind of pulse shaper for the Noise Blanker, maybe it is optimized for the woodpecker radar.

I also corrected some obvious errors that were present in the original manual.

The PDF file has been indexed and page numbered. I kept the original page numbering, adding suffixes where new pages were inserted.

As usual, I cannot guarantee the correctness of the material and, as Yaesu states in the Preface, use it at your own risk.

If you notice errors that need correction, please send me an email to <a href="mailto:eb4apl@gmail.com">eb4apl@gmail.com</a>

I hope this work will be useful for FT-ONE fans and collectors.

## PREFACE

This Technical Manual is intended to serve as a companion volume to the FT-ONE Operating Manual. It will be noted that this volume begins with Section 2. The material covered in the Operating Manual, composing Section 1, is intended to provide general information, specifications, notes on accessories and installation, and operating instructions for the FT-ONE. These subjects are not covered again in this manual.

This purpose of this Technical Manual is to provide the reader with information critical to the maintenance and repair of the FT-ONE transceiver, as will as information useful for understanding its functions and operation more thoroughly. Technical explanations argeared toward providing a clear understanding of the overall system design, rather than attempting to cover many specific circuit details. Therefore descriptions have been kept brief, although photographs and drawings are utilized liberally.

Use of this manual is entirely at the owner's risk. The FT-ONE uses high quality components and a design and construction intended to last a long time without the need for alignment or servicing. Should the reader discover any errors in this manual, however, we invite any corrections; although Yaesu can not assume liability for damage which may occur when this manual is used as a reference.

Your attention to the note below is requested.


Yaesu Musen Company, Ltd. Tokyo


Copyright © 1982 Yaesu Musen Co., Ltd. All Rights Reserved


No portion of this Manual may be reproduced in any form without written permission of Yaesu Musen Co., Ltd.


# SECTION 2—TECHNICAL NOTES


BLOCK DIAGRAM	2-1
CIRCUIT DESCRIPTION	2-7
PLL CIRCUIT FREQUENCY RELATIONSHIPS	2-13
FREQUENCY RELATIONSHIPS	2-14
FREQUENCY RANGE MODIFICATION	2-15
QSK LINEAR AMPLIFIER MODIFICATION	2-17
RECEIVER STABILITY IMPROVEMENT MODIFICATIONS	2-18














FT-ONE CONTROL BLOCK DIAGRAM

## CIRCUIT DESCRIPTION

If you intend to secure the full potential of the high technology design of the FT-ONE a clear understanding of the functions of the various circuits of the transceiver is helpful.

The FT-ONE circuitry incorporates a new type of design in which a microprocessor is used to control many of the circuits in a manner that may not be familiar to the operator. The block diagrams, together with the following circuit descriptions, will provide you with a better understanding of the design of the FT-ONE. Refer to the schematic diagrams for specific component details. The following circuit descriptions apply to the fully equipped FT-ONE.

## RECEIVER

The RF signal from the antenna connects to the ALC Unit (PB-2260) where it is passed through antenna relay  $RL_{7101}$ , and then a low-pass filter and a lamp fuse, after which it is passed through the jumper between the RCV-1 and RCV-2 jacks on the rear panel. From RCV-2 the RF signal is delivered to the RF Unit (PB-2256).

## RF Unit (PB-2256)

The RF signal passes through impedance transformer T<sub>1001</sub> where the 50 ohm input impedance is converted to 200 ohms, and then fed through a diode switch to one of the ten band-pass filters selected by the receive frequency data from the microprocessor. From the band-pass filter the impedance is transformed at T1002 back to 50 ohms and this signal is fed to the PIN diode attenuator, consisting of D<sub>1042</sub>, D<sub>1043</sub> and D<sub>1044</sub> (1SV77); and on to the push-pull RF amplifier;  $Q_{1010}$  and  $Q_{1011}$  (2N4427). The signal then passes through a resistive attenuator to present exactly 50 ohms to the mixer circuit, consisting of three transformers and Schottky-barrier diode module Q<sub>1012</sub> (ND487C2-3R), where the signal is heterodyned with the local signal delivered from the local amplifier, resulting in a first IF frequency of 73.155 MHz. (See PLL description for details of local signal derivation.)

From the first mixer the first IF signal is fed through JFET post-amplifier  $Q_{1013}$  (2SK125-3) to 20 kHz BW, 4-pole crystal band-pass filter  $XF_{1001}$ , after which it is delivered to the IF Unit (PB-2255).

## IF Unit (PB-2255)

The filtered first IF signal is fed to singly-balanced second mixer Q<sub>9001</sub> and Q<sub>9002</sub> (3SK-73GR), where it is heterodyned with the second local signal to produce the 8.9875 MHz second IF. The frequency of the second local signal is determined by the mode of operation and the IF Shift function, and is approximately 64 MHz. The second IF signal from the second mixer is passed through 20 kHz BW, 4-pole crystal filter XF<sub>9001</sub>, except for a portion of this signal, which is diverted to noise blanker buffer Q<sub>9009</sub> (2SK-61GR) and passed to the noise blanker circuit. The signal from the crystal filter is amplified by Q<sub>9003</sub> (3SK73GR), which also serves as the noise blanker gate.

The signal is now passed through one of the 8-pole crystal filters determined by the mode of operation selected (SSB  $XF_{9005}$  is standard, AM  $XF_{9004}$ , CW-M  $XF_{9003}$  and CW-N  $XF_{9002}$  are options), to amplifier  $Q_{9008}$  (3SK73GR): with the exception of the signal from the CW-N crystal filter, which is first amplified by  $Q_{9007}$  (2SC945AP) to compensate for the greater insertion loss of the narrow bandwidth filter. From  $Q_{9008}$  the signal is applied to first width mixer  $Q_{9009}$  (3SK73GR), where it is heterodyned with the 19.7475 MHz ( $\pm$  1.5 kHz) signal from width oscillator  $Q_{9013}$  (2SC945AP) and crystal  $X_{9001}$ , via buffer  $Q_{9012}$  (2SC1923-O).

From the first width mixer the 10.76 MHz signal is fed through the second IF filter;  $XF_{9007}$  for SSB (and for CW and FSK if the optional filter is not installed),  $XF_{9006}$  for CW-M, CW-N, and FSK-N (if installed), or through an attenuator network for AM. Now the signal is fed to second width mixer  $Q_{9010}$  and  $Q_{9011}$  (2SK19TMY), where it is heterodyned again with the width oscillator signal—this time through buffer  $Q_{9014}$  (2SC1923-O). From this second width mixer the 8.9875 MHz signal passes through three stages of IF amplification provided by  $Q_{9015}$ ,  $Q_{9016}$ , and  $Q_{9017}$  (3SK73GR).

A portion of the output of Q<sub>9017</sub> is fed through buffer Q<sub>9018</sub> (2SC945AP) to AM detectors D<sub>9034</sub> and D<sub>9035</sub> (1N60), and through buffer Q<sub>9019</sub> (2SC945AP) to provide a signal for an external monitor scope. A portion of the signal from the AM detector is amplified by AGC amplifier Q<sub>9022</sub> (2SC945AP), which can be switched off by Q<sub>9021</sub> (2SC945AP). The AGC rate is switched by Q<sub>9023</sub> and Q<sub>9024</sub> (2SC945AP) controlling time constant networks R<sub>9135</sub> C<sub>9134</sub> and R<sub>9132</sub> C<sub>9135</sub> respectively. The AGC signal from Q<sub>9022</sub> is fed to quad differential input op amp Q<sub>9025</sub> (MC3403P), from where it is applied to the RF and IF amplifiers, the scanner circuitry (for automatic scan stop) and the S-meter.

The remainder of the signal from the AM detector passes through buffer  $Q_{9020}$  (2SC945AP) and is delivered to the AF Unit (PB-2252). The remainder of the IF amplifier output from  $Q_{9017}$  is also delivered to the AF Unit for SSB, CW, and FSK detection.

## AF Unit (PB-2252)

The IF signal from the IF Unit is applied to the active product detector IC, Q<sub>4001</sub> (SN16913P), where it is mixed with the carrier oscillator signal and the audio frequencies are detected. The frequency of this carrier oscillator signal is determined by the mode selected and the IF shift. The SSB, CW, or FSK signal from the product detector is then fed to one gate of analog switch Q<sub>4002</sub> (MC14016BCP), whose other gates are fed by the detected AM signal and the detected FM signal and whose control gates are selected by the MODE switch.

The output from the selected gate is amplified by one section of quad op amp  $Q_{4003}$  (MC3403P), and then fed through a high-pass filter (another section of  $Q_{4003}$ ), and a low-pass filter (third section), where a portion of the signal is diverted to the NOTCH/APF circuitry. The remainder of the signal from the low-pass filter section is fed directly to the audio power amplifier,  $Q_{4028}$  ( $\mu$ PC2002H), and from there to the speaker. When the NOTCH/APF is activated, the signal from the third section of  $Q_{4003}$  is fed through the audio band-pass filter circuit composed of the remaining quarter of  $Q_{4003}$  and the four op amp sections of  $Q_{4004}$  (MC3403P) before being fed to the audio power amplifier.

Noise Blanker (part of IF Unit (PB-2255) and Local Unit (PB-2253))

A portion of the 8.9875 MHz signal before the second mixer is amplified by JFET Q9004 (2SK-61GR) on the IF Unit and delivered to noise blanker mixer Q<sub>3002</sub> (3SK73GR) on the Local Unit, where it is heterodyned with the 9.4424 MHz signal from the noise blanker local oscillator, Q3001 (2SC945AQ), and crystal X3001. The 455 kHz product from the mixer is amplified by Q<sub>3003</sub> and Q<sub>3004</sub> (3SK73GR), after which a portion of the signal is rectified by noise blanker AGC diodes  $D_{3004}$  and  $D_{3005}$  (1N60), amplified by  $Q_{3007}$  (2SC-945AP), and fed back to  $Q_{3003}$  and  $Q_{3004}$ . The remainder of the signal from Q<sub>3004</sub> is amplified by Q<sub>3005</sub> (2SC945AP) and then rectified by diodes  $D_{3001}$  and  $D_{3002}$  (1N60). The DC output from these diodes is amplified by  $Q_{3006}$  (2SA733AP) and delivered back to the IF Unit, where it is buffered by Q<sub>9005</sub> (2SC945AP) and fed to noise gate MOSFET Q9003 (3SK73GR) just after first 9 MHz crystal filter XF<sub>9001</sub>.

## FM Unit (PB-2254, option)

A portion of the 8.9875 MHz second IF signal from crystal filter XF9001 is buffered by Q9006 (2SC945AP) before being delivered from the IF Unit to the FM Unit, when installed. On the FM Unit this received signal is then buffered by Q2101 (2SC1674L) and applied to mixer Q2102 (2SK-19TMGR), which also receives a 9.4425 MHz local signal generated by crystal oscillator Q2105 (2SC-945AP). The resulting 455 kHz output from Q<sub>2102</sub> is passed through ceramic filter CF2101 and then amplified by Q2103 (2SC945AP) and limiting amplifier Q2104 (µPC577H), where the amplitude variations on the filtered signal are removed. Output from Q2104 is applied through ceramic discriminator CD2101 and diode detectors D2101 and and D<sub>2102</sub> (1S188FM) to result in an audio output corresponding to frequency variations of the 455 kHz input. This audio is then amplified by Q<sub>2111</sub> (2SC945AP) and delivered to analog switch Q<sub>4002</sub> on the AF Unit for final audio amplification and output.

When no carrier is present to quiet the 455 kHz IF, noise present in the audio output from discriminator diodes  $D_{2101}$  and  $D_{2102}$  is passed through a high-pass filter and the Squelch control on the front panel, before amplification at  $Q_{2108}$  (2SC-945AQ) and one half of  $Q_{2109}$  (AN6552). The amplified noise is then detected by  $D_{2105}$  and  $D_{2106}$  (1S188FM), and the resulting DC is applied to  $Q_{2110}$  (2SC945AP), which grounds the base of  $Q_{2111}$  to prevent audio output to the AF Unit when no carrier is present.

A sample of the output from  $D_{2101}$  and  $D_{2102}$  is diverted through meter level trimmer  $VR_{2103}$  to the remaining half of  $Q_{2109}$ , which amplifies the discriminator output sample for discriminator center tuning indication on METER I. Regulated plus 8 volts for  $Q_{2109}$  is derived from the FM plus 13.5 V bus by  $Q_{2106}$  (2SC1959Y) and  $Q_{2107}$  (2SC945), and zener diodes  $D_{2103}$  (RD9.1EB2) and  $D_{2104}$  (RD8.2EB3).

#### TRANSMITTER

#### SSB

From the microphone or patch input the speech signal is amplified by Q<sub>4019</sub> (2SC732TMGR) on the AF Unit (PB-2252) and fed through the active high-pass filter, one half of dual op amp Q4020 (AN6552); and buffered by the other half of Q4020. The signal is now applied to balanced modulator Q4031 (MC1496CP), where it modulates the 9 MHz carrier signal from carrier buffer Q3009 (2SC945AP) on the Local Unit. The modulated sidebands are now fed into sideband filter XF4001 where the unwanted sideband is rejected. The remaining single sideband signal is then buffered by Q4032 (2SC945AP) and one portion delivered to the speech processor circuit on the IF Unit. The remaining portion of the signal is delivered directly to IF amplifier Q<sub>9032</sub> (3SK73GR) when the speech processor is switched off.

When the speech processor is on the signal is amplified by  $Q_{9029}$  (3SK73GR) and fed to RF clipper  $Q_{9030}$  (TA7060AP), from where it is passed through drive control buffer  $Q_{9033}$  (2SC945AP) to IF amplifier  $Q_{9032}$  (mentioned above). A sample of the compression signal at  $Q_{9029}$  is rectified by diodes  $D_{9045}$  and  $D_{9046}$ , amplified by  $Q_{9031}$  (2SC945AP) and delivered to METER I for the COMP indication.

From IF amplifier Q9032 the signal is passed through SSB crystal filter XF9005 and IF amplifier Q9034 (3SK73GR) to first transmit Q<sub>9035</sub> and Q<sub>9036</sub> (3SK73GR), where it is heterodyned with the 64 MHz signal from the LO The 73 MHz product of the mixer is delivered to the RF Unit and fed through 20 kHz BW filter XF<sub>1001</sub> and ALC amplifier Q<sub>1015</sub> (3SK73GR) to mixer Q<sub>1012</sub> (ND487C2-3R). Here the signal is heterodyned with the first local signal from the local amplifier, and the product at the desired output frequency is then amplified by Q1014 (2SC2407) and passed through one of the nine band-pass filters and the PIN diode attenuator, D<sub>1042</sub> through D<sub>1044</sub>, to equalize the output level of the final amplifier for each band.

From the attenuator the signal is amplified by RF amplifier transistors  $Q_{1010}$  and  $Q_{1011}$  (2N4427), which are used as the RF amplifier in receive, to deliver 100 mW to the 100 W PA Unit (PB-2321). Here the signal is amplified by  $Q_{8001}$  (2SC1589), followed by push-pull drivers  $Q_{8002}$  and  $Q_{8003}$  (2SC2395), and final push-pull power amplifiers  $Q_{8004}$  and  $Q_{8005}$  (2SC2290); and then delivered through the proper low-pass filter on the LPF Unit (PB-2259), the directional coupler  $L_{7101}$ , and antenna relay  $RL_{7101}$  on the ALC Unit (PB-2260) to the antenna.

#### CW

On the Local Unit (PB-2253), 24.4992 MHz crystal oscillator  $Q_{3019}$  (2SC945AP), whose frequency can be shifted by switches  $Q_{3015}$  through  $Q_{3018}$  (2SC945AP) controlled by FSK keying, has its output buffered by  $Q_{3020}$  (2SC945AP) before being fed to balanced mixer  $Q_{3008}$  (SN16913P). Also fed to the mixer is the shift and carrier oscillator signal of 15.5110 MHz generated at  $Q_{3013}$  (2SC945AP), switch shifted by  $Q_{3011}$  and  $Q_{3012}$  (2SC945AP), and two sections of  $Q_{3010}$  (MC-14066BCP); and buffered by  $Q_{3014}$  (2SC945AP).

The 8.9882 MHz resultant output of mixer  $Q_{3008}$  is then buffered by  $Q_{3009}$  (2SC945AP) and delivered to CW drive amplifier  $Q_{4029}$  (2SC945AP) on the AF Unit (PB-2252). After this the signal is buffered by  $Q_{4030}$  (2SC945AP) and delivered to IF amplifier  $Q_{9032}$  on the IF Unit before being filtered by crystal filter XF<sub>9005</sub>. The remainder of the signal path for the CW signal is identical to that of the SSB signal already described.

## **FSK**

The FSK keying signal is applied to crystal oscillator  $Q_{3019}$  via switches  $Q_{3015}$  through  $Q_{3018}$ , which cause the oscillator to produce a 24.502125 MHz signal for MARK and a 24.502295 MHz signal for SPACE. Shift and carrier oscillator  $Q_{3013}$  is directed through switches  $Q_{3011}$ ,  $Q_{3012}$  and two sections of  $Q_{3010}$  (controlled via the mode switch) to generate a signal at 15.5140 MHz. These are mixed to produce the carrier, filtered, and amplified in the same manner as CW.

## AM

The audio signal from the microphone is amplified by Q<sub>4019</sub> (2SC732TMGR) on the AF Unit (PB-2252) and fed through the high-pass filter, ½Q<sub>4020</sub> (AN6552), and through the buffer composed of the other half of Q<sub>4020</sub>; from where it is passed to limiter Q<sub>4036</sub> (TA7060AP). The signal is then buffered by Q<sub>4037</sub> (2SC945AP) and fed to AM modulator Q<sub>4038</sub> (MC1496CP). From the modulator the signal is fed through drive control amplifier Q<sub>4034</sub> (2SC945AP) and buffer Q<sub>4035</sub> (2SC-945AP) before being fed to IF amplifier Q<sub>9034</sub> (3SK73GR) on the IF Unit (PB-2255). The signal path is then the same as for SSB, with appropriate changes in the oscillator frequencies by the CPU to provide the correct LO signals at the mixers.

## FM

After amplification and high-pass filtering, the speech signal is delivered from Q4020 on the AF Unit to Q2112 (2SC945AP) on the FM Unit (PB-2254). Pre-emphasis is applied at Q2112 via C2150 and R2152, and the signal is then amplified by  $Q_{2113}$  (2SC945AP) and clipped at  $D_{2107}$  and  $D_{2108}$  (1SS53) to remove any amplitude peaks that would cause overdeviation. After clipping the signal is filtered at Q2114 (2SC945AP) and buffered by Q<sub>2115</sub> for application through deviation trimmer VR<sub>2105</sub> to modulating varactor D<sub>2109</sub> (FC63). D<sub>2109</sub> is located in the 8.9875 MHz VCXO circuit composed also of crystal X2102 and Q2116 (2SC-945AP), which is frequency modulated by the audio voltage on D2109. The resulting output is buffered by Q2117 and delivered from FM drive control VR<sub>2106</sub> to Q<sub>4034</sub> on the AF Unit, from where the signal follows the same path as that for AM transmission. Regulator  $Q_{2118}$  ( $\mu$ PC78L08) provides a separate 8 volt supply for the VCXO from the 13.5 VDC FM transmit bus.

## VOX, AMGC

A portion of the signal from the high-pass filter ½Q<sub>4020</sub> (AN6552) for the microphone audio on the AF Unit (PB2252) is fed to both halves of Q<sub>4006</sub> (AN6552). One half is used for the VOX amplifier, which controls switch Q<sub>4009</sub> (2SC-945AP), which in turn triggers one half of dual monostable multivibrator Q<sub>4008</sub> (MC14538BCP), also fed by the Break-in command from the front panel switch through switch Q<sub>4012</sub> (2SC-945AP) and by the anti-trip signal from the speaker through anti-trip switch Q<sub>4010</sub> and keying switch Q<sub>4011</sub> (both 2SC945AP) keyed by Q<sub>4016</sub>. The output of this half of Q<sub>4008</sub> is fed to the D<sub>4004</sub> through D<sub>4006</sub> diode gate (mentioned in the keying circuit description).

The remaining half of  $Q_{4006}$  is the AMGC amplifier, which feeds through switch  $Q_{4007}$  (2SC945AP) to the other half of  $Q_{4008}$ , the other monostable multivibrator. The output of this monostable is fed through one gate of  $Q_{4013}$ , a quad AND gate (MC14081B), and then switch  $Q_{4014}$  (2SC945AP) to third keying switch  $Q_{4016}$  (2SC945AP), mentioned in the keying circuit description.

#### KEYING

The keying command gate is one section of quad AND gate  $Q_{4013}$  (MC14081BCP) on the AF Unit (PB-2252). This gate is keyed by the signal from keying transistors  $Q_{4016}$ ,  $Q_{4017}$  and  $Q_{4018}$  (all 2SC945AP) which are fed by the Manual Key or optional Keyer Unit (PB-2262). The keying signal from  $Q_{4013}$  is then delivered to the Regulator Unit (PB-2258), where 3/6 of hex inverter  $Q_{7014}$  (MC14069UBCP) are used to delay the keying signal before passing through  $\frac{1}{4}$  of quad buffer  $Q_{7013}$  (MC14071BCP) to Transmit Bias Switch  $Q_{7020}$  (2SA733Q).

A portion of the signal from keying transistor  $Q_{4016}$  on the AF Unit is fed to another ¼ of quad AND gate  $Q_{4013}$ , which is also fed by the Break-in control switch from the front panel, and which switches the diode gate  $D_{4004}$ ,  $D_{4005}$ ,

and D<sub>4006</sub> (1SS53); along with the PTT signal through Q<sub>4015</sub> (2SC945AP) and the VOX signal mentioned earlier. This diode gate delivers the VOX/PTT signal to the Control Unit (PB-2251), and also feeds a signal through switches Q<sub>2202</sub> and Q<sub>2201</sub> (2SC945P) connected together by a jumper at the External Control Unit (PB-2238) to the keying command gate of Q<sub>4013</sub> mentioned above.

This signal from the diode gate is also limited at another ¼ of Q<sub>4013</sub> by the TX DISABLE command from the Control Unit. The keying command gate portion of Q<sub>4013</sub> also has a third input from the PLL Unit (PB-2257). Additional keying-related circuitry is covered in the RX MUTE/TX DELAY circuit description.

## SIDETONE

Sidetone oscillator  $Q_{4021}$  (2SC945AP) on the AF Unit (PB-2252) feeds its signal through sidetone keying switch  $Q_{4022}$  (2SC945AP) (keyed by a portion of the output of the third keying transistor,  $Q_{4016}$ ) and buffer  $Q_{4023}$  (2SC945AP) to both the VOX amplifier portion of  $Q_{4006}$  and switch  $Q_{4026}$  (2SC945AP).  $Q_{4026}$  then passes the sidetone signal on to AF power amplifier  $Q_{4028}$ .

## RECEIVER MUTE, TRANSMIT DELAY (QSK)

From the Control Unit (PB-2251) the TX Signal switching command is delivered to the sequential delay gates on the Regulator Unit (PB-2258), composed of quad OR gate Q<sub>7013</sub> (MC14071B), and also the same half of hex inverter Q<sub>7014</sub> mentioned earlier in the Keying Circuit description controlling the Transmit Bias switching. Of Q<sub>7013</sub>'s delay gates, one set controls the Transmit Zero Voltage Reference Switch, Q<sub>7011</sub> (2SC945AQ), which in turn controls Relay Drivers Q<sub>7025</sub> (2SA733Q) and Q<sub>7026</sub> (2SA719Q) to the antenna relay. This set of gates also controls the Receiver Zero Voltage Reference Switch, Q<sub>7012</sub> (2SC945AQ).

The other set of delay gates in  $Q_{7013}$  controls drivers  $Q_{7017}$  and  $Q_{7018}$  (2SC945AQ) to Receiver 13.5V Switch  $Q_{7019}$  (2SB772Q); driver  $Q_{7021}$  (2SC945AQ) to Transmitter 13.5V Switch  $Q_{7022}$  (2SB536K); Receiver Bias Switch 1,  $Q_{7016}$  (2SA-733Q); and Receiver Bias Switch 2,  $Q_{7015}$  (2SA733Q).

## **REGULATOR UNIT (PB-2258)**

In addition to the Mute and Delay circuitry, the Regulator Unit contains the minus 8 V supply, derived from 13.5 V through DC-DC Converter  $Q_{7023}$  (2SC2002L) and Regulator  $Q_{7024}$  (MC-7908CT). The 13.5 VDC output of Power Supply Unit PS1 is also fixed by Regulator  $Q_{7027}$  ( $\mu$ PC78L05) to provide plus 5 V, by  $Q_{7010}$ (μPC78L08) to provide plus 8 V, through Power Switch S<sub>2</sub> to Switch Driver Q<sub>7003</sub> (2SC945AQ) to Switch Q<sub>7001</sub> (2SA733Q) and then to Regulator Q<sub>7002</sub> (2SD882Q) to provide plus 8 V; and also through Switch Q7007 (2SC945AQ) to Regulator Q<sub>7006</sub> (2SB536K) providing plus 11 V to the PLL, a portion of which is fed through an Error Amplifier, Q<sub>7008</sub> and Q<sub>7009</sub> (2SC945AQ), and back to Q<sub>7007</sub>.

Power Supply PS2 provides 8 V for memory backup through power transformer PT1 and bridge rectifier  $D_{7001}$  (S2VB10), delivering 12 V to the 13.5 V bus when the POWER Switch is off. This 12 V is regulated by  $Q_{7004}$  (2SC2562Y) and  $Q_{7005}$  (2SC945AQ) to provide PS2 plus 8 V.

## PLL CIRCUITS

The PLL system is composed of four loops, each consisting of a VCO, prescaler, crystal oscillator reference signal, programmable divider and a phase detector. Synthesized signal frequencies are thus produced for the local signals for transmitter and receiver stages, using 10 Hz steps. In PLL4, the VCO to be used is selected by the microprocessor in the Control Unit, which chooses one of 6 VCOs, each covering a 5 MHz portion of the 30 MHz range of the First Local signal. PLL1 is located on the Local Unit, but is functionally an integral part of the rest of the PLL circuitry located on the PLL Unit.

## **PLL Circuit Configuration**

The 73.115 MHz–102.11499 MHz First Local signal is generated by one of the six VCO's composed of  $Q_{6001}$ – $Q_{6006}$  (2SC1923-O) selected for the desired 5 MHz portion of the frequency range by the microprocessor on the Control Unit. This signal from the VCO is buffered by  $Q_{6008}$  (2SC1923-O) and  $Q_{6007}$  (2SC2026) before being

delivered to the RF Unit (PB-2256), where it is buffered further by  $Q_{1016}$  (2SC1923-O) and  $Q_{1017}$  (2SC2026), and amplified by  $Q_{1018}$  (2SC2407) and  $Q_{1019}$  (2SC1589) before being delivered to the mixer.

A portion of the signal from the selected VCO is also amplified by  $Q_{6009}$  (3SK74L) and fed to the mixer composed of  $Q_{6016}$  and  $Q_{6017}$  (2SK206-3), where it is mixed with the 105.115 MHz–106.11499 MHz signal from PLL3. The resulting 3 to 32 MHz output of the mixer is buffered by  $Q_{6018}$  (2SC1923-O), amplified by  $Q_{6019}$  (2SC2026), and buffered again by  $Q_{6020}$  (2SC1923-O) and  $Q_{6021}$  (2SC2407) before being applied to the Programmable Divider composed of  $Q_{6011}$  (SN-74S113N),  $Q_{6012}$  (SN74S11N),  $Q_{6013}$  (SN74LS-196N) and  $Q_{6015}$  (SN74LS196N); which is programmed by ROM  $Q_{6014}$  (TBP18SA030N-0376), fed with the 10 MHz and 1 MHz binary data from the Control Unit.

Thus the Programmable Divider feeds a 1 MHz signal to Phase Detector  $Q_{6022}$  (MC4044P), which also receives a 1 MHz reference from Reference Amplifier  $Q_{6026}$  (2SC945AQ). 20.0 MHz crystal reference oscillator  $Q_{6062}$  (2SC535B) feeds a portion of its signal through buffer  $Q_{6061}$  (JF-1033B) to 1/20 divider  $Q_{6060}$  (HD10551), a portion of whose output provides 1 MHz to  $Q_{6026}$ .

The Error Correcting DC voltage from the Phase Detector is then fed through the low-pass filter composed of Q<sub>6023</sub> through Q<sub>6025</sub> (2SC732BL) before being applied back to the selected VCO, Q<sub>6001</sub> to Q<sub>6006</sub>. Q<sub>6010</sub> (2SD882Q) and Q<sub>6065</sub> (2SC1959Y) each serve as Regulators to provide 5 V and 8 V respectively to the loop mentioned above (PLL4) from the 11 V supplied to the PLL Unit.

In PLL3, a 105 MHz signal is generated at VCO3, Q<sub>6029</sub> (2SC1923-O), from where it is amplified by Q<sub>6028</sub> (3SK74L) before being fed to the mixer in PLL4. A portion of the output of VCO3 is buffered by Q<sub>6027</sub> (2SC945AQ) and applied to doubly balanced mixer Q<sub>6043</sub> (SN76514N), which also receives a 48.615 MHz signal through buffer Q<sub>6042</sub> (2SC945AQ) from crystal oscillator Q<sub>6041</sub> (2SC-535B). The 56.50 MHz-57.4999 MHz output of the mixer is then buffered by Q<sub>6039</sub> (2SC945AQ) and applied to doubly balanced mixer Q<sub>6038</sub> (SN16913P), which also receives a 56.280 MHz-57.27009 MHz signal from PLL2.

The 220.0 kHz-229.9 kHz output from this mixer is then buffered by Q6037 before being fed to the phase detector, Q6034 (MC4044P). This phase detector also receives a 220.0 kHz-229.9 kHz signal derived from the 22.0 MHz-22.99 MHz signal delivered to the PLL Unit from PLL1 on the Local Unit, after it is amplified by Q6032 (2SC-1923-O) and divided by 100 at Q6033 (SN74LS-390N). The DC output from the phase detector is fed to inverter Q6035 (SN74LS26N), which produces an Unlock signal if the PLL is not locked, and passes the Error Correcting Voltage to Switch Q6036 (MC14066B). This switch then passes the voltage on through a low-pass filter back to VCO3. 48.615 MHz crystal oscillator Q6041 has another output through buffer Q6044 (2SC945AQ) which is delivered to the Local Unit.

In PLL2, a 56.280 MHz-57.27009 MHz signal is generated at VCO2, Q<sub>6048</sub> (2SC1923-O), from where it is buffered by Q<sub>6050</sub> (2SC945AQ) before being fed to mixer Q<sub>6038</sub> in PLL3. A portion of the output of VCO2 is buffered by Q<sub>6049</sub> (2SK-19TMGR) and applied to doubly balanced mixer Q<sub>6053</sub> (SN16913P), which is also fed with a 54.280 MHz-54.28009 MHz signal from VCXO Q<sub>6051</sub> (2SC535B), buffered by Q<sub>6052</sub> (2SC945AQ). The VCXO frequency is controlled by the 10 Hz BCD Data from the Control Unit, through Digital-to-Frequency Converter D<sub>6028</sub> (1T25).

The 2.0 MHz-2.99 MHz output of the mixer is amplified by Q6054 (2SC945AQ) and fed to programmable divider/phase detector Q6055 (MB-8718M), which also receives a 10 kHz reference signal derived from the 20.0 MHz Reference Oscillator Q<sub>6062</sub>, through Q<sub>6061</sub> and 1/20 Divider Q<sub>6060</sub> mentioned as the 1 MHz reference in PLL4, which is further divided by 100 at Q<sub>6059</sub> (MC14518B) to provide this 10 kHz reference and also the 10 kHz reference for PLL1 on the Local Unit. Q6055 also receives the 100 kHz and 10 kHz BCD Data delivered from the Control Unit. A PLL Unlock signal from Q<sub>6055</sub> connects with the Unlock signal from PLL3 and is delivered to the Control Unit. The DC Error Correcting Voltage from Q6055 is fed through low-pass filters Q6046 (2SC732TMBL) and Q6047 (MPS-A13) back to VCO2.


PLL1 is located on the Local Unit (PB-2253). Its 22.0 MHz–22.99 MHz output is generated at VCO1, Q<sub>3034</sub> (JF1033B), and then buffered by Q<sub>3035</sub> (2SK19TMGR) before being delivered to amplifier Q<sub>6032</sub> (mentioned in PLL3) on the PLL Unit. A portion of the output of VCO1 is buffered by Q<sub>3033</sub> (2SK19TMGR) on the Local Unit and applied to doubly balanced mixer Q<sub>3032</sub> (SN-16913P), which also receives a 20.0 MHz signal from 20.0 MHz Reference Oscillator Q<sub>6062</sub>, buffered by Q<sub>6063</sub> (JF1033B) before being delivered from the PLL Unit.

The 2.0 MHz-2.99 MHz output from the mixer is amplified by Q<sub>3031</sub> (2SC945AP) and applied to programmable divider/phase detector Q<sub>3030</sub> (MB-8718M), which also receives a 10 kHz reference signal through Reference Amplifier Q<sub>3027</sub> (2SC-


945AP) after being delivered from 1/100 Divider  $Q_{6059}$  on the PLL Unit.  $Q_{3030}$  also receives 1 kHz and 100 Hz data delivered from the Control Unit, while the Unlock signal from  $Q_{3030}$  is delivered to the Control Unit together with the Unlock signals from PLL3 and PLL2 on the PLL Unit. The DC Error Correcting Voltage from  $Q_{3030}$  is fed through a low-pass filter composed of  $Q_{3028}$  and  $Q_{3029}$  (2SC732TMBL) before being fed back to VCO1.  $Q_{3026}$  (2SC945AP) is used as an 8 V regulator to provide DC for PLL1 on the Local Unit from 13.5 V.

On the PLL Unit,  $Q_{6057}$  (2SC945AQ) and  $Q_{6058}$  (2SC1959Y) act as 5 V regulators from the 11 V supply bus; while  $Q_{6040}$ ,  $Q_{6045}$  (2SC1959Y) and  $Q_{6030}$  and  $Q_{6064}$  (2SC945AQ) act as 8 V regulators from the 11 V.

## PLL CIRCUIT FREQUENCY RELATIONSHIPS



## FT-ONE FREQUENCY RELATIONSHIPS



### FREQUENCY RANGE MODIFICATION

The following information will allow you to change the transmitting and receiving frequencies of the FT-ONE to conform with local requirements.


- Remove the CONTROL UNIT from the FT-ONE.
- Referring to Figures 1 and 2 (following page), note that connecting a jumper wire from Point A to either Point B or C sets the receiving frequency range; while connecting another jumper wire from Point D to Point E, F, G or H sets the transmitting frequency range.
- 3. Solder the jumper wires to the appropriate points, selected from the Table below.
- The example shown in Figure 3 illustrates how to set the receiver coverage for 150 kHz through 29.9999 MHz and the transmitter coverage for the new WARC bands.


## RECEIVING FREQUENCY RANGE SETTING CHARI

Range:	Jumper Connection: A - C	
150 kHz - 27 MHz, 28 MHz - 30 MHz (no 11 meter band)		
150 kHz - 30 MHz	A – B	

## TRANSMITTING FREQUENCY RANGE SETTING CHART

Range:	Jumper Connection
1.8 - 2 MHz; 3 - 4 MHz; 7 - 8 MHz; 10 - 11 MHz; 14 - 15 MHz; 18 - 19 MHz; 21 - 22 MHz; 24 - 25 MHz; 27 - 30 MHz (WARC plus 11 meter band)	D – E
1.8 - 2 MHz; 3 - 4 MHz; 7 - 8 MHz; 10 - 11 MHz; 14 - 15 MHz; 18 - 19 MHz; 21 - 22 MHz; 24 - 25 MHz; 28 - 30 MHz; (WARC)	D - F
1.8 - 2 MHz; 3 - 4 MHz; 7 - 8 MHz; 14 - 15 MHz; 21 - 22 MHz; 27 - 30 MHz (11 meters, no WARC)	D – G
1.8 - 2 MHz; 3 - 4 MHz; 7 - 8 MHz; 14 - 15 MHz; 21 - 22 MHz; 28 - 30 MHz (no 11 meters, no WARC)	D – H
1.8 – 30 MHz	No connection






Receive : General coverage ( Jumper 1 : A-B )


Transmit: WARC (Jumper 2:D-F)

Figure 3


## **QSK Operation** Using the FT-ONE and a Full Break-in Linear Amplifier

To guard against accidental damage to non-QSK amplifiers, the FT-ONE is wired at the factory with the FLN-1 and FLN-2 lines (pins 6 and 7 on the ACC-1 jack) jumpered together. Therefore, to operate a QSK amplifier with the FT-ONE it is necessary to cut this jumper, located on the EXT Cont Unit, PB-2338, PB-2367 or PB-2367A. This Unit is attached to the bottom of the chassis just beneath the LPF Unit, and is accessible by removing the bottom cover. (On some Units there is no silk screening on the circuit board). The location of the jumper to be cut is illustrated in the Figure.






PB-2338



PB-2367/A

Connect the ACC-1 and ANT jacks on the FT-ONE to the jacks on the ALPHA 78 as shown in the diagram.




## FT-ONE RECEIVER STABILITY IMPROVEMENT MODIFICATIONS

If your FT-ONE has a serial no. beginning with 01 or 02, you must ensure that a TX carrier oscillator sub-board is attached to the Local Unit before making the following modifications. If the sub-board is not attached and your dealer has not already contacted you, please contact the firm from whom you purchased your FT-ONE immediately.

The following modifications can improve receiver stability in many FT-ONEs having serial nos. beginning with 01 through 03, and some beginning with 04 and 05. Some 01 through 05 lot units have already been modified, as have all units with serial nos. 06 and above. Modification A must be performed first, and then Modification B, if needed. If either modification appears too difficult after reading through the procedure (before beginning), contact your dealer for assistance.

### A. Width Oscillator Modification

- Remove the IF Unit (PB-2255 or PB-2255A) and locate the Width Oscillator Circuit enclosed with a metal shield. Referring to the figure below, locate transformer T<sub>10</sub>. If this is the only transformer in the Width Oscillator enclosure, Modification A has already been performed.
- Remove the shield on the solder side of the board, and then remove those components noted on the following figure.



IF unit

Viewed from component side


### Remove

C9062	D9024	R9082	T9009	TC9001	X9001
C9064		R9083	T9010		
C9065		R9084			
C9066		R9086			
C9067					
C9068					
C9069					


Install the following parts on the board according to the figure on the following page.


Circuit	Type or Value	Part Number
Designatio	on	
D9055	FC-52M5 varactor	G2090165
X9001	19.7475 MHz xtal	H0102470
R9085	10K ohm resistor	J02245103
R9086	12K ohm resistor	J02245123
R9214	10K ohm resistor	J01245103
R9215	22K ohm resistor	J10246223
C9068	47 pF CH cap	K02175470
C9069	100 pF CH cap	K02175101
C9201	62 pF UJ cap	K06179010
TC9001	40 pF trimmer	K91000096
L9060	FL5H151K	L1190020
T9010	transformer	L0021267

- Remove the Local Unit (PB-2253/PB-2253A), and remove the shield covers from each side. Locate R<sub>3090</sub> and R<sub>3091</sub>, and replace each of these resistors with 560K ohm resistors (part no. J02245564) as shown below.
- 5. Replace the shields on the Local Unit and the IF Unit, and reinstall these boards in the FT-ONE. Align the new Width Oscillator as follows:
  - a. Set the Width and Shift controls on the front panel to their center positions, and connect a frequency counter to TP<sub>9001</sub> on the IF Unit.
- b. Adjust TC<sub>9001</sub> for a frequency of 19.7475 MHz on the counter. If TC<sub>9001</sub> cannot tune this frequency, install a service extender board on the IF Unit and adjust T<sub>9010</sub> for the correct frequency.



Viewed from component side





## Note:


\* R<sub>86</sub> should be installed opposite to the printed indication on the board.

Boldface wiring indicates interconnection with component lead.

The lead of  $R_{215}$  nearest  $X_{01}$  should be soldered to the case of the crystal.

The crystal has three leads, but the center lead is not used and should be cut.


## Width Oscillator Schematic After Modification



## B. Shift Oscillator Modification

Modification A must be performed first.


 Referring to the next two figures, remove the components from Local Unit PB-2253 or PB-2253A indicated. Note that the area around  $C_{57}$  differs on PB-2253 from PB-2253A. The modification, however, is the same.




PAQ -1 + CO8	C3055	R3046	T3005
TO SALE CITY OF THE COLOR OF TH	C3056	R3048	T3006
91+ C07	C3057	R3053	
12 th	C3058	R3055	TC3001
C4B	C3059	R3056	
	C3061	R3057	VR3002
Lower (Contact) Edge		R3059	
	D3007	R3060	X3002

Circuit	Type or Value	Part Number
Designatio	n	
D3024	FC52M5 varactor	G2090165
X3002	15.514 MHz xtal	H0102471
R3046	560 ohm resistor	J02245561
R3048	2.7K ohm resistor	J02245272
R3053	8.2K ohm resistor	J02245822
R3055	2.2K ohm resistor	J02245222
R3057	6.8K ohm resistor	J02245682
R3059	220 ohm resistor	J02245221
R3060	680 ohm resistor	J02245681
*R3090	270K ohm resistor	J02245274
*R3091	270K ohm resistor	J02245274
R3156	10K ohm resistor	J01245103
R3157	10K ohm resistor	J01245103
VR3002	20K ohm (B) pot.	J50749203
C3055	39 pF UJ cap.	K06175390
C3058	47 pF UJ cap.	K06175470
C3059	100 pF UJ cap.	K06175101
C3061	7 pF CH cap.	K02173070
C3164	47 pF CH cap.	K02175470
TC3001	40 pF trimmer	K91000096
T3005	transformer	L0021271

- Install the following parts on the board according to the figures on the following page.
  - \* These were changed once in Modification A, but must be changed again for Modification B.
- Align according to the procedure on pages 3-12 and 3-13.







## SECTION 3-SERVICING


OUTER COVER REMOVAL
BOARD LAYOUT
FRONT PANEL REMOVAL
REAR PANEL REMOVAL
ALIGNMENT
PARTS LAYOUT AND CIRCUIT DIAGRAM 3-2
RF UNIT (PB-2256)
SENSOR UNIT (PB-2265)
IF UNIT (PB-2255)
AF UNIT (PB-2252)
KEYER UNIT (PB-1728A)
LOCAL UNIT (PB-2253)/TX CAR OSC UNIT (PB-2400)
CONTROL UNIT (PB-2251)
RAM BOARD UNIT (PB-2267)
PLL UNIT (PB-2257)
100W PA UNIT (PB-2321)
DIODE SW UNIT (PB-2266)
ALC UNIT (PB-2260)
REG UNIT (PB-2258)
LPF UNIT (PB-2259)
PUSH SW UNIT (PB-2264)
LEVER SW UNIT (PB-2263)
KEYBOARD UNIT (PB-2262)
EXT CONTROL UNIT (PB-2367A)
DISPLAY UNIT (PB-2261)
FM UNIT (PB-2254)
SOLDERING AND DESOLDERING TECHNIQUE 3.70

# **OUTER COVER REMOVAL**







**TOP VIEW** 




BOTTOM VIEW



# **REAR PANEL REMOVAL (1)**



# **REAR PANEL REMOVAL (2)**



## ALIGNMENT

The following Alignment Procedure for the FT-ONE is divided into two separate sections. The first section covers the various alignments and adjustments that may be made by the owner, as these do not require sophisticated test equipment outside of the FT-ONE itself and standard tools and equipment normally found in the ham shack. The second alignment section covers the sometimes critical and tedius adjustments, which must not be performed without the proper test equipment conforming to the specifications called for in the test equipment list. If you do not have, or are not familiar with this test equipment; or have any doubts about its use in these specific applications, you should not attempt any of the alignment procedures in this section. Unless you are experienced with alignment of these types of circuits and thoroughly understand their operation, let the alignments covered in the second section be performed by your authorized Yaesu dealer's service department.

Every FT-ONE has been completely aligned at the factory prior to shipment. However, your particular operating environment may call for some readjustments, such as VOX, Anti-trip, Monitor Volume, or Sidetone Pitch. Yaesu's design engineers have made a special effort to make these controls, and all of the adjustments that might require readjustment due to shipping and environmental variations, readily accessible to the user through the plastic circuit board cover under the cabinet's top cover. Under normal use, no other alignment should be necessary. Service or realignment of a major component may require substantial adjustment; under no circumstances, though, should realignment be attempted unless the operation of the transceiver is fully understood, the malfunction has been carefully analyzed, and the fault has definitely been traced to misalignment. Sudden difficulties are almost always caused by component failure rather than misalignment.

## SECTION I

The following adjustments can be made by removing the top cover of the FT-ONE. The controls are labelled on the plastic cover over the pc boards, and can be adjusted with a small screwdriver. You will need to have on hand a microphone, CW key, headphones and, for the Carrier Balance adjustment, an external receiver in order to make these adjustments.


## A. VOX Anti-Trip Level

- Preset the transceiver front panel controls for normal SSB operation, but with the DRIVE control set to minimum. Tune in a station on the receiver, and set the AF GAIN for a comfortable listening level.
- Preset the ANTI-TRIP control, VR<sub>4003</sub>, fully counter-clockwise (minimum). Place the microphone near to the loudspeaker (do not activate the PTT).
- Rotate the VOX GAIN control on the front panel gradually clockwise from its counterclockwise (minimum) position just to the point where the transmitter is activated.
- Gradually rotate the ANTI-TRIP control, VR<sub>4003</sub>, clockwise to the point where the transmitter ceases to be activated by the audio from the loudspeaker.
- Now retune the transceiver to a clear frequency and speak into the microphone to ensure that the VOX activates the transmitter properly.

## B. AMGC (Automatic Mic Gain Control) Sensitivity

This control has been preset at the factory to cause the AMGC to pass on to the transmitter any signal presenting at least 1 mV (at 1 kHz) to the microphone jack. It may need to be readjusted to accommodate the particular microphone in use.

- Preset the front panel controls for normal SSB transmission.
- Close the PTT switch and speak into the microphone at normal volume, incorporating pauses in your speaking to allow the opportunity for the AMGC to trigger.
- Adjust AMGC GAIN control VR<sub>4001</sub> so that transmitter output appears on the meter when speaking.



## C. AMGC Delay


This control is preset at the factory to allow a 1 second delay (pause) before squelching off the audio from the microphone to the transmitter.

 Depress the PTT switch and speak into the microphone as above while adjusting the AMGC DELAY control, VR<sub>4002</sub>, for the desired delay after having stopped speaking, or during a long pause.

## D. CW Sidetone Pitch

- Set the MODE selector on the front panel to one of the CW positions, and key down.
   Switch ON the MONI lever so that the sidetone is audible.
- Adjust SIDETONE PITCH control VR<sub>4004</sub> for the desired audio frequency. See page 26 of the Operating Manual for CW Spot calibration.





AF UNIT (PB-2252)
ALIGNMENT POINTS (SECTION I)

#### E. Sidetone Level

This control is preset at the factory to present a 60 mW signal to the speaker.

 Using the same setup as in the previous adjustment, adjust LEVEL control VR<sub>4005</sub> to your desired volume.

## F. SSB Monitor Level

This control is preset at the factory so that, with the MIC GAIN control on the front panel set to maximum and a 0.5 mV, 1 kHz signal applied to the MIC jack, 60 mW of audio is presented to the speaker. For this adjustment, use headphones to monitor the transceiver so as to avoid feedback from the speaker to the microphone.

- Set the MONI switch ON, and the MODE selector to LSB.
- Depress the PTT switch and speak into the microphone while adjusting MONI LEVEL control VR<sub>4006</sub> for a comfortable volume in the headphones.

### G. Carrier Balance

- Set the MODE selector to USB and tune the transceiver to the 14 MHz band.
- Set the MIC GAIN control fully counterclockwise (minimum), and disconnect the microphone from the MIC jack.
- Set the VOX control fully counter-clockwise and into the click stop (MOX) position.
- Tune an external receiver to the same frequency as the FT-ONE, and adjust CARRIER BALANCE control VR<sub>4008</sub> for minimum signal at the external receiver.
- Switch the MODE selector to LSB, and repeat step 4.
- Switch back and forth from LSB to USB several times while adjusting VR<sub>4008</sub> to obtain an equal minimum output in the two modes.

#### SECTION II

Those procedures marked with an asterisk (\*) require the use of the optional Extender Board, which is available from Yaesu dealers.

## SERVICE EXTENDER KIT

### EXTENDER BOARD

14P	Single face	(D3100002)
18P	Double face	(D3100010)
22P	Double face	(D3100009)
18Px2	Double face	(D3100011)
EXTENDER	CABLE	(T9204357)








D3100002

D3100010

D3100009



D3100011



T9204357

## ALIGNMENT EQUIPMENT REQUIRED

The following precision test equipment is required for the alignment procedures in this section:

Frequency Counter

YC-500E (YAESU) or equivalent

Signal Generator

HP 8640B (Hewlett Packard) or equivalent

DC Voltmeter

HP 4304B

VTVM with RF probe HP 3406A (Hewlett Packard) or equivalent AF VTVM **HP 400E** In-line Wattmeter Bird 43 Dummy Load (200 W) Bird 8343-200 Oscilloscope HP 1222A (Hewlett Packard) or equivalent Spectrum Analyzer HP 141T 8552B 8553B Distortion Meter HP 334A Audio Generator HP 200CD Linear Detector HP 8901A 25 ohm Dummy Load DC Ammeter (20 A)

#### **COMMON CIRCUITS**

#### PLL CIRCUIT


Set the FINE key OFF (out) to provide 100 Hz PLL steps.

#### (1) PLL Reference Oscillator (20 MHz)

- a) Connect the RF probe of the voltmeter and the frequency counter to pin 27 of edge connector MJ8 or J6005 pin 2.
- b) Adjust  $T_{6022}$  for a reading of 160 to 240 m $V_{rms}$  on the meter.
- c) Adjust trimmer  $TC_{6003}$  for 20 MHz ± 100 Hz on the counter.

## (2) PLL Reference Oscillator (48.615 MHz)

- a) Connect the RF probe of the voltmeter and the frequency counter to pin 31 of edge connector MJ8 or J6007 pin 2.
- Adjust T<sub>6017</sub> for maximum deflection on the meter (100 to 160 mV<sub>rms</sub>).
- c) Adjust trimmer  $TC_{6001}$  for 48.615 MHz  $\pm$  0.5 kHz on the frequency counter.



VTVM with RF probe HP 3406A (Hewlett Packard) or equivalent AF VTVM **HP 400E** In-line Wattmeter Bird 43 Dummy Load (200 W) Bird 8343-200 Oscilloscope HP 1222A (Hewlett Packard) or equivalent Spectrum Analyzer HP 141T 8552B 8553B Distortion Meter HP 334A Audio Generator HP 200CD Linear Detector HP 8901A 25 ohm Dummy Load DC Ammeter (20 A)

#### COMMON CIRCUITS

#### PLL CIRCUIT


Set the FINE key OFF (out) to provide 100 Hz PLL steps.

#### (1) PLL Reference Oscillator (20 MHz)

- a) Connect the RF probe of the voltmeter and the frequency counter to pin 27 of edge connector MJ8 or J6005 pin 2.
- b) Adjust  $T_{6022}$  for a reading of 160 to 240 m $V_{rms}$  on the meter.
- c) Adjust trimmer  $TC_{6003}$  for 20 MHz ± 100 Hz on the counter.

## (2) PLL Reference Oscillator (48.615 MHz)

- a) Connect the RF probe of the voltmeter and the frequency counter to pin 31 of edge connector MJ8 or J6007 pin 2.
- Adjust T<sub>6017</sub> for maximum deflection on the meter (100 to 160 mV<sub>rms</sub>).
- c) Adjust trimmer  $TC_{6001}$  for 48.615 MHz  $\pm$  0.5 kHz on the frequency counter.



#### (3) PLL Local Oscillator (54.28 MHz)

- a) Connect the RF probe of the voltmeter and the frequency counter to the hot lead of resistor R<sub>6190</sub>.
- b) Adjust  $T_{6021}$  for maximum deflection on the meter (100 to 160 mV  $_{rms}$ ).
- Adjust trimmer TC<sub>6002</sub> for 54.28 MHz ± 100 Hz on the counter.

## \*(4) VCO1 (22.0 to 22.99 MHz)

VCO1 is located on the Local Unit.

- a) Connect the DC voltmeter to TP<sub>3004</sub> on the Local Unit.
- Set the transceiver frequency to exactly 10.0000 MHz.
- c) Adjust  $T_{3013}$  for 6.0 V ± 0.25 V on the meter.
- d) Now set the transceiver frequency to 10.0099 MHz, and check that the voltmeter reads approximately 3.6 V.
- e) Connect the RF probe of the voltmeter to pin 35 of edge connector MJ8, and check that the RF voltmeter shows 40 to 80 mV<sub>rms</sub>.

#### (5) VCO2 (56.280 to 57.270 MHz)

- a) Connect the DC voltmeter to the lead of R<sub>6159</sub> that connects to the collector of Q<sub>6047</sub>.
- Set the transceiver frequency to 10.0000 MHz.
- c) Adjust  $T_{6020}$  for 5.5 V  $\pm$  0.25 V on the meter.
- d) Now set the frequency to 10.9999 MHz and check that the voltmeter reads approximately 4 V.

#### (6) VCO3 (105.115 to 106.11499 MHz)

- a) Connect the DC voltmeter to the lead of  $R_{6127}$  that connects to  $R_{6123}$ , and connect the frequency counter to the source of  $Q_{6016}$ .
- b) With the transceiver frequency set to 10.9999 MHz, adjust T<sub>6016</sub> for 6.0 V on the meter. Check that the counter shows approximately 106.115 MHz.
- Set the transceiver frequency to 10.0000 MHz.

- d) Check that the voltmeter reads approximately 4.7 V, and that the counter reads 105.115 MHz.
- Now disconnect the frequency counter and connect the RF probe of the voltmeter to the same point.
- f) Set the frequency to 0.5000 MHz and adjust T<sub>6015</sub> for maximum deflection on the RF voltmeter (nom.: 1.0 ± 0.3 Vrms).

#### (7) VCO4 (73.115 to 102.11499 MHz)

- Connect the DC voltmeter to either lead of R<sub>6089</sub>.
- Set the transceiver frequency to 4.9999 MHz and adjust T<sub>6004</sub> for 7.0 V on the meter.
- Set the frequency to 0.0000 MHz and check that the meter shows approximately 2.4 V.
- d) Now set the frequency to 9.9999 MHz and adjust  $T_{6005}$  for 7.0 V on the meter.
- Set the frequency to 5.0000 MHz and check for a reading of approximately 2.2 V on the meter.
- f) Set the frequency to 14.9999 MHz and adjust T<sub>6006</sub> for a reading of 7.0 V on the meter.
- g) Set the frequency to 10.0000 MHz and check that the meter shows approximately 2.6 V.
- h) Set the frequency to 19.9999 MHz and adjust T<sub>6003</sub> for a reading of 7.0 V on the meter.
- Set the frequency to 15.0000 MHz and check that the meter shows approximately 2.8 V.
- j) Set the frequency to 24.9999 MHz and adjust T<sub>6002</sub> for a reading of 7.0 V on the meter.
- Set the frequency to 20.0000 MHz and check that the meter shows approximately 2.4 V.
- Set the frequency to 29.9999 MHz and adjust T<sub>6001</sub> for a reading of 7.0 V on the meter.
- Set the frequency to 25.0000 MHz and check that the meter shows approximately 2.5 V.

#### (8) First Local LPF

- a) Connect the RF probe of the voltmeter to pin 1 of J<sub>6002</sub> and set the transceiver to 29.9999 MHz.
- Adjust T<sub>6007</sub> -T<sub>6009</sub> for maximum deflection on the meter.

#### (9) 10 kHz Reference Signal

a) Connect the RF probe of the voltmeter to pin 32 of edge connector MJ8, and check that  $420 \pm 100$  m  $V_{rms}$  is shown on the meter.

#### LOCAL CIRCUIT

Before commencing with these procedures the WIDTH and SHIFT controls must be set to the center position.

#### (1) Carrier Oscillator (24.5 MHz)


- a) Connect the frequency counter to TP<sub>3006</sub> on the Local Unit, and set the MODE selector to the FSK position and the VOX control to the MOX position. Short the FSK jack on the rear panel.
- Adjust VR<sub>3007</sub> for 24.502295 MHz on the counter.
- c) Remove the short on the FSK jack and adjust VR<sub>3006</sub> for 24.502125 MHz on the counter.
- d) Now switch the VOX control to PTT (receive) and switch the MODE selector to a CW position.

- e) Adjust VR<sub>3004</sub> for 24.5 MHz ± 100 Hz on the counter.
- f) Set the VOX control to the MOX position, and adjust VR<sub>3005</sub> for 24.4992 MHz ± 100 Hz on the counter. Return the VOX control to the PTT position.

#### (2) Carrier Oscillator (15.5 MHz)

Note that the alignment for production lots 001 through 005 is slightly different than for prod. lot 6 and later lots. Alignment information particular to the earlier models is indicated by a double asterisk (\*\*).

- a) Connect the frequency counter to  $TP_{3002}$  on the Local Unit.
- b) Set the MODE selector to the LSB position and adjust trimmer TC<sub>3002</sub> (\*\*TC<sub>3001</sub>) for 15.5140 MHz ±100 Hz on the counter. (\*\*On Lots 001 through 005 the adjustment range of TC<sub>3001</sub> may be insufficient to obtain this frequency, in which case the Local Unit should be raised with the extender card and T<sub>3005</sub> adjusted for this frequency. It is not necessary to readjust TC<sub>3001</sub> afterward.)



- c) Set the MODE selector to the USB position and adjust TC<sub>3001</sub> (\*\*VR<sub>3003</sub>) for 15.5110 MHz ±100 Hz on the counter.
- d) Set the MODE selector to the AM position and adjust VR<sub>3002</sub> for 15.5125 MHz ±100 Hz on the counter.
- e) Set the MODE selector to the LSB position, key the transmitter, and adjust VR<sub>3001</sub> (\*\*TC<sub>2302</sub> on the TX CAR OSC Unit) for 15.5140 MHz ±100 Hz on the counter.

This completes the alignment for prod lots 006 and up. For lots 001 through 005, the following steps must also be performed.

- f) (\*\*) Set the MODE selector to the USB position key the transmitter, and adjust TC<sub>2303</sub> on the TX CAR OSC Unit for 15.5110 MHz ±100 Hz on the counter.
- g) (\*\*) Set the MODE selector to the AM position, key the transmitter, and adjust TC<sub>2301</sub> on the TX CAR OSC Unit for 15.5125 MHz ±100 Hz on the counter.

#### \*(3) Carrier Mixer

- a) Connect the RF probe of the voltmeter to pin 16 of MJ8.
- Adjust T<sub>3004</sub> for maximum deflection on the meter. (nom.: 220 ± 40 mV.)

#### \*(4) Second Local Mixer

- a) Connect the RF probe of the voltmeter to pin 17 of MJ8.
- b) Adjust  $T_{3007} T_{3012}$  for maximum deflection on the meter (nom.: 220 ± 60 mV).


#### RECEIVER

#### \*[1] Front End

- a) Connect the 4 ohm dummy load and the AF millivoltmeter to the SP jack on the rear panel, and connect the standard signal generator (SSG) to the ANT jack.
- b) Set the transceiver frequency to 14.2500 and set the SSG on the same frequency with an output level of 0 dB (1  $\mu$ V), and 1 kHz modulation.
- c) Set the MODE selector to USB and adjust T<sub>1008</sub> on the RF Unit for maximum deflection on the meter.

#### [2] IF Amplifiers

Set the MODE selector to USB, and the RF GAIN control fully clockwise. Also set the RF ATT control fully counter-clockwise. Keep the SSG connected as in the Front End alignment, above, throughout the IF Amplifier alignment.



IF UNIT (PB-2255)

- (1) Width and Shift
- a) Set the WIDTH and SHIFT controls on the front panel to their center positions.
- b) Connect the frequency counter to TP<sub>9001</sub> on the IF Unit.
- c) Adjust trimmer  $VR_{9006}$  for 19.7475 MHz  $\pm$  100 Hz on the counter.

#### \*(2) IF Coils

- a) With the transceiver and SSG set on 14.2500 MHz, as above, set the AGC switch on the front panel to the FAST position.
- b) Now set the SSG output level for an S-meter reading of 3 on the FT-ONE.
- c) Adjust  $T_{9001}$ ,  $T_{9002}$ ,  $T_{9003}$ ,  $T_{9005}$ ,  $T_{9007}$ ,  $T_{9008}$ ,  $T_{9011}$ ,  $T_{9013}$ ,  $T_{9014}$ ,  $T_{9015}$ , and  $T_{9016}$  (in this order) for maximum deflection on the Smeter.

## \*(3) CW(N) Filter Compensation Amplifier

This procedure is to be performed when the optional XF8.9KCN is installed.

- a) Set the MODE selector to the CW(N) position, and tune the SSG frequency to obtain maximum deflection on the S-meter.
- b) Now adjust the SSG output level to provide an S-meter reading of S3 on the transceiver.
- Adjust T<sub>9006</sub> on the IF Unit for maximum deflection on the S-meter.

#### (4) System Gain

- a) Set the MODE selector to the USB position, and set the SSG output level to zero at the ANT terminal.
- b) Adjust VR<sub>9004</sub> to obtain an S-meter reading of S3 on the transceiver.
- c) Now set the SSG output level to 0 dB (1  $\mu$ V). The S-meter should still read S3.
- d) Adjust VR<sub>9001</sub> to the point just before that at which the S-meter reading begins to decrease.

#### (5) S-meter

- a) Set the SSG output level to 6 dB (2  $\mu$ V), and adjust VR<sub>9004</sub> to obtain a reading of S1 on the S-meter.
- b) Now set the SSG output level to 90 dB (31.6 mV), and adjust VR<sub>9003</sub> to obtain a full scale reading on the S-meter.

- c) Repeat steps a) and b) several times.
- d) Check that the output level of the SSG is between 24 and 36 dB when the S-meter reads S9.

#### [3] AF Circuit

For the following procedures (except for procedure (2)), connect the 4 ohm dummy load and the AF voltmeter to the SP jack on the rear panel, and the SSG to the ANT terminal. The AGC switch should be set to the FAST position.

#### (1) AF Gain

- a) Set the SSG output level to 20 dB (10  $\mu$ V) at the same frequency as the transceiver, and set the MODE selector to USB. Set the AF GAIN control to the 9 o'clock position.
- b) Adjust the SSG frequency slightly to obtain approximately a 1 kHz beat, and check that the audio output level is between 350 and 900 mV (30 to 200 mW).
- c) Maintaining the same SSG output level and frequency, modulate the signal at 400 Hz with 40% modulation.
- d) Set the MODE selector to AM. The AF voltmeter should read between 350 and 900 mV (30 to 200 mW).

#### (2) AF Output Level

- Connect the AF voltmeter and a 50K ohm resistor across the AF OUT jack on the rear panel. Set the MODE selector to USB.
- b) Set the SSG output level to 20 dB (10  $\mu$ V) and switch the modulation OFF. Set the SSG frequency for approximately a 1 kHz beat.
- c) Check that the AF voltmeter indicates 300 to 500 mV.
- d) Switch on the modulator as in step (1) c) above, and set the MODE selector to AM. Check that the AF voltmeter still indicates 300 to 500 mV.
- (3) AF Power Amplifier
  - a) Set the MODE selector to USB, and rotate the AF GAIN control fully clockwise (maximum). Switch the SSG modulation OFF.
- b) Check that, with a 1 kHz beat, the AF millivoltmeter indicates at least 3.5 V (3 W).

#### [4] PLL Mixer

- Connect the SSG to the ANT jack, with output level of 90 dB (32 mV) at 1.885 MHz.
- Set the MODE selector to USB and tune the transceiver around 1.865 MHz for an audible beat.
- Adjust VR<sub>6002</sub> on the PLL Unit for minimum S-meter deflection.

#### \*[5] Noise Blanker

For this alignment, set the MODE selector to USB and the NB switch ON.

- (1) Noise Blanker LO
- a) Connect the frequency counter and the RF probe of the voltmeter to the second gate of Q<sub>3002</sub> on the Local Unit.
- b) The frequency counter should show 9.4425 MHz ± 1.0 kHz.
- c) The RF voltmeter should show 2.5 V  $\pm$  1.0 V  $_{\rm rms}$  .
- (2) Noise Blanker IF Coils
- a) Connect the DC voltmeter to  $TP_{3001}$  on the Local Unit and temporarily short the base of  $Q_{3007}$  to ground.
- b) Set the SSG to 14.2250 MHz and tune the transceiver to this frequency.
- c) Turn the AGC switch OFF and adjust the SSG output so that the DC voltmeter shows -1 V.
- d) Adjust  $T_{3001} T_{3003}$ , and  $T_{9004}$  for maximum deflection on the voltmeter (negative voltage).

#### \*[6] FM Unit-Receiver Section


- Receiver Local Oscillator
  - Connect the frequency counter to 1K resistor R<sub>2108</sub>, and adjust trimmer TC<sub>2101</sub> for 9442.5 kHz ± 100 Hz.
- (2) IF Amplifier Coils
- a) Set the transceiver frequency to 14.2500 MHz and connect the SSG to the ANT connector. the AF millivoltmeter to the speaker terminals.
- b) Set the SSG for an output level of -8 dBμ at the same frequency, and adjust T<sub>2101</sub> through T<sub>2103</sub> for minimum deflection on the millivoltmeter.

#### (3) Squelch Preset

a) Set the SQL control on the front panel to the 10 o'clock position and adjust VR<sub>2101</sub> on the FM Unit so that the squelch is just closed (with no input signal).

#### (4) DISC Meter Adjustment

- a) With the METER selector set to DISC, adjust VR<sub>2102</sub> so that the METER I needle indicates exactly at the center of the scale (with no input signal).
- (5) DISC Meter Sensitivity Adjustment
  - a) Connect the SSG as in step (2)a) above, and set for an output level of 20 dBμ at 14.2500 MHz.
- b) Tune the transceiver VFO for maximum deflection of the meter (METER I).
- Adjust VR<sub>2103</sub> for a deflection on METER I coinciding with the 15A marking on the IC scale (METER I indicating DISC).
- (6) Repeat steps (4) and (5).



FM UNIT (PB-2254)

#### TRANSMITTER

For the following procedures connect the dummy load/wattmeter to the ANT terminal, and the audio generator to the MIC jack. Set the audio generator to 1 kHz at 1 mV output level. Set the MODE selector to the USB position, and the transceiver frequency to 28.5000 MHz. Set the MIC GAIN fully clockwise (maximum) unless otherwise noted.

#### 1 Or use the Patch RCA socket at rear

#### [1] TX Coils

#### \*(1) Balanced Modulator Transformer

- a) Connect the RF probe of the voltmeter to pin 3 of edge connector MJ10.
- b) Close the PTT line (VOX control to MOX position) and adjust T<sub>4001</sub> on the AF Unit for maximum deflection on the RF voltmeter.

#### \*(2) TX First IF Transformers

- a) Connect the RF probe of the voltmeter to pin 9 of edge connector MJ6.
- b) Set the VOX control to the MOX position and adjust T<sub>9002</sub>, T<sub>9019</sub>, T<sub>9020</sub> and T<sub>9021</sub> for maximum deflection on the RF voltmeter.

#### \*(3) TX Second IF Transformer

Adjust  $T_{1010}$  on the RF Unit for maximum RF power output on the wattmeter.


#### [2] Directional Coupler

- Set the METER selector to the REF position, and the FWD SET control fully clockwise (maximum).
- b) Set the VOX control to the MOX position and adjust trimmer TC<sub>7101</sub> on the ALC Unit for minimum deflection on the transceiver REF indicating Meter (METER 1).

#### [3] Carrier Balance

This alignment requires an external receiver.

- Set the transceiver frequency to 14.2500 MHz, and the MODE selector to USB.
- Set the MIC GAIN control fully counterclockwise (minimum), and remove the audio generator from the MIC jack.
- c) Set the VOX control to the MOX position, and tune the external receiver to the carrier frequency.
- d) Adjust VR<sub>4008</sub> on the AF Unit for minimum S-meter deflection on the external receiver.
- e) Set the MODE selector to LSB and again adjust VR<sub>4008</sub> for a minimum.
- f) Repeat steps d) and e) several times in USB and LSB alternatively to obtain the same minimum carrier level in both modes.




AF UNIT (PB-2252)

#### \*[4] ALC Level


- a) Set the transceiver frequency to 28.5000 MHz, and the VOX control to the MOX position. Adjust VR<sub>7102</sub> on the ALC Unit for a reading of 90 W on the RF wattmeter.
- b) Set the transceiver frequency to 24.5000 MHz, and adjust VR<sub>7103</sub> on the ALC Unit for 100 W on the RF wattmeter.

#### \*[5] Overall Gain

- Set the MODE selector to the USB position, and connect the output of the AF generator to the MIC jack.
- b) Set the AF generator output level to 0.4 mV at 1 kHz, and set the VOX control to the MOX position.
- Adjust VR<sub>4009</sub> to the point just before that at which the ALC meter begins to deflect.



ALC UNIT (PB-2260)



100W PA UNIT (PB-2321)

#### [6] Transmit Level


- a) Set the transceiver frequency to 14.2500 MHz, and adjust VR<sub>1002</sub> so that the ALC meter deflects to the maximum edge of the ALC zone on the meter.
- b) Set the transceiver frequency to 7.1000 MHz, and adjust VR<sub>1004</sub> so that the ALC meter again deflects to the maximum edge of the ALC zone.
- c) Set the transceiver frequency to 3.5000 MHz, and adjust  $VR_{1007}$  for the same maximum ALC point.
- d) Set the transceiver frequency to 1.8000 MHz, and adjust VR<sub>1009</sub> in the same manner.

#### \*[7] ALC Meter

- With the MODE selector in USB, set the transceiver frequency to 28,000 MHz.
- b) Set the VOX control to the MOX position and adjust the output level of the AF generator to the point where it is 10 dB above that at which the ALC meter just begins to deflect.
- c) Adjust VR<sub>7104</sub> on the ALC Unit so that the ALC meter needle points within the right side of the ALC zone.

## \*[8] Speech Processor

- \*(1) Compression Amplifier
  - With the transceiver frequency set to 28.0000
     MHz, turn the PROC switch ON.
  - b) Set the AF generator output level to 2 mV at 1 kHz, and adjust the DRIVE control for a comfortable reading on the output wattmeter.
  - c) Set the METER selector to the COMP position and the COMP gain control fully clockwise (maximum). Adjust the MIC GAIN control so that the COMP reading is about 10 dB on the COMP scale of the meter.
  - d) Adjust T<sub>9017</sub> on the IF Unit for maximum deflection on the COMP meter.
  - f) Adjust T<sub>9018</sub> for maximum deflection on the output wattmeter.
- \*(2) Compression Level
  - Set the MIC GAIN, COMP gain and DRIVE controls all fully clockwise (maximum).
  - b) Set the AF generator output level to 1 mV at 1 kHz, and adjust VR<sub>9005</sub> so that the ALC meter needle indication is within the right side of the ALC zone.



#### [9] AMGC

#### (1) AMGC Gain

- Connect the DC voltmeter to pin 10 of Q<sub>4008</sub> on the AF Unit, and set VR<sub>4001</sub> fully counterclockwise.
- b) Set the VOX control to the MOX position, and adjust VR<sub>4001</sub> just to the point where the DC voltmeter indicates the shift from the low level (0 V) to high (5.5 V).

#### (2) AMGC Delay

This adjustment can be set to individual operator and environmental requirements. Adjust VR<sub>4002</sub> on the AF Unit for the desired "hang" time after speaking into the microphone. Clockwise rotation increases the delay period.

#### [10] CW Sidetone

#### (1) Sidetone Pitch

- Set the MODE selector to a CW position, and turn the MONI switch ON.
- b) Close the keying line and adjust VR<sub>4004</sub> on the AF Unit for the desired pitch. (This is normally set to around 800 Hz).

#### (2) Sidetone Level

 With the controls set as in the previous step, adjust VR<sub>4005</sub> on the AF Unit for comfortable sidetone volume.

#### \*[11] AM Circuit

#### (1) AM Modulator


- a) Connect the RF probe of the voltmeter to TP<sub>4001</sub> on the AF Unit.
- b) Set the MODE selector to the AM position, and reduce the output level of the AF generator to nil.
- Adjust T<sub>4002</sub> for maximum deflection on the RF voltmeter.

#### (2) Carrier Level

- a) With the transmitter frequency at 28.0000 MHz and the MODE selector in AM, set the MIC GAIN control fully counter-clockwise (minimum) and the DRIVE control fully clockwise (maximum).
- Adjust VR<sub>4011</sub> on the AF Unit so that the ALC meter just begins to deflect.

#### (3) AM Modulation Level

- a) Connect the vertical input of the oscilloscope to TP<sub>4001</sub> on the AF Unit, and set the MIC GAIN control fully clockwise (maximum).
- b) Set the AF generator output level to 1.3 mV at 1 kHz, and adjust VR<sub>4010</sub> so that the pattern indicating 100% modulation is displayed on the scope.



LPF UNIT (PB-2259)

#### [12] Monitor Level

- a) Set the MODE selector to LSB, and the MONI switch ON. Connect the headphones to the PHONES jack, and the microphone to the MIC jack.
- b) Close the PTT and speak into the microphone with a normal voice while adjusting VR<sub>4006</sub> on the AF Unit for comfortable volume in the headphones.

#### \*[13] IC Meter

- a) Connect the ammeter between pins 4 and 6 of the DC dummy plug on the rear of the transceiver.
- b) Set the transceiver to transmit on 14.2500 MHz in the FSK mode, and adjust the DRIVE control for 18 A on the ammeter.
- c) Set the METER selector to the IC position, and adjust VR<sub>7001</sub> on the Regulator Unit for a reading of 15 on the IC scale.

#### [14] VOX Anti-Trip Level


- a) Preset the transceiver front panel controls for normal SSB operation, tune in a station on the receiver, and set the AF GAIN for a comfortable listening level.
- b) Preset the ANTI-TRIP control, VR<sub>4003</sub>, fully counter-clockwise (minimum). Place the microphone near to the loudspeaker (do not activate the PTT).

- c) Rotate the VOX GAIN control on the front panel gradually clockwise from its counterclockwise (minimum) position just to the point where the transmitter is activated.
- d) Gradually rotate the ANTI-TRIP control, VR<sub>4003</sub>, clockwise to the point where the transmitter ceases to be activated by the audio from the loudspeaker.
- e) Now retune the transceiver to a clear frequency and speak into the microphone to ensure that the VOX activates the transmitter properly.


#### \*[15] AFP Circuit

The following procedure must not be attempted without the proper 25 ohm dummy load, i.e.: two 50 ohm dummy loads in parallel.

- a) With the transceiver set at 28.0000 MHz and the MODE selector in a CW position, connect the 25 ohm dummy load to the ANT jack.
- b) Close the keying line, and adjust the DRIVE control so that the ALC meter needles rests at the center of the ALC zone.
- c) Adjust VR<sub>7101</sub> on the ALC Unit to the point where the ALC meter needle just begins to move from its center position.



REG UNIT (PB-2258)



**FM UNIT (PB-2254)** 


#### \*[16] FM Unit-Transmit Section

Preset potentiometers  $VR_{2104}$ ,  $VR_{2106}$  and  $VR_{2107}$  to their center positions, and key the transmitter (connected to a dummy load) for each of the following adjustments.

- (1) Transmit Frequency Adjustment
  - a) Connect the frequency counter to pin 10 of MJ7 (pin 9 is ground).
  - Adjust T<sub>2104</sub> for a reading 8987.5 kHz ±500 Hz on the counter (with no microphone input).
- (2) Buffer Amplifier Adjustment
  - a) Connect the RF probe of the VTVM from pin 10 to pin 9 of MJ7. Adjust T<sub>2105</sub> for maximum deflection on the VTVM.
- (3) FM Transmit Level Adjustment
- a) Set the transceiver to 27 MHz and the DRIVE control fully clockwise. Adjust VR<sub>2106</sub> to the point where ALC indication just begins on METER II.


- (4) IDC Level Adjustment
- a) Connect the audio generator to the MIC input, and set for an output of 10 mV at 1 kHz. Connect the deviation meter through a directional coupler with the dummy load to the ANT terminal.
- Adjust VR<sub>2105</sub> for a deviation of ±5 kHz on the deviation meter.
- (5) Microphone Input Sensitivity Adjustment
- a) With the audio generator connected to the MIC input, set for an output of 1 mV at 1 kHz. Use the same deviation meter connection as in step (4).
- b) Adjust VR<sub>2104</sub> for a deviation of ±3.5 kHz.
- (6) Final Transmit Frequency Adjustment
- a) Remove the extender board and install the FM Unit back into position. Repeat step (1), adjust VR<sub>2107</sub> for 8987.5 kHz ±100 Hz on the counter (no microphone input).

# **MEMO**




ANT INPUT; 0 dB $\mu$  (1  $\mu$ V)


## RF UNIT PARTS LAYOUT





Viewed from component side





Viewed from solder side











## RF UNIT VOLTAGE CHART


(DC VOLTS)

	E(S)	C(D)	B(G1)	G2	REMARKS
Q1001	8.3	7.6	8.3		TX 21 MHz
Q1002	8.4	7.7	8.4		TX 14.5 MHz
Q1003	8.5	7.8	8.4		TX 6 MHz
Q1004	8.5	7.6	8.4		TX 7.5 MHz
Q1005	8.4	7.7	8.4		TX 10.5 MHz
Q1006	8.5	7.7	8.4		TX 4.5 MHz
Q1007	8.5	7.7	8.4		TX 3.5 MHz
Q1008	8.5	7.8	8.4		TX 2.5 MHz
Q1009	8.4	7.7	8.4	14	TX 1.9 MHz
Q1010	0.05	12.3	2.7		
Q1011	0.05	12.3	2.7		
Q1013	1.6	13.3	0		RX
Q1014	1.6	13.1	2.3		TX
Q1015	2.1	8.9	2.1	2.7	TX
Q1016	0.4	3.1	1.1		
Q1017	1.1	8.9	1.9		
Q1018	4.9	11.5	5.7		
Q1019	4.0	9.5	4.8		

## COMPONENT APPLICATIONS


Q1001	2SB774	Transistor	TX Power Controller	D1001	1SS53	Si Diode	Switch
Q1002	100	**	2000	20	969	ř.	ĉ
Q1003	77	"	390	5	3	)	)
Q1004		22	255	D1040	1SS53	Si Diode	Switch
Q1005	ē	e e	100	D1040			1) Supremities
Q1006	7	**			RD8.2EB3	Zener Diode	Regulator
Q1007	8	23	9900	D1042	1SV70	PIN Diode	TX, RX, RF
Q1008	77	**	500	D1042			Attenuator
Q1009	20	<b>24</b> C		D1043	**	100	
Q1010	2N4427	"	TX, RX, RF	D1044	,,		
N. 7. 7. 7.			Amplifier	D1045	RD6.2EB3	Zener Diode	Regulator
Q1011	7.		,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	D1046	1SS53	Si Diode	Switch
Q1011	ND487C2-3R	IC (Ring	RX 1st Mixer	D1047	900)	900	**
Q1012	ND407C2-3R	Module)	TX 2nd Mixer	D1048	**	900	"
01013	2SK125-3	Junction FET	RX 1st IF Amplifier	D1049	**	20:	100
Q1013		Self-spreightung einere	THE RESERVE AND ADDRESS OF THE PARTY AND ADDRE	D1050			1.00
Q1014	2SC2407	Transistor	TX Amplifier	D1051	- 100 m	••	
Q1015	3SK73GR	Dual Gate	TX ALC Amplifier	D1052	900		
II tarenarousa	revisiones restances meets.	MOS FET	TAMEN SYSTEM NAME OF THE	D1053	900	220	
Q1016	2SC1923-O	Transistor	RX 1st LOCAL	D1054	92	200	77
			Buffer Amplifier	D1055	***	(**):	: 14
			TX 2nd LOCAL	D1056	***	**	
			Buffer Amplifier	D1057	RD9.1EB2	Zener Diode	Regulator
Q1017	2SC2026	220	RX 1st LOCAL	2,00,	1125.1222	Boner Brode	regulator
			Amplifier	XF1001	XF-73KX	Crystal Filter	RX 1st IF Filter
			TX 2nd LOCAL	A1 1001	ALI - I SICA	Crystal I liter	TX 2nd IF Filter
			Amplifier				1 × 210 IF FILE
Q1018	2SC2407	••	RX 1st LOCAL	TH1001	D22A	Thermistor	Towns
			Buffer Amplifier	111001	DZZA	Inermistor	Temperature
			TX 2nd LOCAL				Compensator
			Buffer Amplifier				
Q1019	2SC1589	**	e en la company de la company				


## SENSOR UNIT PARTS LAYOUT




#### COMPONENT APPLICATIONS


Q7301	ON-1105	Photo Interrupter	Switch
Q7302	900	**	201
Q7303	2SC945AP	Transistor	DC Amplifier
Q7304	**	**	"








Viewed from component side




Viewed from solder side


ANT INPUT; 0 dB $\mu$  (1  $\mu$ V)




## IF UNIT PARTS LAYOUT




Viewed from component side



Viewed from solder side




**TA7060AP** 




ANT OUTPUT; SSB 100 W, AM 25 W


RX: FREQUENCY; 14.2 MHz





Viewed from component side





Viewed from solder side














#### IF UNIT VOLTAGE CHART


(DC VOLTS)

	E(S)	C(D)	B(G1)	G2	REMARKS
Q9001	1.9	13.5	2.1	2.5	RX
Q9002	1.9	13.5	2.1	2.5	RX
Q9003	3.5	12.8	3.4	4.6	RX
Q9004	0.7	13.3	0		RX
Q9005	0	4.9	0		NB OFF
Q9006	6.6	12.0	7.2		RX
Q9007	6.1	12.8	6.7		RX
Q9008	3.0	12.9	2.9	3.9	
Q9009	3.2	12.9	2.9	3.7	RX
Q9010	1.3	13.2	0		RX
Q9011	1.3	13.2	0		RX
Q9012	5.6	12.2	6.4		RX
Q9013	3.1	7.2	3.5		
Q9014	5.3	12.3	6.0		RX
Q9015	3.0	12.9	2.9	3.9	
Q9016	3.0	12.9	2.9	3.9	
Q9017	2.7	12.9	2.7	4.2	
Q9018	6.3	12.8	6.9	1	
Q9019	6.3	12.3	5.6		
Q9020	6.4	12.8	7.0		
Q9021	0/0	0.1/0	0/0.7	4	AGC ON/OFF
Q9022	0/0	0/3.4	0.1/0		AGC ON/OFF
Q9023	0	0	0.7		AGC S
Q9024	0	0	0.7		AM, FM
Q9026	0	4.3	3.9		AGC OFF
Q9027	3.9	-8.1	3.3		
Q9028	3.9	12.4	7.1		
Q9029	0.9	12.9	0.8	2.6	PROC ON
Q9031	0	13.4	0		PROC ON
Q9032	1.3	12.6	0.8	1.7	SSB, FSK, CW
Q9033	0	0	6.1	5,000.0	DRIVE VR CCW
Q9034	1.2	13.3	0.8	1.8	SSB, FSK, CW
Q9035	1.7	9.3	1.7	2.6	TX
Q9036	1.7	9.3	1.7	2.6	TX

	1	2	3	4	5	6	7	8	9	10	11	12	- 13	14	REMARKS
Q9025	-7.7	4.0	3.9	8.2	3.4	3.2	6.9	3.3	2.0	2.0	-8.1	3.4	4.1	4.1	4
Q9030	-	1.5	1.5	0	12.6	12.6	_			0.5000					PROC ON

# IF UNIT COMPONENT APPLICATIONS

		2. <del>0</del>	- 01,11 00,110,111		CALLIOINE		
Q9001	3SK73GR	Dual Gate	RX 2nd Mixer	D9012			***
00002	92925	MOS FET		D9013	577	••	**
Q9002	**	**	MAI	D9014	(66)	78	**
Q9003		**	RX NB Gate	D9015	200.5	***	**
Q9004	2SK61GR	Junction FET	RX NB Amplifier	D9016	900	•	**
Q9005	2SC945AP	Transistor	RX NB Controller	D9017	<b>**</b>	(**)	200
Q9006	90)		RX FM Buffer	D9018	•	**	• •
And the control of th			Amplifier	D9019	•	**	•
Q9007	200	***	RX CW(N) Buffer	D9020		,,	
			Amplifier	D9021	**	300	n.
Q9008	3SK73GR	Dual Gate	RX 2nd IF	D9022	•••	**	
		MOS FET	Amplifier	D9023	1SS53	Si Diode	Switch -
Q9009	990	•	RX Width First	D9024	1S1658	Varactor	RX Width VCXO
			Mixer	, R.S. 3.55	222220	Diode	TOT WIGHT TENO
Q9010	2SK19TMY	Junction FET	RX Width Second	D9025	1SS53	Si Diode	Switch
			Mixer	D9026	,,	"	,,
Q9011	•	880	***	D9027			
Q9012	2SC1923-O	Transistor	RX Width Buffer	D9028		385 588	
			Amplifier	D9028	***		•
Q9013	2SC945AP	77	RX Width VCXO	D9029	**		**
Q9014	2SC1923-O	,,	RX Width Buffer			***	***
176			Amplifier	D9031	366	3940	200
Q9015	3SK73GR	Dual Gate	RX 2nd IF	D9032		3886	763
		MOS FET	Amplifier	D9033	300	3.00	<i>(1)</i>
Q9016		"	0.50	D9034	1N60	Ge Diode	RX AM Detector
Q9017	10	· ·		D9035	**	*	20
Q9018	2SC945AP	Transistor		D9036	•		Temperature
Q9019	25C)+5A1		RX Buffer Amplifier				Compensator
Q9019 Q9020		1188	DV AV LE	D9037	1SS53	Si Diode	Discharge Diode
Q9020	555	365	RX AM AF	D9038	1000	**	Switch
00021			Amplifier	D9039	YZ033	Zener Diode	Regulator
Q9021	"	**	RX AGC OFF	D9040	1SS53	Si Diode	Switch
00000			Switch	D9041			***
Q9022	177	247	RX AGC Amplifier	D9042	V.	.,	,,
Q9023	•	30	RX AGC Switch	D9043			7.
Q9024	£55	::00	(22)	D9044	1SS53	Si Diode	Switch
Q9025	MC3403P	IC	RX AGC DC	D9045	1N60	Ge Diode	COMP. M Detector
			Amplifier	D9046	,,	"	" Detector
Q9026	2SA733Q	Transistor	RX S-Meter	D9047			Logarithmic
			Amplifier	DOTT			Compensator
Q9027			RX IF AGC Buffer	D9048	10002	C: Diada	
			Amplifier	D9049	1SS53	Si Diode	Switch
Q9028	2SC945AP		RX RF AGC	D9049			
			Amplifier	D9050	.,	<i>n</i> :	2
Q9029	- 3SK73GR	Dual Gate	TX IF Amplifier	D9051			75 - 7
100111111111111111111111111111111111111		MOS FET	1 A II Ampinier	D9032	RD9.1EB3	Zener Diode	Regulator
Q9030	TA7060AP	IC	TV DE Sassah	******		***************************************	Carried Control Control Control Control
2,000	1117000711	10	TX RF Speech	X9001	19.7475MHz	Crystal	RX Width VCXO
Q9031	2SC945AP	Transistor	Processor Amplifier				
Q2021	25C)43A1	11411515101	TX COMP. M Driver	XF9001	XF-8.9JF	Crystal Filter	RX 2nd IF Filter
Q9032	3SK73GR	D10	Amplifier	H1092079-41-0-12-0-0-12-0-12-0-12-0-12-0-12-0-12			(for NB, FM)
Q9032	33K/3GK	Dual Gate	TX IF Amplifier	XF9002	XF-8.9KCN	192	RX 3rd IF Filter
Q9033	200045 A.D.	MOS FET	Market at the				(for CW(N), Option)
Q9033	2SC945AP	Transistor	TX Driver Controller	XF9003	XF-8.9KC	(96)	"
Q9034	3SK73GR	Dual Gate	TX IF Amplifier				(for CW(M), Option)
00025		MOS FET		XF9004	XF-8.9KA	**	***
Q9035	•	**	TX 1st Mixer				(for AM, Option)
Q9036	500		"	XF9005	XF-8.9KS	***	**
D9001	RD9.1EB3	Zener Diode	Regulator				(for SSB)
D9002	1SS53	Si Diode	Switch	XF9006	XF-10.7KC	5000	<b>RX Width Filter</b>
D9003	**						(for CW(M), Option)
D9004	200			XF9007	XF-10.7KS		
D9005	996	**	WF				(for SSB)
D9006	96	500	7				mediaeticaseas ES #41
D9007	250		55 2019	TH9001	D22A	Thermistor	Temperature
D9008		300	"		NASS TOTAL		Compensator
D9009		·	n:	TH9002	SDT-1000	500	compensator "
D9010	**	•	,,			a1958	W7-75**
D9011		5W)	e N				
4.9000000000000000000000000000000000000		400	30				




AF UNIT SIGNAL LEVELS


TX: FREQUENCY; 14.2 MHz

ANT OUTPUT; SSB 100 W, AM 25 W


RX: FREQUENCY; 14.2 MHz ANT INPUT; 0 dBμ (1 μV)


# AF UNIT PARTS LAYOUT






PIN 5










TA7060P

μPC2002H





## **AF UNIT PARTS LAYOUT**



AF UNIT (PB-2252)

## AF UNIT VOLTAGE CHART

(DC VOLTS)

1	1	2	3	4	5	6	7	8	9	10	11	12	13	14	REMARKS
Q4001	9.2	5.5	3.8	0	3.8	5.6	5.6	11.2							SSB, CW, FSK
Q4002	0	6.2	6.2	0	0	12.8	0	6.2	6.2	0	0	0	0	13.5	SSB, CW, FSK
Q4003	6.6	6.6	6.5	13.1	6.6	6.6	6.6	6.6	6.6	6.6	0	6.6	6.6	7.9	
Q4004	6.6	6.6	6.6	13.1	6.6	6.6	6.6	6.6	6.6	6.6	0	6.6	6.6	6.6	Elec II
Q4006	4.9	5.0	5.0	0	5.0	5.0	4.9	13.2						35	
Q4020	3.8	3.8	3.8	0	3.8	3.8	3.8	7.6							SSB, AM, FM
Q4028	0.7	0.7	0	6.6	13.6										
Q4036	-	1.5	1.5	0	9.8	12.5	-								AM

	E	C	В	REMARKS
Q4007	0	5.0	0	
Q4009	0	5.0	0	
Q4010	0.4	4.7	1.0	SSB, AM, FM
Q4019	0.2	4.9	0.8	SSB, AM, FM
Q4023	3.0	7.2	3.6	CW
Q4026	0	0	0.7	
Q4027	0	0	0.7	
Q4029	0/0	0/0	6.3/0	DRIVE VR CCW/CW
Q4030	5.6	12.4	6.3	CW, FSK
Q4032	5.6	12.4	6.2	SSB
Q4034	0/0	0/0	5.9/0	DRIVE VR CCW/CW
Q4035	4.4	10.0	5.0	AM, FM
Q4037	5.4	6.1	12.2	AM

	IN	OUT	REMARKS
Q4005	13.5	5.0	
Q4024	13.5	8.1	CW
Q4025	12.7	8.1	SSB, AM, FM

IC

IC

Transistor

Transistor

Regulator

TX Sidetone

TX CW Driver

Controller

TX Monitor Switch

RX Audio Amplifier

\*\*

Switch

μPC78L08

2SC945AP

μРС2002Н

2SC945AP

..

Q4024

Q4025

Q4026


Q4027 Q4028


Q4029

## COMPONENT APPLICATIONS


				01000			THE CHIEF
				Q4030	.,	**	TX CW Driver
Q4001	SN16913P	IC	RX Balanced				Buffer Amplifier
			Demodulator	Q4031	MC1496CP	IC	TX Balanced
Q4002	MC14016BCP		RX Mode Selector				Modulator
Q4003	MC3403P	"	RX AF Amplifier,	Q4032	2SC945AP	Transistor	TX Buffer Amplifier
			Active LPF, HPF	Q4033	MC1496CP .	IC	TX AM Modulator
Q4004	**	"	RX APF Amplifier,	Q4034	2SC945AP	Transistor	TX Drive Controller
			Notch Filter	Q4035		**	TX Buffer Amplifier
Q4005	μPC78L05	.,	Regulator	Q4036	TA7060AP	IC	TX AF Limiter
Q4006	AN6552	**	TX VOX Amplifier,				Amplifier
			AMGC, Amplifier	Q4037	2SC945AP	Transistor	TX AF Buffer
Q4007	2SC945AP	Transistor	TX AMGC Switch				Amplifier
Q4008	MC14538BCP	IC	TX AMGC, VOX	D4001	1SS53	Si Diode	Switch
			Switch	D4002	**	**	"
Q4009	2SC945AP	Transistor	TX VOX Switch	D4003	••	**	"
Q4010			TX ANTI-TRIP	D4004	**		
			Amplifier	D4005	1SS53	Si Diode	Switch
Q4011			TX ANTI-TRIP	D4006	1N60	Ge Diode	
			Switch	D4007	1SS53	Si Diode	**
Q4012	**		TX BREAK-IN	(	(	(	(
			Switch	)	)	)	)
Q4013	MC14081BCP	IC	TX Gate	D4016	**		**
Q4014	2SC945AP	Transistor	TX AMGC Switch	D4018	RD5.1EB2	Zener Diode	Regulator
Q4015		**	PPT Switch	D4019	1SS53	Si Diode	Switch
Q4016	**		TX Keying	D4020	RD8.2EB3	Zener Diode	Regulator
Q4017	**		**	D4021	RD4.7EB2	**	Switch
Q4018	**			D4022	1SS53	Si Diode	,,
Q4019	2SC732TMGR		TX MIC Amplifier	D4023	.,	.,	,,
Q4020	AN6552	IC	TX AF Active HPF	D4024		**	**
			TX AF Buffer	D4025		.,	"
			Amplifier	D4026	.,		,,
Q4021	2SC945AP	Transistor	TX Sidetone				
***************************************			Oscillator	XF4001	XF-8.9KP	Crystal Filter	TX SSB Filter
Q4022	.,		TX Sidetone		0.7161	Cijoui i ittei	1.1.000 1 1101
			Switch	TH4001	SDT-1000	Thermistor	Temperature
Q4023	,,	**	TX Sidetone Buffer	1114001	321 1000	memistor	Compensator
			Amplifier	TH4002	.,		compensator "
			1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	1114002		***	


## KEYER UNIT PARTS LAYOUT







Viewed from component side






Viewed from foil side






TC01: AM/FM TC02: FSK/LSB TC03: CW/USB


# LOCAL UNIT PARTS LAYOUT (Early model)





Viewed from component side




Viewed from solder side









2SA733AP 2SA733AQ 2SC732TMBL 2SC945AP 2SC945AQ






# LOCAL UNIT | PARTS LAYOUT (After prod 6)




Viewed from component side



Viewed from solder side

# LOCAL UNIT PARTS LAYOUT (after prod 6)



### LOCAL UNIT VOLTAGE CHART

(DC VOLTS)

\	E(S)	C(D)	B(G1)	G2	REMARKS
Q3001	4.5	12.5	1.8		NB ON
Q3002	2.4	11.9	2.4	2.7	NB ON
Q3003	3.2	11.5	3.1	3.8	NB ON
Q3004	2.9	10.8	3.1	3.8	NB ON
Q3005	6.1	12.5	6.7		NB ON
Q3006	7.9/7.9	0/0	8.2/7.9		NB ON NB VR CCW/CW
Q3007	0	3.8	0		NB ON
Q3009	3.6	7.3	4.2		
Q3011	0/0	0/8.0	0.7/0		AM, FM/OTHER
Q3012	0/0	0/8.0	0.7/0		CW, USB/OTHER
Q3013	1.9	7.9	2.5		1070
Q3014	3.6	7.3	4.2		100
Q3015	0	0.7	0 -		RX SSB
Q3016	0	0	0.7		RX SSB
Q3017	0	6.5	0		RX SSB
Q3018	0	6.5	0		RX SSB
Q3019	2.1	7.8	2.5		
Q3020	3.5	7.3	4.2		
Q3021	13.5/13.5	13.4/0	12.8/13.0		AM, FM RX/TX AM
Q3023	0.8	7.4	1.1	1.1	
Q3024	0.8	7.4	1.1	1.1	
Q3025	1.1	7.6	1.5	3.7	
Q3026	8,1	13.4	8.8		
Q3027	0	3.0	0		
Q3028	0.1	6.2	0.7		
Q3029	0.7	6.2	1.1		
Q3031	0	2.2	0.4	9.7	171
Q3033	3.7	8.0	2.4		
Q3034	2.6	7.9	0		
Q3035	2.7	7.7	3.3		
Q3036	8.2	13.4	8.8		


	1	2	3	4	5	6	7	8	9	10	11	12	13	14	REMARKS
Q3008	6.7	3.1	2.8	0	2.8	4.0	4.0	8.1							resources pressures of
Q3010	12.2	12.2	12.2	0	0	0	0	1.2	1.2	0/2.6	0/2.6	13.5	13.5	13.3	SHIFT VR CCW/CW
Q3032	6.9	4.2	3.0	0	2.9	4.2	4.2	8.3							conjen

	_	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Q3(	030	0	1.1	0	5.0(0)	3.0	-	0	:	0	-	2.2	5.0	4.9/0	4.9/0	4.9/0	4.9/0
17	18	19	20	21	22	23	24					REMA	ARKS				
4.9/0	4.9/0	4.9/0	4.9/0	0	5.0	0	4.9	D	АТА Н	igh/Lo	w, (UN	NLOCK	()				


	IN	OUT	REMARKS				
Q3037	13.3	8.1		PIN 8 -		A PI	N 13
Á	PIN	5 -PIN 8 - AN65	552 <sub>PIN</sub>		PIN 14	PIN 12	PIN 24
PIN 4	1 NO	SN16 TCH	913P	MC14066B	NOTCH PIN 1	MB8718M	NOTCH NOTCH

## LOCAL UNIT COMPONENT APPLICATIONS

Q3001	2SC945AQ	Transistor	RX NB Oscillator	D3001	1N60	Ge Diode	RX NV Noise
Q3002	3SK73GR	Dual Gate	RX NB Mixer	D2002			Detector
02002	160)	MOS FET		D3002	2003 Section 1991	**	*
Q3003		(55)	RX NB IF	D3003	1SS53	Si Diode	Clipper
02004	••		Amplifier	D3004	1N60	Ge Diode	RX NB AGC
Q3004		(r)	# ************************************	VIEW 212-070			Detector
Q3005	2SC945AP	Transistor	RX NB Buffer	D3005		M.C.	
02006	20172215		Amplifier	D3006	1SS53	Si Diode	Switch
Q3006	2SA733AP	W.	NB Controller	D3007	FC52M5	Varactor	VCXO (for ALL
Q3007	2SC945AP	961	NB AGC			Diode	MODES)
02000	011160100	***	Amplifier	D3008	1SS53	Si Diode	Switch
Q3008	SN16913P	IC	CARRIER Mixer	D3009	200	W	1946
Q3009	2SC945AP	Transistor	CARRIER Buffer	D3010	FC52M5	Varactor	VCXO (for SSB, CW,
00010		_=	Amplifier			Diode	FSK)
Q3010	MC14066B	IC	MODE Selector	D3011	1SS53	Si Diode	Switch
Q3011	2SC945AP	Transistor	•	D3012	ž.		•
Q3012	"	220	SANDER SANDERS	D3013	1N60	Ge Diode	•
Q3013	"	200	VCXO (for ALL	D3014	RD9.1EB2	Zener Diode	Regulator
5			MODES)	D3015	1N60	Ge Diode	Switch
Q3014	**	**	VCXO Buffer	D3016	RD5.1EB2	Zener Diode	Regulator
42945 SEATE			Amplifier	D3017	MV104	Varactor	PLL VCO-1
Q3015	**	**	VCXO Frequency			Diode	
iling recherence			Controller	D3018	RD9.1EB2	Zener Diode	Regulator
Q3016	"	<b>**</b> ()	SW.				
Q3017	**	**	366	X3001	9.4425MHz	Crystal	NB Oscillator
Q3018	"	<b>#</b>	( <b>**</b>	X3002	15.5125MHz	1355	VCXO (for ALL
Q3019	"	<b>*</b>	VCXO (for SSB, CW,				MODES)
			FSK)	X3003	24.5MHz	(**	VCXO (for SSB, CW,
Q3020	324	**	VCXO Buffer				FSK)
			Amplifier				
Q3021	2SA733AQ	UKK	Switch				
Q3022	AN6552	IC	RX Shift, Width	TV CA	D OCC HAIR		
			Controller	IX CA	R OSC UNIT		
Q3023	3SK73GR	Dual Gate	RX 2nd LOCAL	*******	2002402000	122	2010 0 10 10 10 10 10 12 10 10 10 10 10 10 10 10 10 10 10 10 10
		MOS FET	Premixer	Q2301	2SC945AP	Transistor	Switch (for AM, FM)
			TX 1st LOCAL	Q2302	**	1955	" (for CW, USB)
			Premixer	Q2303	(**)	7.50	TX Carrier Oscillator
Q3024	086	***	**	Q2304	••	**	TX Carrier OSC
			200	RESOCIALISM	256413115415541610		Buffer Amplifier
Q3025	•	**	RX 2nd LOCAL	Q2305	2SA733AP	**	Switch
			Amplifier	Q2306	2SC945AP	***	
			TX 1st LOCAL				
			Amplifier	D2301	1SS97	Schottky	Switch (for AM, FM)
Q3026	2SC945AP	Transistor	Regulator			Barrier Di	
Q3027	5.000		PLL VCO-1	D2302	7#6 538277538	100	" (for CW, USB)
			Reference Amplifier	D2303	1SS53	Si Diode	1(22)
Q3028	2SC732TMBL	••	PLL VCO-1 Active				
			LPF	X2301	15.514MHz	Crystal	TX Carrier Oscillator
Q3029	200						
Q3030	MB8718M	IC	PLL VCO-1 DIV,				
			PH. DET.				
Q3031	2SC945AP	Transistor	PLL VCO-1 IF				
			Amplifier				
Q3032	SN16913P	IC	PLL VCO-1 Mixer				
Q3033	2SK19TMGR	Junction FET	PLL VCO-1 Buffer				
		-	Amplifier				
Q3034	JF1033S	000	PLL VCO-1				
Q3035	2SK19TMGR	396	PLL VCO-1 Buffer				
			Amplifier				
Q3036	2SC945AP	Transistor	Regulator				
			NO ROLL				




## CONTROL UNIT PARTS LAYOUT



Viewed from solder side

## CONTROL UNIT PARTS LAYOUT



## **CONTROL UNIT**

VOLTAGE CHART (DC VOLTS)

REMARKS	В	C	E	
	5.8	6.2	5.1	Q5027
	5.9	7.0	5.1	Q5028
	5.9	6.5	5.3	Q5029
	6.1	7.3	5.3	Q5030
(UNLOCK)	0(5.1)	0.7(0)	0	Q5032
(POWER DOWN)	0(5.4)	0.6(0)	0	Q5033
	9.1	13.3	8.4	Q5041

### COMPONENT APPLICATIONS

Q5001	2SC1317R	Transistor	BPF Selector	Q5050	MC14012BCP	IC	Counter
Q5002	2SA733AQ	VVC	i ii	Q5051	MC14069UBCP	**	500
Q5003	2SC1317R	200	i ii	Q5052	MC14013BCP	•	3 <b>44</b>
Q5004	2SA733AQ	960	"	Q5053	MN9005		CPU
Q5005	2SC1317R	56	344	Q5054	2SC945AP	Transistor	LED Driver
Q5006	2SA733AQ	•	ı ili	Q5055	301	**	877
Q5007	2SC1317R	37	••	Q5056	**	***	500
Q5008	2SA733AQ	\$\$65	o .	Q5057	**		1000
Q5009	2SC1317R	(W)	<i>ii</i>	Q5058	•		(24
Q5010	2SA733AQ	***	,,,	Q5059	MC14066BCP	IC	Switch
Q5011	2SC1317R	***	300	Q5060	MC14001BCP		
Q5012	2SA733AQ		5.00	Q5061	2SC945AP	Transistor	<b>10</b> 23
Q5013	2SC1317R	•	155	Q5062	2SC1317R		LED Digit Driver
Q5014	2SA733AQ	**	1.00	)	)	)	)
Q5015	2SC1317R	•	,,	Q5071		(	(
Q5016	2SA733AQ	200	100	Q5071	2SA719R	**	I ED Comment Daisse
Q5017	2SC1317R	2006	398	23072		, ,	LED Segment Driver
Q5018	2SA733AQ	2001	900	(	}	(	(
Q5019	2SC1317R	250	366	Q5079	,		u .
Q5020	2SA733AQ	•					
Q5021	TBP18SA030	IC	ROM	D5001	1SS53	Si Diode	Switch
Q5022	•	***		D5002		••	
Q5023	**	965		D5003	200		ï.
Q5024	SN7406N	<b>20</b> 00	VCO Selector Driver	D5004	- no		ü
			Amplifier	D5005	900	1000	"
Q5025	MC14011BCP	M(s)	BPF Selector	D5006		5566	
Q5026		•	TX Disable Switch	D5007	1SS53	Si Diode	Switch
Q5027	2SC1317R	Transistor	Regulator	D5008	RD5.6EB3	Zener Diode	Regulator
Q5028		.,		D5009			
Q5029	2SD288K	22	Tr.	D5010	•	700	
Q5030	2SC1317R	2200	1000	D5011	••		
Q5031	MC14081BCP	IC	Scan Controller	D5012	1SS53	Si Diode	Switch
Q5032	2SC945AP	Transistor	Unlock Signal	D5013	883	500	W.
			Amplifier	D5014			100
Q5033	<i>77</i> c		Power Down Switch	D5015	RD5.6EB3	Zener Diode	
Q5034	MC14066BCP	IC	Switch	D5016	1SS53	Si Diode	5 <b>6</b>
Q5035	2SA733AQ	Transistor	VCO Selector	D5017	996		
Q5036	550	**	C.C.	D5018	<b>20</b> 00	***	,,
Q5037	**	550	966	D5019	**		**
Q5038	**	•		D5020	RD9.1EB2	Zener Diode	Regulator
Q5039	**	**		D5021	1SS53	Si Diode	Switch
Q5040			- 0	D5022			
Q5041	2SC1317R	**	Regulator	D5023		166	
Q5042	MN1201A	IC	Latch	D5024		,,	
Q5043	**	98%		D5025	1N60	Ge Diode	
Q5044	**	20	000	D5026	1SS53	Si Diode	077
Q5045	MC14081BCP	96	Gate	D5027	#3	7 M	H22
Q5046	••	••	••	D5028	**	386	
Q504'/	MC14069BCP	550	10Hz/100Hz	D5029			100
en-constitution			Counter	D5030			126
Q5048	MC14001BCP	996	160	D5031	RD5.6EB3	Zener Diode	Regulator
Q5049	MC14510BCP	985)	196		#105-14825241F52556		wasta@mnaaadi:


#### SERVICING


D5032	1SS53	Si Diode	Switch
{	)	}	}
D5052	**		**
D5053	1SS53	Si Diode	Switch
D5054	Not Used		
D5055	RD5.6EB	Zener Diode	Regulator
D5056	1SS53	Si Diode	Switch
D5057	w.		
D5058	RD3.3EB2	Zener Diode	,,


#### COMPONENT APPLICATIONS

Q7901	MN1203	IC	RAM
Q7902	**	***	**
D7901	1SS53	Si Diode	Switch


#### RAM BOARD UNIT PARTS LAYOUT














Viewed from foil side




# PLL UNIT PARTS LAYOUT (Early model)




Viewed from component side




Viewed from solder side




PLL UNIT







Viewed from component side



Viewed from solder side



PLL UNIT



### PLL UNIT VOLTAGE CHART

(DC VOLTS)

	E(S)	C(D)	B(G1)	G2	REMARKS		E(S)	C(D)	B(G1)	G2	REMARKS
Q6001	3.8	7.6	4.1			Q6032	0	1.0	0.7		
Q6002	3.8	7.6	4.1			Q6037	0	2.2	0.6		
Q6003	3.8	7.6	4.1			Q6039	4.7	7.2	5.4		
Q6004	3.8	7.6	4.1			Q6040	8.2	10.8	8.8		
Q6005	3.8	7.6	4.1			Q6041	3.4	7.9	3.9	-	
Q6006	3.8	7.6	4.1			Q6042	4.7	7.2	5.4		
Q6007	1.0	7.2	1.8		1500	Q6044	1.8	7.8	2.5	N. P.	
Q6008	1.8	7.4	2.5		71.3	Q6045	8.3	10.9	9.0		100
Q6009	2.5	5.1	2.6	4.8		Q6046	1.1	8.3	1.6	1.845	
Q6010	5.4	10.7	6.0			Q6047	0.02	5.6	1.1		
Q6016	0	6.5	0.7			Q6048	4.0	7.8	4.7		
Q6017	0	6.5	0.7			Q6049	3.4	7.8	2.7		1
Q6018	2.4	6.5	3.1			Q6050	1.9	8.0	2.5		
Q6019	1.6	4.0	2,4			Q6051	3.3	7.9	3.8		3
Q6020	3.3	8.4	4.2			Q6052	4.6	7.2	5.4		
Q6021	1.5	5.3	1.8			Q6054	0	2.0	0.5		1.0
Q6023	1.1	8.3	1.6			Q6056	0	3.1	0		12.0
Q6024	0.7	4.9	1.1			Q6057	5.2	11.3	5.8		
Q6025	0.1	4.9	0.7			Q6058	5.2	7.9	5.9		
Q6026	0	2.8	0.2			Q6061	1.6	7.8	1.0		
Q6027	4.6	7.1	5.3			Q6062	3.5	7.8	3.7		
Q6028	2.5	6.9	2.6	4.8		Q6063	1.8	7.7	0.9		
Q6029	4.6	7.7	4.8			Q6064	8.2	11.3	8.8		
Q6030	8.2	11.3	9.0		100	Q6065	8.4	10.5	9.1		
Q6031	5.2	10.3	5.8		4300						

## (DC VOLTS)


	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Q6022	2.8	4.3	4.0	0	0	-	0	0	0	1.7	4.4	7-	4.4	5.3		
Q6033	1.0	0	1.7	1.7		-	0.8	0		1.7	=	2.1	2.1	0	0.8	5.1
Q6034	2.9	4.0	1.7	0	0	=	0	0	0	===	5.1	9=	0.5	5.1	III SERVESON	1905/2500
Q6035	4.0	0.5	2.7	2.7	2.7	0.2	0	0.2	4.0	4.0	6.9	0.5	0.5	5.2		
Q6036	0	-0	4.1	4.0	0.2	6.9	0	4.2	4.2	325	0	0	0	8.3		
Q6038	6.1	3.6	2.6	0	2.6	3.6	3.6	7.3								
Q6043	122	7.9	7.1	4.0	4.0	0	-	877	2.6	4.0	4.0	4.0	7.1	-		
Q6053	6.1	3.6	2.6	0	2.6	3.6	3.6	7.3								
Q6059	2.0	5.2	150	200	2.1		0	0	2.1	5.2	-	×-	2.1	=	0	5.2
Q6060	0	0	2.0	0	4.9	0	4.9	2.8							0.00	E-C-KM

	\	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Q6	055	0	1.6	0	5.2	3.1		0	2=	0	-54	2.0	5.2	5.5/0	5.5/0	5.5/0	5.5/0
17	18	19	20	21	22	23	24					REM	ARKS				
5.5/0	5.5/0	5.5/0	5.5/0	0	5.2	0	-		DAT	A High	/Low						

### PLL UNIT COMPONENT APPLICATIONS

Q6001	2SC1923-O	Transistor	PLL VCO-4-6	Q6051	2SC535B	•	PLL Local Oscillator
Q6002	••		PLL VCO-4-5	Q6052	2SC945AQ		PLL Local Buffer
Q6003	3005	920	PLL VCO-4-4				Amplifier
Q6004	10.5	3300	PLL VCO-4-1	Q6053	SN16913P	IC	PLL Mixer
Q6005	30.	901	PLL VCO-4-2	Q6054	2SC945AQ	Transistor	PLL IF Amplifier
Q6006	<b>25</b> 0	995	PLL VCO-4-3	Q6055	MB8718B	IC	PLL Divider, Phase
Q6007	2SC2026	•	PLL VCO-4 Buffer				Detector
			Amplifier	Q6056	2SC945AQ	Transistor	PLL Reference
Q6008	2SC1923-O	993	**				Amplifier
Q6009	3SK74L	Dual Gate	,,	Q6057	346	200	Regulator
		MOS FET		Q6058	2SC1959Y		600.
Q6010	2SD882Q	Transistor	Regulator	Q6059	MC14518B	IC	PLL Reference
Q6011	SN74S113	IC	PLL Programmable				1/100 Divider
			Divider	Q6060	HD10551	*	PLL Reference
Q6012	SN74S11	••					1/20 Divider
Q6013	SN74LS196	96	**	Q6061	JF1033B	Junction FET	PLL Reference
Q6014	TBP18SA030	36.60	PLL ROM				Buffer Amplifier
Q6015	SN74LS196	(0)	PLL Programmable	Q6062	2SC535B	Transistor	PLL Reference
			Divider				Oscillator
Q6016	2SK 206-3	Junction FET	PLL Mixer	Q6063	JF1033B	Junction FET	PLL Reference
Q6017	and the second	( <b>*</b> )					Buffer Amplifier
Q6018	2SC1923-O	Transistor	PLL Buffer	Q6064	2SC945AQ	Transistor	Regulator
			Amplifier	Q6065	2SC1959Y		763
Q6019	2SC2026	9660	PLL IF Amplifier	D6001	1T25	Varactor	PLL VCO-4-6
Q6020	2SC1923-O	**	PLL Buffer			Diode	
			Amplifier	D6002		.,	900
Q6021	2SC2407	••	"	D6003	1SS53	Si Diode	Switch
Q6022	MC4044P	IC	PLL Phase Detector	D6004	1T25	Varactor	PLL VCO-4-5
Q6023	2SC732TMBL	Transistor	PLL Active LPF			Diode	
Q6024	97	**	F	D6005	900	300	•
Q6025	2005	3000		D6006	1SS53	Si Diode	Switch
Q6026	2SC945AQ	800	PLL Reference	D6007	1T25	Varactor	PLL VCO-4-4
			Amplifier			Diode	
Q6027	••	**	PLL VCO-3 Buffer	D6008	1SS53	Si Diode	Switch
			Amplifier	D6009	1T25	Varactor	PLL VCO-4-1
Q6028	3SK74L	Dual Gate	PLL VCO-3			Diode	
0.000000000		MOS FET	Amplifier	D6010	1SS53	Si Diode	Switch
Q6029	2SC1923-O	Transistor	PLL VCO-3	D6011	1T25	Varactor	PLL VCO-4-2
Q6030	2SC945AQ	35	Regulator			Diode	ARCENEN DESERTS DESER
Q6031	2SC1959Y	••	,	D6012	1SS53	Si Diode	Switch
Q6032	2SC1923-O	**	PLL VCO-1	D6013	1T25	Varactor	PLL VCO-4-3
			Amplifier			Diode	
Q6033	SN74LS390	IC	PLL VCO-1 1/100	D6014	1SS53	Si Diode	Switch
			Divider	D6015	RD9.1EB2	Zener Diode	Regulator
Q6034	MC4044P	9.50	PLL Phase Detector	D6016	RD5.6EB3	1000	**
Q6035	SN74LS26	•	PLL Inverter	D6017	1SS97	Schottky	Switch
Q6036	MC14066BCP	**	PLL Switch			Barrier Di.	
Q6037	2SC945AQ	Transistor	PLL Buffer	D6018	RD9.1EB2	Zener Diode	Regulator
			Amplifier	D6019	1T25	Varactor	PLL VCO-3
Q6038	SN16913P	IC	PLL Mixer			Diode	
Q6039	2SC945AQ	Transistor	PLL Buffer	D6020		W.	<i>n</i>
			Amplifier	D6021	1SS53	Si Diode	Switch
Q6040	2SC1959Y	986	Regulator	D6022	RD5.6EB3	Zener Diode	Regulator
Q6041	2SC535B		PLL Local Oscillator	D6023	1N60	Ge Diode	Switch
Q6042	2SC945AQ	W	PLL Local Buffer	D6024	RD9.1EB2	Zener Diode	Regulator
	AND THE RESERVE THE SERVE		Amplifier	D6025	973	,	,,
Q6043	SN76514N	IC	PLL Mixer	D6026	200	5370 3353	,
Q6044	2SC945AQ	Transistor	PLL Local Buffer	D6027	MV104	Varactor	PLL VCO-2
	35-76 1513 151	Section 1997	Amplifier		07.E.C.C.M.	Diode	122.134.2
Q6045	2SC1959Y		Regulator	D6028	1T25	Diode "	D/F Converter
Q6046	2SC732TMBL	**	PLL Active LPF	D6029	RD5.6EB3	Zener Diode	
Q6047	MPS-A13		"	D6030	,,	Zener Diode	Regulator
Q6048	2SC1923-O		PLL VCO-2	20000	656	100 N	**
	2SK19TMGR	Junction FET		X6001	48.615MHz	Crystal	PLL Local Oscillator
()6/12/9		Juneuon FE1	PLL VCO-2 Buffer			Ciystai	TEL LOCAL OSCILLATOR
Q6049	-53.55713.500		Amplifia-	X6002	54 28MH2	**	22
Q6049 Q6050	2SC945AQ	Transistor	Amplifier	X6002 X6003	54.28MHz 20MHz		" PLL Reference

## 100W PA UNIT



#### COMPONENT APPLICATIONS


## VOLTAGE CHART


(DC VOLTS)


	E	C	В	REMARKS
Q8001	0,5	13.5	1.3	TX
Q8002	0	13.5	0.7	TX
Q8003	0	13.5	0.7	TX
Q8004	0	13.5	0.7	TX
Q8005	0	13.5	0.7	TX
Q8007	0.7	8.0	1.3	TX


	IN	OUT	REMARKS	
08006	13.5	8.0	TX	

Q8001	2SC1589	Transistor	TX Driver Amplifier
Q8002	2SC2395	**	772
Q8003		22	900
Q8004	2SC2290	**	TX Final Amplifier
Q8005	**		"
Q8006	μPC14308	IC	Regulator
Q8007	2SD235Y	Transistor	•
D8001	YZ-033	Zener Diode	Regulator
D8002	10D10	Si Diode	Temperature
			Compensator
D8003	**	**	**
D8004	₩	<i>#</i>	
D8005		**	












## 100W PA UNIT PARTS LAYOUT




Viewed from component side



## 100W PA UNIT PARTS LAYOUT




## **COOLING FAN MOUNTING DETAIL**








#### FT-ONE THERMAL FAN CONTROL

- 1. Remove the 100W PA Unit from the radio.
- 2. Remove the four screws from the 100W PA Unit, as shown in Figure 1.
- 3. Drill a 3mm (1/8 inch) diameter hole in the 100W PA Unit side cover, as shown in A of Figure 1 (Lot 1 and 2).
- 4. Apply thermal grease to thermal switch TS01, and install along with the diode (VO6B) and the jumper wire, as shown in Figure 2 (3 x 8 screw, nut and spring washer provided).
- 5. Replace the four screws. Modification is now complete.












## DIODE SW UNIT PARTS LAYOUT



#### COMPONENT APPLICATIONS

D7801	V06B	Si Diode	Switch
D7802	**	300	
D7803	***	•	"
D7804	966	350	"
D7805	6 <b>5</b> 62	(55)	,
D7806	7.0		
D7807	**	•	,,
D7808	**	**	,,
D7809	**	**	100
D7810	**	906	•






Viewed from foil side

Viewed from component side

# ALC UNIT



SIGNAL LEVELS


TX: FREQUENCY; 14.2 MHz

ANT OUTPUT; SSB 100 W, AM 25 W

RX: FREQUENCY; 14.2 MHz ANT INPUT; 0 dBμ (1 μV)

# VOLTAGE CHART (DC VOLTS)


1	E(S)	C(D)	B(G)	REMARKS
Q7101	0.3	-4.0	0	ALC OFF
Q7102	0.8	-4.0	0.3	ALC OFF
Q7103	-4.0	2.6	-4.0	ALC OFF
Q7104	4.4	7.6	2.6	ALC OFF
Q7105	4.9	0	4.3	ALC OFF




#### COMPONENT APPLICATIONS

LC Amplifier
PAGE SENSEN BROWN CHILDS
LC Meter
fier
EF. Voltage
tor
LC Voltage
tor
VD. Voltage
tor
erature
ensator
se Voltage
tor
Amplifier
e Protector

## ALC UNIT PARTS LAYOUT




Viewed from component side




Viewed from solder side

## ALC UNIT PARTS LAYOUT



## **REG UNIT**




#### VOLTAGE CHART


#### (DC VOLTS)

				(DC VOLI
/	E	C	В	REMARKS
Q7001	12.8	12.0	12.0	
Q7002	8.2	12.0	8.8	
Q7003	0	0	0.7	
Q7004	7.6	13.5	8.2	132
Q7005	8.2	13.5	8.9	
Q7006	13.5	11.6	12.7	
Q7007	0	10.9	0	
Q7008	0	10.9	0.3	
Q7009	0	0.4	0.7	
Q7011	0	0	0.7	
Q7012	0	0	0.8	
Q7015	-4.0/2.7	3.3/2.7	4.2/2.1	TX/RX
Q7016	3.3/2.9	-3.9/2.9	5.0/2.4	TX/RX
Q7017	0/0	0/0.8	0.7/0	TX/RX
Q7018	0/0	13.5/0	0/0.8	TX/RX
Q7019	13.5/13.5	0/13.5	13.5/0	TX/RX
Q7020	0.8/0.9	0.8/-3.9	0.3/5.0	TX/RX
Q7021	0/0	0.4/13.5	0.8/0	TX/RX
Q7022	13.5/13.5	13.5/0	0.4/13.5	TX/RX
Q7023	0	13.5	0	
Q7025	12.7/12.9	12.6/0	12.0/13.3	TX/RX
Q7026	13.5/13.5	12.6/0	12.7/12.9	TX/RX


/	IN	OUT	REMARKS
Q7010	13.5	8.3	
Q7024	-9.1	-8.1	
Q7027	13.5	5.0	




## **REG UNIT PARTS LAYOUT**




Viewed from component side







Viewed from solder side




### REG UNIT PARTS LAYOUT





## REGULATOR UNIT COMPONENT APPLICATIONS

Q7001	2SA733AQ	Transistor	Switch
Q7001 Q7002	2SD882Q	"	Regulator
Q7002	2SC945AQ		Switch Driver
Q7003	2SC2562Y		Regulator
07005	2SC945AQ	,,	7.
	8		**
Q7006	2SB536A		
Q7007	2SC945AQ	•	Switch
Q7008		<i>n</i>	Error Amplifier
Q7009		rese	
Q7010	78L08	IC	Regulator
Q7011	2SC945AQ	Transistor	Switch
Q7012		"	
Q7013	MC14071B	IC	Delay Amplifier,
			Buffer Amp.
Q7014	MC14069B	700 C-000	Delay Amplifier
Q7015	2SA733AQ	Transistor	Switch
Q7016	***	***	**
Q7017	2SC945AQ	<b>**</b>	Switch Driver
Q7018	97		
Q7019	2SB772Q		Switch
Q7020	2SA733AQ	160	199
Q7021	2SC945AQ	<b>77</b> 22	Switch Driver
Q7022	2SB536K	**:	Switch
Q7023	2SC2002L	**	DC-DC Converter
Q7024	μPC7908	IC	Regulator
Q7025	2SA733AQ	Transistor	Relay Driver
Q7026	2SA719Q	••	
Q7027	78L05	IC	Regulator
2/2020	HORSE MAN CO		2007 2000
D7001	S2VB10	Si Diode	Rectifier
		Bridge	
D7002	V06B	Si Diode	Switch
D7003	RD9.1EB2	Zener Diode	Regulator
D7004	V06B	Si Diode	Switch
D7005	RD9.1EB2	Zener Diode	Regulator
D7006	RD10EB1	570	v
D7007	1SS53	Si Diode	Switch
D7008	900	1885	200
D7009	1556		
D7010	••	**	***
D7011	**	**	••
D7012	360	**	<b>70</b> 2
D7013	· · ·	306	365
D7014	m 72.	200	
D7015	1885	315	70
D7016			Rectifier
D7017	RD12EB2	Zener Diode	Regulator
D7018	1SS53	Si Diode	Reverse Voltage
CONTRACTOR OF STREET	randa, स्वयंत्रवर्षित	: T4413844 (\$1500.11	Protector
D7019	506	2000	00
SS NACLS			




## **POWER SUPPLY**






### LPF UNIT




#### COMPONENT APPLICATIONS




D7201	1SS53	Si Diode	Reverse Voltage
			Protector
D7202		<i>,,</i>	" [32]
D7203	"	u u	"
D7204	,,	11	"
D7205	,,	"	,,
D7206	"	n	
D7207	"	"	,,
D7208	,,	11	"
D7209	"	"	,,
D7210	"	<i>n</i> .	<i>ii</i>
D7211			,,
D7212	,,	<i>ii</i> .	"
D7213	"	n n	,,
D7214	,,	<u> </u>	"
D7215	"	"	<i>u</i>
D7216	,,	"	,,
D7217	,,	"	,,
D7218	,,		,,

## LPF UNIT PARTS LAYOUT




Viewed from component side




Viewed from solder side


# LPF UNIT PARTS LAYOUT




# **PUSH SW UNIT**



D7401	1SS53	Si Diode	Switch
D7402			
D7403	e	**	
D7404			746




Viewed from component side




Viewed from solder side

## LEVER SW UNIT




#### COMPONENT APPLICATIONS

D7501 1SS53 Si Diode Switch




Viewed from component side




Viewed from solder side


## KEYBOARD UNIT





D7601	1SS53	Si Diode	Switch
D7602	**		**
D7603	277	77	
D7604		"	
D7605	**	"	
D7606	***		**
D7607	**	"	
D7608			
D7609			




## **EXT CONTROL UNIT**











Q2201	2SC945AP	Transistor	Switch
Q2202	"	**	**
Q2203	AN6552	IC	"
Q2204	2SC945AP	Transistor	
D2201	1SS97	Schottky Barrier Di.	Switch





Viewed from component side




Viewed from solder side

## DISPLAY UNIT






Viewed from component side




Viewed from solder side



\* D7701-7706 (HP5082-7623) is not used PIN 1, 7, 8, 14.

D7701	HD5082-7623	Display LED	Frequency Display
D7702	**	***	20.
D7703		••	<b></b>
D7704	••	••	11.
D7705		**	••
D7706			**
D7707	HD5082-7415	100	Clarifier Frequency,
			VFO Channel
			Display
D7708	LN410YP	LED	Dial Lock Indicator
D7709	**		TX Disable Indicator
D7710	**	•	TRX Clarifier
			Indicator
D7711	366	500	Transceive Indicator
D7712	200	200	RX Clarifier
			Indicator
D7713	555	**	Processor Indicator
D7714		.,	NB Indicator
D7715		**	AMGC Indicator
D7716	***		Monitor Indicator
D7717	8,000	:00	Audio Peak Filter
			Indicator
D7718	**	200	Notch Filter
			Indicator
D7719	.,		Auto Scan Indicator



#### FM UNIT SIGNAL LEVELS

TX: FREQUENCY; 29.0 MHz


DEVIATION; 3.5 kHz @ 1 kHz Mod.

MIC INPUT; 1 mV


RX: FREQUENCY; 29.0 MHz

ANT INPUT;  $0.38 \mu V$  (QN 20 dB)

## **FM UNIT PARTS LAYOUT**



# **FM UNIT PARTS LAYOUT**



# FM UNIT (OPTION)

#### VOLTAGE CHART


(DC VOLTS)

	E(S)	C(D)	B(G)	REMARKS
Q2101	0.8	7.8	1.5	RX
Q2102	2.2	7.8	0	RX
Q2103	0.7	7.8	1.4	RX
Q2105	4.9	7.5	4.3	RX
Q2106	8.0/-0.5	13.0/13.1	8.8/0.05	RX/TX
Q2107	0	8.8/0.05	0.1/0.8	RX/TX
Q2108	0.5	4.8	1.2	RX
Q2110	0	0.8/0	0.03/0.6	RX/TX
Q2111	0.13	3.0	0.8	RX
Q2112	0.4	6.9	1.1	TX
Q2113	1.1	5.0	1.7	TX
Q2114	5.7	10.7	6.2	TX
Q2115	0.8	5.2	1.4	TX
Q2116	1.9	8.1	2.5	TX
Q2117	0.8	7.9	1.4	TX


	Anode	Cathode
D2109	1.3	6.5

257	1	2	3	4	5	6	7	8
Q2104		14		0	3.7		7.1	
Q2109		181		-8.0				8.0


	IN	OUT
Q2118	13.2	8.0





μPC577H




2SC945AP 2SC945AQ 2SC1674L 2SC1959Y










# NOISE BLANKER PULSE SHAPER








Components side view

Solder side view



# **MEMO**

### SOLDERING AND DESOLDERING TECHNIQUE ON PRINTED CIRCUIT BOARDS

The FT-ONE circuit boards are tough, but mishandling during soldering can cause circuit traces to "lift." While this does not cause permanent damage to the board, much servicing trouble can result, because of the tendency for this lifted trace to break. A few simple precautions will keep your circuit boards in A-1 condition.

- Use only a 12 to 30 watt chisel-tip soldering iron. Yes, some "repairmen" have been known to use small blowtorches on cards.
- 2. Use only a soldering iron equipped with a three-wire cord, with the tip grounded. Also acceptable is a soldering iron isolated through a transformer. An old soldering iron or gun may have 117 volts on the tip, and will certainly cause more damage than it repairs!
- USE ONLY 60/40 ROSIN CORE SOLDER. Acid core solder should be thrown away if you find it in your radio shop!
- Use a solder sucker and solder tape to ensure a professional repair job.
- If you do lift a trace, don't worry! Read on to find out how to repair traces like a pro.

#### NOTES ON USE OF CMOS COMPONENTS:

As CMOS devices are extremely sensitive to damage from static electricity, special precautions must be observed.

In storage, use only sponge specially designed for CMOS components.

When installing a CMOS part in a socket, or on a circuit board, be certain that the power is off. In addition, the technician should rest his hand on the chassis as the component is inserted, so as to place his hand at the same potential as the chassis (better to discharge small amounts of static electricity through your fingers than through a \$5 IC!).

When soldering a CMOS part onto a circuit board, use a low wattage iron, and be sure to ground the tip with a clip lead, if the tip is not grounded through a three-wire power cord.

### INSERTION OF PARTS ON CIRCUIT BOARDS

All of the below are acceptable ways of inserting components into circuit board mounting holes.



= (a) Bend leads slightly



= (b) Straight-in mounting



(c) Vertical mounting




(d) Preformed disc ceramic capacitor




(e) Preformed resistor, diode, etc.

## EXAMPLES OF POOR SOLDERING PRACTICE




- Prepare soldering iron and solder.
- (2) Apply soldering iron to surface to be soldered.
- (3) Apply solder to heated surface.
- (4) When enough solder is applied, remove solder. Continue to apply heat until solder flows cleanly.
- (5) Remove iron from work. Do not apply more heat than necessary for good solder flow.




#### Soldering to terminal posts:

(Be certain to apply heat to both post and wire.)



If you have previously lifted a trace, make an etch cut on each side of the lifted trace as shown in the drawing, and install a wire bridge.



Coat Cut Area With Eastman 910

# SECTION 4-REPAIR PARTS

ORDERING DATA	 -1
PARTS LIST	 -5

## PARTS LIST

Part No.  G2090027  G2090003  J10276100  J10276101  J01245681  J01245102  J01245823  J32009011  J62800061  J62800062  J60800080  J60800081  J62800063	Description	PT1 CH1 L1 FH1,2 F1 F2 F2 F2	L3030092A L2030001 L0021255 P2000012 Q0000002 Q0000007 Q0000005	SE-77KYA 4Ω, 3W  TRANSFORMER  T-12  Balun Trans  FUSE HOLDER  SN-2059  FUSE  1A (Backup)  10A (100-117 VAC)  5A (200-234 VAC)  LAMP  13.5V 80mA
G2090003  J10276100  J10276101  J01245681  J01245102  J01245823  J32009011  J62800061  J62800062  J60800080  J60800081  J62800063	Si 1SS53 " V06B  RESISTOR  Carbon Composition 1/2W GK 10Ω " " 100Ω " Film 1/4W TJ 680Ω " " " 1kΩ " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2 K16BA004C-10KBX2 10KBX2 K1611008TE-10KB 10KB K1611008TE-10KC 10KC	CH1 L1 FH1,2 F1 F2 F2	L2030001 L0021255 P2000012 Q0000002 Q0000007 Q0000005	T-12 Balun Trans FUSE HOLDER SN-2059  FUSE 1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC)  LAMP
G2090003  J10276100  J10276101  J01245681  J01245102  J01245823  J32009011  J62800061  J62800062  J60800080  J60800081  J62800063	V06B   RESISTOR   Carbon Composition   1/2W GK   10Ω     100Ω     100Ω   100Ω     100Ω	CH1 L1 FH1,2 F1 F2 F2	L2030001 L0021255 P2000012 Q0000002 Q0000007 Q0000005	T-12 Balun Trans FUSE HOLDER SN-2059  FUSE 1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC)  LAMP
J10276100 J10276101 J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	Carbon Composition	CH1 L1 FH1,2 F1 F2 F2	L2030001 L0021255 P2000012 Q0000002 Q0000007 Q0000005	T-12 Balun Trans FUSE HOLDER SN-2059  FUSE 1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC)  LAMP
J10276101 J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	Carbon Composition  1/2W GK 10Ω  " " " 100Ω  " Film 1/4W TJ 680Ω  " " 1kΩ  " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	CH1 L1 FH1,2 F1 F2 F2	L2030001 L0021255 P2000012 Q0000002 Q0000007 Q0000005	Balun Trans  FUSE HOLDER  SN-2059  FUSE  1A (Backup)  10A (100-117 VAC)  5A (200-234 VAC)  LAMP
J10276101 J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	Carbon Composition  1/2W GK 10Ω  " " " 100Ω  " Film 1/4W TJ 680Ω  " " 1kΩ  " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	F1 F2 F2	D0021255 P2000012 Q0000002 Q0000007 Q0000005	Balun Trans  FUSE HOLDER  SN-2059  FUSE  1A (Backup)  10A (100-117 VAC)  5A (200-234 VAC)  LAMP
J10276101 J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	Carbon Composition  1/2W GK 10Ω  " " " 100Ω  " Film 1/4W TJ 680Ω  " " 1kΩ  " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	F1 F2 F2	P2000012 Q0000002 Q0000007 Q0000005	FUSE HOLDER SN-2059  FUSE 1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC)  LAMP
J10276101 J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	1/2W GK 10Ω	F1 F2 F2	Q0000002 Q0000007 Q0000005	FUSE 1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC) LAMP
J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	" " " 100Ω " Film 1/4W TJ 680Ω " " 1kΩ " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	F1 F2 F2	Q0000002 Q0000007 Q0000005	FUSE 1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC) LAMP
J01245681 J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	" Film 1/4W TJ 680Ω " " " 1kΩ " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	F2 F2	Q0000007 Q0000005	1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC) LAMP
J01245102 J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	" " " 1kΩ " " 82kΩ  Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	F2 F2	Q0000007 Q0000005	1A (Backup) 10A (100-117 VAC) 5A (200-234 VAC) LAMP
J01245823 J32009011 J62800061 J62800062 J60800080 J60800081 J62800063	### ### ### ### ### #### #### ########	F2 F2	Q0000007 Q0000005	10A (100-117 VAC 5A (200-234 VAC LAMP
J62800061 J62800062 J60800080 J60800081 J62800063	Meter Shunt  POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC	F2	Q0000005	5A (200–234 VAC
J62800061 J62800062 J60800080 J60800081 J62800063	POTENTIOMETER  K16B20034-2KBX2 2KBX2  K16BA004C-10KBX2 10KBX2  K1611008TE-10KB 10KB  K1611008TE-10KC 10KC			LAMP
J62800062 J60800080 J60800081 J62800063	K16B20034-2KBX2 2KBX2 K16BA004C-10KBX2 10KBX2 K1611008TE-10KB 10KB K1611008TE-10KC 10KC	PL1	Q1000047	1 TO
J62800062 J60800080 J60800081 J62800063	K16B20034-2KBX2 2KBX2 K16BA004C-10KBX2 10KBX2 K1611008TE-10KB 10KB K1611008TE-10KC 10KC	PL1	Q1000047	
J62800062 J60800080 J60800081 J62800063	K16B20034-2KBX2 2KBX2 K16BA004C-10KBX2 10KBX2 K1611008TE-10KB 10KB K1611008TE-10KC 10KC	PL1	Q1000047	13.5V 80mA
J62800062 J60800080 J60800081 J62800063	K16BA004C-10KBX2 10KBX2 K1611008TE-10KB 10KB K1611008TE-10KC 10KC			
J60800080 J60800081 J62800063	K1611008TE-10KB 10KB K1611008TE-10KC 10KC			
J60800081 J62800063	K1611008TE-10KC 10KC			
J62800063				CONNECTOR
MACHAEOG INGWOODERIN	TELEP LEONG CLEVELL	J1	P1090246	D8-701B-00
162000064	K16BA100C-5M1111	J2	P1090034	D7-701B-00
163000064	20ΚΒ,10ΚΒ 20ΚΩΒ,10ΚΩΒ	J3	P0090094	PA-125
J62800064	K16BA004C-10KB,10KA	J4	P0090249	QS-AB8M(I)
	10ΚΩΒ,10ΚΩΑ	J5	P1090004	SG-7814
J61800012	K162B00B8J-100KCX2	J7	P1090001	SG-7701
	100KΩCX2	18	P1090003	SG-7615
J62800065	K16BA004C-5KBX2	19	P0090158	FM-214-8SS
				3191-06R1
J62800066				MBR-06B
	500KC,1MB 500KΩC,1MΩB	J12	P1090111	7015J
				3305-014-011SN
	The state of the s	THE RESERVE AND ADDRESS OF THE PARTY OF THE PARTY.		1150-044-009
K13170102				1150-036-009
THOUGH THE CONTROL OF		MJ7	P4090010	3305-018-011SN
K14180103				
K12329001	" " 1.4KV 0.01μF			TERMINAL BOARD
	(ECKDAL103PE)	SQ1	Q9000133	(RCV-1, RCV-2, RF OUT)
K13170103		SQ2	Q9000134	(SP, FSK, AF OUT )
	(DB201YF103Z5L5)			
K13170473				PLUG
	(DB207YF473Z5L5)	P1 (with wire)	T9204296	3191-02P1
K40179012		P2 ( " )	T9204297A	3191-04P1
	(50RE4R7)	P3 ( " )		(TMP15DP)
K41140228	2011 1 2200/41	P4 ( " )	100000000000000000000000000000000000000	TMP15DP
		P5,6 ( " )	THE PERSON NAMED IN COLUMN TWO IS NOT THE OWNER.	5251-02
	N-5000000000000000000000000000000000000			5251-02
	The state of the s	P10 ( " )		5251-02
- SPECIFOUVIAL - NOVEMBER	a control of the second of the	P11 ( " )		5251-02
N0190094	SRN202CN	P12 ( " )	T9204304	5251-02
N0190091	SRN1025N	P13 ( " )	T9204305	5251-03
N0190093	SRN2046N	P31 ( " )	T9204316	5251-03
		P14,18( " )		
		P34 ( " )		5251-04
	METER	P35 ( " )	T9204320	5251-04
M0290027	AP-90	P15,17( " )	T9204307A	
M0290028	AP-90	P16 ( " )	T9204308A	
		P23,27( " )	T9204311B	5251-06
		P28 ( " )	T9204313	5251-06
	RELAY	P7 ( " )	T9204299	5251-07
M1190033	LY3F DC12V	P29 ( " )	T9204314	5251-07
	N6090001 N0190096 N0190094 N0190093 N0190093 M0290027 M0290028	CAPACITOR   SOUNT   CAPACITOR	J62800066	J62800066   K16BA100C-5M1111-  S00KC,1MΩB   S00KΩC,1MΩB   J12   P1090194

## REPAIR PARTS

P24 (with wire)	T9204312	5251-08	Q1015	G4800730G	3SK73GR		
P30 ( " )	T9204315	5251-08					
P33 ( " )	T9204318	5251-08					
P19 ( " )	T9204308A	5251-09			DIODE		
P22,26( " )	T9204310A	5251-09	D1045	G2090015	Zener	RD6.2E	В3
P21,25( " )	T9204309A	5251-11	D1041	G2090042		RD8.2E	
P32 ( " )	T9204317	5251-12	D1057	G2090155	.,	RD9.1E	ACTAVI
P37	P1090256	QS-P8FK	D1001-1040,	G2090027	Si	1SS53	
P38,39	P0090075	P-7015	1046-1056	32070027	Si .	13333	
	T9100304	SPEAKER LEADS	D1042-1044	G2090200	PIN	1SV77	
			210.12 101.1	02070200		101,77	
		BATTERY HOLDER			CRYSTAL FI	TED	
	Q9000096	C-4	XF1001	H1102043		LICH	
	Q9000090	C-4	AF1001	П1102043	XF-73KX		
					RESISTOR		
		BATTERY SNAP	R1086	J02245479	Carbon Film	1/4W S.	1 4.7Ω
	P2000011	S6	R1091	J10276100	" Com	position	
						1/2W GI	K 10Ω
			R1101	J02245100	" Film	1/4W SJ	10Ω
		KNOB	R1054,1057	J02245120			12Ω
	R3040673B	MAIN	R1065,1099	J02245180		** **	18Ω
	R6073240	SUB	R1061	J02245220			22Ω
	R3072910	METER, APF/NOTCH, RF,	R1087	J02245270			The second state
		MODE VFO A B, VFO SELECT,	R1055,1056,1106, 1111,1114	J02245330			-
	P20/0/21	RF ATT	R1115,1116	J10276470	" Com	position	
	R3068621	VOX, MIC, DRIVE, DELAY, AF	R1075,1076,1108,	J02245560	" Film	1/2W GI 1/4W SJ	
	R3072930A	FWD SET, COMP, NB, KEYER, SQL	1112 R1072,1074,1103,	J02245820			82Ω
	R3072940	SHIFT/WIDTH (KNOB)	1104	302243620		" "	0242
	R3072960	SHIFT/WIDTH (LEVER)	R1069,1084	J02245101			100Ω
	R3072880	POWER, PROC, NB, AMGC,	R1073	J02245101			-017497740
	K3072880	MONI, APF, AGC, SCAN (LEVER)	R1052,1068,1071, 1082,1096,1113	J02245151	# W		120
	R3072890A	FINE, MHz, CLAR, RX TRX,	R1048.1059	J02245181		-24 78	180Ω
	K3072030A	LOCK (PUSH KNOB)		J02245181 J02245221			
	R3072900	KEYBOARD (PUSH KNOB)	R1004,1060,1062, 1063,1079,1088, 1089,1117	302243221			220Ω
			R1001,1002,1005, 1007,1008,1010, 1111,1013,1014, 1016,1017,1019, 1020,1022,1023, 1025,1026,1028,	J02245271		0. 30	270Ω
		UNIT	1029,1032,1035,				
Symbol No.	Part No.	Description	1037,1064,1066,				
PB-2256A	F0002256A	Printed Circuit Board	1077,1080,1097,	7.1.14.5	1		
	C0022560	P.C.B. with Components	Harris of the state of the stat				
			R1067,1078	J02245331	0 0		100 000 000
		200	R1095	J02245391			
		IC	R1105	J02245471			
Q1012	G2090135	ND487C2-3R	R1051,1090	J02245561	,, ,,		
			R1081,1083	J02245681	" "		
		TRANSISTOR	R1049,1050,1053, 1058,1085,1092	J02245102	" "	ne an	lkΩ
Q1001-1009	G3207740	2SB774	R1003	J02245122			1.2ks
Q1019	G3315890	2SC1589	R1031	J02245332			
Q1016	G3319230O	2SC1923-O	R1006,1009,1012,	J02245472			
Q1017	G3320260	2SC2026	1015,1018,1021,		900		
	G3324070	2SC2407	1024,1027,1030,	500	1101		
O1014.1018	1 - PERSON TOWN TOWN	- September 19 - Sept	1036,1038-1046,	2005			
Q1014,1018 Q1010,1011	G3090010	2N4471					
National Control of the Control of t	G3090010	2N4427		102245562		401 1-1	5.640
Name and Address of the Owner o	G3090010	2N4421	R1070,1109,1110	J02245562			5.6kΩ
Q1014,1018 Q1010,1011	G3090010	FET		J02245562 J02245103 J02245153	" "		10kΩ

R1102	J02245224	Carbon Film 1/4W SJ 220kΩ	C1048	K10176102	Ceramic Disc 50WV B (DD104B102K50V02)	1000pF
		THERMISTOR	C1060	K10176152	(DD105B152K50V02)	1500pF
TH1001	G9090002	D22A	C1017,1036	K10176222		2200pF
			C1013,1162,1164,	K13170102		0.001μF
		POTENTIOMETER	1168,1178-1181, 1186,1187,1189,		(DB200YF102Z5L2)	
VR1001-1009	J50749202	H0812A003-2KB 2KΩB	1191,1193,			
			1197-1199,1202, 1203,1206-1211,		The second	
		CAPACITOR	1214-1217			
C1196	K00173060	Ceramic Disc 50WV SL 6pF	C1002,1004,1010,	K14180103	" " 63WV	0.01µF
		(DD104SL060J50V02)	1015,1026,1028, 1030,1041,1044,	I I I I I I I I I I I I I I I I I I I	(RD871-1FZ103Z)	
C1153	K00175150	" " " 15pF	1053,1056,1065,			
C1104,1106	K00175180	(DD104SL150J50V02) " " 18pF	1068,1074,1077, 1083,1086,1092,			
C1104,1100	K001/3180	(DD104SL180J50V02)	1095,1099,1103, 1107,1109,1111,			
	K00175220	" " 22pF	1112-1130,1132,			
		(DD104SL220J50V02)	1135,1137,1138, 1140,1143,			
C1096,1098	K00179006	" " 24pF	1146-1148,1151,			
C1176,1177	V00175270	(DD104SL240J50V02)	1155,1158,1160, 1161,1163,			
C1170,1177	K00175270	" " 27pF (DD104SL270J50V02)	1165-1167, 1170-1175,			
	K00175330	" " " 33pF	1182-1184,1195,			
		(DD104SL330J50V02)	1200,1201,1212			
C1070,1072,1078, 1082	K00175390	" " " " 39pF	C1101,1169,1185,	K13170473	50WV	0.047μF
27.669	W00175170	(DD104SL390J50V02)	1188,1190,1192, 1194		(DB207YF473Z5L5)	
C1079,1081,1152, 1154	K00175470	" " 47pF	C1133,1134	W10140025		
C1218,1219	K00179011	(DD104SL470J50V02) " " 62pF	C1155,1154	K19149025	Semiconductor Ceramic 25WV	0.1μF
0.5.5.5.1.10.0.000		(DD104SL620J50V02)			(UAT13X104K-L46AE)	
C1069,1073,1088,	K00175680	" " 68pF	C1001,1005,1009,	K40179013	Electrolytic 50WV	1μF
1090	Parket and the state of the state of	(DD104SL680J50V02)	1131,1136,1139, 1141,1142,1156,		(50RE1)	
C1087,1091	K00175820	" " " 82pF	1157			
C1105	K00179013	(DD104SL820J50V02) " " " 91pF	C1011.1012.1027.	K40129004	16WV	10µF
	1001/2012	(DD105SL910J50V02)	1042,1054,1066,	K40129004	(16RE10)	тодт
C1062,1064	K00175101	" " 100pF	1075,1084,1093, 1100,1108,1110,		3	
Regulation		(DD105SL101J50V02)	1144,1145,1149, 1205			
C1097	K00179017	" " " 130pF	: May to the	*********		22.00
C1050,1052	K00175151	(DD105-257SL131J50V02) " " 150pF	C1003,1014,1029, 1043,1055,1067,	K40129016	(16RE22)	22µF
C1000,1002	R00173131	(DD104SL151J50V02)	1076,1085,1094, 1102,1213		(16KE22)	
C1038,1040,1057,	K00175181	" " 180pF	1102,1213			
1071	Face and all Controls	(DD104SL181J50V02)	C1150,1159	K40129008	*	33µF
C1023,1025,1059, 1080	K00175221	" " " 220pF			(16RE33)	
C1006,1008,1018,	K00175271	(DD104SL221J50V02) " " 270pF				
1032,1035,1045,	R00173271	(DD104SL271J50V02)			INDUCTOR	
1047,1061,1063, 1204			L1053	L1020700		0.45µH
2000 HE SON TOWN	CONTRACTOR OF STREET		L1082-1084	L1190092	FL4H-R47M	0.47µH
C1016,1021,1037, 1051,1089	K00175331	" " " 330pF	L1048	L1190004	FL4H-R68M	0.68 <sub>µ</sub> H
C1020,1033,1039	K00175391	(DD104SL331J50V02) " " 390pF	L1046,1050,1059 L1033	L1190005 L1190006	FL4H-1R0M FL4H-1R2M	1μH
	100110331	(DD104SL391J50V02)	L1051,1055	L1020701	I LTH-I NAM	1.2μH 1.4μH
C1049	K00175471	" " 470pF	W. C	L1190087	FL4H-1R5M	1.5µH
		(DD104SL471J50V02)	L1031,1035,1038	L1190007	FL4H-1R8M	1.8µH
C1034,1046	K10176561	" " B 560pF	L1052,1054	L1020702		2.0µH
C1019,1022,1024,	K10176681	(DD104B561K50V02) 680pF	L1043	L1190008	FL4H-2R2M	2.2µH
01017,1022,1024,	K101/0001	(DD104B681K50V02)	L1047,1049	L1190126 L1190009	FL4H-2R4M FL4H-3R3M	2.4μH 3.3μH
1031		(DD104D001K30V021				
1031 C1007,1058	K10176821	" " 820pF	21047,1045	L1190010	FL4H-3R9K	3.9µH

## REPAIR PARTS

	L1190111	FL4H-5R6K	5.6µH	Q3028,3029	G3307320B	2SC732TMBI	L	
L1025-1027,1041,	L1190013	FL4H-6R8K	6.8µH	Q3005,3007,3009,	G3309451P	2SC945AP		
1045				3011-3020,3026, 3027,3031,3036,				
L1028,1029,1037, 1039	L1190070	FL4H-8R2K	8.2μH	3038				
L1042,1044	L1190014	FL4H-100K	10µH	Q3001	G3309451Q	2SC945AQ		
L1019-1023	L1190015	FL5H-120J	12µH					
L1016,1017	L1190019	LF5H-150K	15µH			FET		
L1015	L1190021	FL5H-180K	18µH	Q3034	G3090023	JF1033B		
L1006,1009,1010	L1190023	FL5H-220K	22µH	Q3033,3035	G3090035	2SK19TM-GI	3	
L1002,1003,1007, 1014	L1190073	FL5H-270K	27μH	Q3002-3004, 3023-3025	G4800730G	3SK73GR		
L1013	L1190027	FL5H-390K	39µH					
L1008,1057	L1190029	FL5H-470K	47µH					
L1058,1060,1062, 1071,1075,1078,	L1190020	FL5H-151K	150µH			DIODE		
1080,1081				D3007,3010,3023	G2090165	Varactor	FC52M-5	
		1227232 500222	V 744	D3017	G2090043	700	MV-104	
L1001,1004,1005, 1011,1012,1018, 1024,1030,1056,	L1190017	FL5H-102K	1mH	D3001,3002,3004, 3005,3013,3015	G2090029	Ge	1N60	
1063-1066,1072,				D3016	G2090152	Zener	RD5.1EI	
1074,1079				D3014,3018	G2090155	100	RD9.1EI	3-2
L1073	L0021120			D3003,3006,3008, 3009,3011,3012,	G2090027	Si	1SS53	
L1089	L1020691A			3019,3020				
L1067-1070,1076, 1077,1086	L1020693A			D3021,3022	G2090118	Schottky	1SS97	
L1087	L1020694A							
L1088	L1020692A					CRYSTAL		
L1085	L1020696A			X3001	H0102275	HC-18/U	9.4425M	Hz
				X3002	H0102469	HC-18/U3P	15.511M	Hz
				X3003	H0102429	HC-18/U3P	24.5MH2	
		TRANSFORMER		X3004	H0102471	HC-18/U3P	15.514M	Hz
T1001,1003,1004, 1006,1007	L0020883		70.7			THERMISTOR		
T1002,1009	L0020856			TH3001,3002	G9090001	SDT-250	`	
T1005	L0021123					500000000000000000000000000000000000000		
T1008,1010	L0021122A							
	27-10-2010-4-010-000					RESISTOR		
				R3010	J02245829	Carbon Film	1/4W SJ	8.2Ω
		CONNECTOR		R3144	J02245220			22Ω
J1001	P0090218	5045-02A		R3096-3098,3109	J02245470			47Ω
				R3006,3039,3040, 3065,3129,3148	J02245560	<i>ii ii</i> )		56Ω
	Q5000011	Wrapping terminal C		R3004,3028,3043,	J02245101		991 199	100Ω
				3044,3063,3080, 3084,3092,3093, 3103,3114,3130, 3134,3143	WESS-SECTION			80.553
				R3108	J02245121	n 11	., .,	120Ω
				R3128	J02245151			150Ω
Symbol No.	LOCAL Part No.	UNIT Description		R3012,3019,3025, 3059,3145	J02245221			220Ω
PB-2253B	F0002253B	Printed Circuit Board		R3023	J02245271	n 20	76. 70	270Ω
	C0022530	P.C.B. with Component	ts	R3110	J02245331	n n	26. 00	330Ω
				R3011	J02245391		** **	390Ω
		IC		R3015,3017,3045, 3064,3085,3142	J02245471	"- "		470Ω
Q3022	G1090246	AN6552		R3135	J02245561	n n		560Ω
Q3030	G1090153	MB8718M		R3003,3060	J02245681	n n	m in	680Ω
Q3010	G1090257	MC14066BCP		R3016,3022,3027,	J02245102	#8 #8	m. :n	1kΩ
Q3008,3032	G1090012	SN16913P		3035,3048,3074,				
Q3037	G1090080	μPC78L08		3081,3086,3112, 3126,3131				
				R3116	J02245122			1.2ks
			-	R3037,3049,3055,	J02245152			1.5ks
		TRANSISTOR		3155				
Q3006,3039	G3107331P	2SA733AP		R3070,3113	J02245222		n :n	2.2ks
Q3021	G3107331Q	2SA733AQ		R3117	J02245272			2.7ks

R3005,3038,3100	J02245332	Carbon Film	1/4W S	SJ	3.3kΩ	C3094	K00175180	Ceramic Disc 50WV SL 18pF (DD104SL180J50V02)
R3067 R3009,3013,3020,	J02245392 J02245472		**		3.9kΩ 4.7kΩ	C3093	K00179005	" " " 20pF (DD104SL200J50V02)
3033,3104,3115, 3118-3125, 3150,3152	302243472				4.784	C3148	K00175390	" " 39pF (DD104SL390J50V02)
R3046,3052,3053, 3056	J02245562	W #	,,,	990	5.6kΩ	C3058,3142	K06175470	" " UJ 47pF (DD104UJ470J50V02)
R3029,3057	J02245682		117		6.8kΩ	C3001,3136,3063	K00175470	SL 47pF
R3002,3075	J02245822			**	8.2kΩ	1 1 2 A 1 2 A 1		(DD104SL470J50V02)
R3030,3047,3058, 3066,3069,3071, 3076,3079,3087,	J02245103	" "	**	**	10kΩ	C3140	K06179047	" " UJ 51pF (DD104UJ510J50V02)
3094,3095,3147 R3007,3014,3021, 3087	J02245153	· · · · · · · · · · · · · · · · · · ·	***		15kΩ	C3074,3121,3123	K00173560	" " SL 56pF (DD104SL560J50V02)
R3008,3041,3061, 3077,3082,3107	J02245183		"	**	18kΩ	C3056,3057	K06175680 K02175101	" " UJ 68pF (DD105-257UJ680J50V02) " " CH100pF
R3042,3057,3062,	J02245223	, n	.,		22kΩ		K02173101	(DD107CH101J50V02)
3073,3078,3083, 3099,3105,3106, 3133,3140,3154	3-1-1-1				55.111.5	C3065,3095,3122, 3133,3135,3149, 3150	K00175101	" " SL 100pF (DD105SL101J50V02)
R3024,3141	J02245333	0 %	**	**	33kΩ	C3059,3071,3072	K06175101	" " UJ 100pF
R3001,3034,3050, 3051,3136,3149,	J02245473		**	,,	47kΩ	C3076,3077	K10176101	(DD106UJ101J50V02) " " B 100pF
3151,3153 R3068,3072,3132,	J02245563	## D##3		***	56kΩ	C3130,3131	K00175121	(DD104B101K50V02) " " SL 120pF
3146							W00185151	(DD105SL121J50V02)
R3031 R3018, 3137-3139	J02245683 J02245104	" "	.,	"	68kΩ 100kΩ	62066 2067	K02175151	" " CH150pF (DD109CH151J50V02) " " B 150pF
No. of the last of	102245124		**	ee-	120kΩ	C3066,3067	K10176151	(DD104B151K50V02)
R3032,3111,3127 R3090,3091	J02245124 J02245184			,,		C3002,3003	K00175151	" " SL 150pF
R3088,3089	J02245184 J02245224			,,	220kΩ	C5002,5005	K00175151	(DD104SL151J50V02)
R3026	J02245274			,,	120372101931	C3021,3046,3047,	K00175221	" " 220pF
	J02245394		**	.,	390kΩ	3134		(DD107SL221J50V02)
R3036	J02245105		**	"	1ΜΩ	C3013	K00175331	" " " 330pF (DD107SL331J50V02)
		BLOCK RESIS	STOR			C3006,3007,3024,	K13170102	" " 0.001μF
RB3001	J40900026	RK1/16B6R	220K 22	0k	Ωx6	3026,3036, 3086-3088,3090,		(DB200YF102Z5L2)
RB3002	J40900006	RK1/16B8R		7ks	Ωx8	3096,3097,3099, 3128,3132,		
VR3001	J50749102	H0812A002-	-		1kΩB	3137-3139,3147, 3158		
VR3002	J50749202	·· 005-	2KB		2kΩB	C3004,3005,3014,	K14180103	" " 63WV 0.01μI
VR3007	J50749502	" 004-	-5KB		5kΩB	3018,3025,3030, 3031,3033,		(RD871-1FZ-103Z63Z)
VR3004,3005	J50749202	" 003-	-2KB		2kΩB	3037-3045,		
VR3006	J50749104	" 008	-100KB		$100k\Omega B$	3048-3055,3060, 3062-3064,		
		CAPACITOR				3062-3064,		
C3092	K00179001	Ceramic Disc (DD104SL0)	R5C50V	02	)	3073,3075,3078, 3079,3081,3083, 3091,3100,3102,		
C3056	K06172030	(DD104UJ0	30J50V0	(2)		3105,3108-3115, 3117,3118,3120, 3124-3127,3129,		
C3089	K00172040	 (DD104SL04	40C50V	02)		3144,3152-3154, 3157,3159,3161,		
C3055,3057	K06172050	" " (DD104UJ0:	50J50V0	(2)		3162 C3008-3012, 3015-3017,3019,	K13170473	50WV 0.047µF (DB207YF473Z5L5)
C3098	K00173070	(DD104SL0	70D50V	02)		3020,3022,3023, 3027,3028,3035	WIL 42	a makerita ekesit
C3061	K02173080	" " (DD104CH0	80D50V	02	40	C3032,3101,3103, 3151	K40179013	Electrolytic " 1µF (50RE1)
C3145,3160	K00173100	(DD104SL1	00D50V	02		C3106,3107	K40179001	" 'μF (ECE-A1HK01050V1)
C3141	K02175150				H 15pF	C3029,3034, 3080,3082,3084, 3085,3104,3116,	K40129004	" 16WV 10μF (16RE10)
C3143	K06175150	" " " (DD104UJ1			J 15pF	3119,3146,3155, 3156		

Laborator Consister	- CANTON	TRIMMER CAPACITOR		Q4027,4029,4030,	G3309451P	2SC9	45AP			
TC3001,3002	R9100024	ECV1ZW60x40	60pF	4032,4034,4035 4037						
	BELL			Q4019	G3307320G	2SC7:	32TMG	R		
		INDUCTOR								
L3012,3025-3027	L1190092	FL4H-R47M	0.47µH							
L3010,3024	L1190004	FL4H-R68M	0.68µH			DIODE				
L3007	L1190006	FL4H-1R2K	1.2µH	D4006	G2090029	Ge		1N60	)	
L3033,3034	L0021268		2.4µH	D4001-4005.	G2090027	Si		1885		
L3021,3022	L1190027		39µH	4007-4017,4019,	02070021			1355	20	
L3002	L1190033		82µH	4022-4026						
L3030-3032	L1190018		120µH	D4021	G2090158	Zener		DD4	200	
L3001,3003,3006,	L1190020	- COASSERVED F	150µH	D4021				RD4		
3008,3009,3011,	21170020	LISTITIAN	150μ11	125-037-05-25	G2090152			RD5		
3013-3017,3020,				D4020	G2090042			RD8		33
3023,3028				D4027	G2090012	77		WZ1	10	
1 2004 2005 2020	******									
L3004,3005,3029	L1190017	FL5H-102K	lmH			CRYST	AL FIL	TER		
L3018,3019	L1190035	FL7H-392J	3.9mH	XF4001	H1102035	XF-8.	9KP			
						RESIST	OB			
		TRANSFORMER		R4113	J10276229		n Comp	neitic-	S	
T3001	L0020158	700000		******	3102/0229	Calbo	a comp			2.2
T3002,3003	L0020101			D4133	102245220		****			2.25
T3004	L0020101			R4122	J02245220	"	Film	1234-0-230	100,000	22Ω
.5304	L0021118A			R4001,4007,4165, 4166	J02245560	"		**	**	56Ω
	THE STATE OF THE S			(1)509157	Lugite Control of the Lot					
T2007	L0021121			R4013,4043, 4062,	J02245101		***	••	**	1009
T3007	L0021124A			4103,4114,4132, 4136,4140,4145,						
T3008	L0021125A			4147,4149,4155						
T3009	L0021127A			TOWNS ARROWS AND INVESTIG						
T3010,3011	L0021126A		- 1	R4089	J01245221	100		74	TJ	2200
T3012	L0021092A			R4112,4164	J02245221	.,				2205
T3013	L0020404			R4066,4162	J02245271		**	**		2705
				R4005,4168	J02245331				_	3305
				R4097,4121,4144,	J02245471	**		**		-
		CONNECTOR		4163	3022434/1	100	**	"	355	4705
J3001	P0090256	5046-08A	_	Page State Co.	T02245561	10.40		-		
33001	10090230	3040-08A		R4060	J02245561		**	**		5605
				R4148	J02245681	:00	n	**	333	6805
	0.5000011			R4082,4117,4128,	J02245821		**	**	**	8205
	Q5000011	Wrapping terminal C		4152,4159						
				R4057,4074,4084,	J02245102		**	9	(55)	$1k\Omega$
				4102,4124,4126, 4127,4129,4131,						
	AF U	NIT	1	4139,4141,4146.						
Symbol No.	Part No.	Description		4151,4154,4156						
PB-2252	F0002252A	Printed Circuit Board		R4092	J02245122	(3.6)				1.2k
PB-2252A	C0022520	P.C.B. with Components		R4012,4172	J02245152					1.5k
		1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1		R4157	J02245182	300	:#			
				R4036-4039,4138		75.4		166	_	1.8ks
		IC	-	Demonstration - Charles Visit Alberta	J02245222	**	eff.	-55		2.2ks
Q4006,4020	G1090246	AN6552		R4002	J02245272	**	**			2.7ks
Q4006,4020 Q4036	G1090246 G1090063			R4047,4053,4064, 4116	J02245332	***	**	"	••	3.3k
-	FRANCISCHOOL SPINISCH	TA7060AP		Anietse.	TATA TANAH DI BARBANANA				_	
Q4002	G1090257	MC14066BCP		R4096,4171	J02245392	346		**	**	3.9k
Q4013	G1090053	MC14081BCP		R4003,4021,4034,	J02245472	140	100	**	•	4.7k
Q4008	G1090384	MC14538BCP		4035,4041,4044,	the law of					
Q4031,4033	G1090340	MC1496CP		4050,4061,4071, 4073,4093,4094,						
Q4003,4004	G1090077	MC3403P		4107,4108,4111						
Q4001	G1090012	SN16913P		R4067,4080,4087,	J02245562		"			5.6ks
Q4005	G1090084	μPC78L05		4133			7255	0.554	590	J.UK
-	G1090080	μPC78L08		R4070,4109,4115	J02245682	200	100	5.22	34.1	6 01
04028	G1090164	μPC2002H			The state of the s			**	_	6.8ks
	21070104	MI CEUVEII		R4158	J02245822	300	**	æ		8.2k
				R4006,4008,4011, 4016,4025,	J02245103	355	356	166	**	10ks
				4045,4046,4052,						
04000 4000		TRANSISTOR		4058,4063,4068,						
Q4007, 4009-4012,	G3309451P	2SC945AP		4069,4075,4077,						
4014-4018,4021, 4022,4023,4026	64 J			4083,4099,4105, 4110,4120						

R4130,3137,4153, 4170	J02245103	Carbon F	ilm 1/4V	V SJ	10kΩ	C4058-4060	K50177223	Mylar (50F2U223M)	50WV	0.022μF
R4169	J02245123			.,	12kΩ	C4019,4020,4050,	K50177333	10.	**	0.033µF
R4026,4029	J02245153				34-14-2 STUDE	4051		(50F2U333M)		0.055 <b>µ</b> 1
R4017,4085	J02245183				P. 102 C. 102 C.	C4100,4101	K50177473	"	.,	0.047μF
R4072,4078,4104, 4106	J02245223				La restriction			(50F2U473M)		Constant of the second
R4095,4118,4135, 4142,4161	J02245273			.,	27kΩ	C4071,4076	K50177104	" (50F2U104M)		0.1μF
R4019,4020,4098,	J02245333		(34)		33kΩ	C4127	K40179010	Electrolytic (50RE-R47)	"	0.47μF
4119,4123,4125, 4134,4143,4160						C4031,4035,4129	K40179013	(50RE1)	"	1μF
R4018,4086	J02245393		••	**	39kΩ	C4013,4016,4017	K40179009		**	2.2µF
R4014,4048,4049, 4054,4056,4079, 4081,4150	J02245473	500 00	***	**	47kΩ	C4023,4027,4028	K40179011	(50RE2R2)		3.3μF
R4055,4059	J02245683	n n		_	601.0	C4045 4070	V40170013	(50RE3R3)		40.0
R4022-4024.				"		C4045,4070	K40179012	**)	**	$4.7\mu$ F
4030-4032,4065, 4090,4091, 4100	J02245104		155	"	100kΩ	C4003,4004,4006, 4011,4024,4029,	K40129004	(50RE4R7) " (16RE10)	16WV	10μF
R4101	J02245124	100 SW	76	.,	120kΩ	4030,4033,4038, 4039,4041,4043.		(101010)		
R4015,4033,4076, 4088	J02245224	*e: :::::::::::::::::::::::::::::::::::		77	220kΩ	4039,4041,4043, 4048, 4052–4055,4057, 4061,4064,4066,				
R4027,4028,4042, 4051	J02245684		(5.5)	**	680kΩ	4067,4074,4079, 4085–4087,4096,				
R4004,4009,4010	J02245105			"	lMΩ	4098,4099, 4102-4104,4107, 4109,4118,4122,				
		THERMIST	OR			4125,4128				
TH4001,4002	G9090011	SDT-1000				C4018,4049,4056, 4088,4097,4111, 4126	K40129002	" (16RE47)	,,	47μF
		POTENTIO	METER		-	C4073	K40129007	.,	**	100µF
VR4009,4011	J50749501	H0812A0	01-500B	T	500ΩΒ			(16RE100)		
VR4010	J50749102	" 0	02-1KB		lkΩB	C4009	K40129009	,,	**	220µF
VR4004,4008	J50749502	0	04-5KB		5kΩB	112247720002574		(16RE220)		22041
VR4001,4003, 4005,4006	J50703103	EVL-V0A	A00B14		10kΩB	C4072,4075	K40129019	(16RC1000)	••	1000μF
	J50749503	H0812A	50kΩB		50kΩB	C4130	K70167684	The second control of	35WV	0.68µF
VR4002	J50749105	H0812A	1ΜΩΒ		1ΜΩΒ			(CS15E1VR68)		N 3672
		CAPACITO	R		2012109-00-09106-0	C4032,4036	K70127225		16WV	2.2µF
C4090	K00179005	Ceramic d (DD104SI			20pF		K70127685	(CS15E1C2R2)		6.8μF
C4046,4047	K10176471	(DD104B4		В	470pF		K/012/063	(CS15E1C6R8)		6.6µг
C4001,4002,4005,	K14180103				0.01 F	T 4002 4014 4015	7.1100022	INDUCTOR		22 11
4007,4008,4010,	X17100103				0.01µF	L4003,4014,4015	L1190023	FL5H-220K		22µH
4012,4014,4034, 4037,4040,4065, 4068,4077,4078, 4080–4084, 4091–4095,4105, 4106,4108,4110,		(RD871-1	· Z-103Z6	( V C		L4018 L4001,4002, 4004–4007,4009, 4010,4013,4016, 4017	L1190018 L1190020	FL5H-121K FL5H-151K		120µН 150µН
4112,4114-4116,						L4008,4012	L1190017	FL5H-102K		1mH
4119,4120,4123, 4124,4131						L4011	L1190102	S-104K		100mH
C4015,4069,4089, 4113,4117,4121,	K13170473	" (DB207Y)	" 50W F473Z5L5		0.047μF					
4135		MCK GARGE CHAP	, manuscrap-ass	-02				TRANSFORMER		
C4132-4134	K13170103	(DB201YI	 F103Z5L5	5)	0.001µF	T4001,4002	L0021084A			
C4022	K50177102	Mylar (50F2U10	)2M)		0.001µF	101 11		CONNECTOR		
C4021	K50177222	,, (50F2U22	144	0.	.0022μF	J4001	P1090248	IL-D-9S-S3TA2		
C4062,4063	K50177472	(50F2U47	e.	0.	.0047μF		05000011	Wanni- 1	-10	
C4025,4026	K50177682	(3012047	2N1)	0	.0068µF		Q5000011	Wrapping termin	nai C	

### REPAIR PARTS

Part No. F0002251	Description					1/4W	GK	100
F0002251			***		-			
September 1985	Printed Circuit Board	R5152-5161	J02245680	**	Film	(72)	SJ	68n
C0022510	P.C.B. with Components	R5045,5049	J02245101	"	20.	••	7.0	100Ω
		R5106-5110	J02245121	**	100	986	(ee	120Ω
TILLET				"	20	556	"	220Ω
	7.7	LOS CONTRACTOR DE PRODUCTO	J02245331	"	**	••	**	330Ω
		- CONTROL TO THE CONTROL THE CONTROL TO THE CONTROL THE CONTROL TO THE CONTROL TH	J02245391	**		**	***	390Ω
		R5061,5162-5167	J02245102		**	**	100	lkΩ
	MC14012BCP	R5001,5004,5007,	J02245222	"	**	•		2.2kΩ
G1090067	MC14013BCP							
G1090257	MC14066BCP	5028,5031-5033						
G1090126	MC14069UBCP							
G1090053	MC14081BCP	R5116,5118,5120,	J02245272	.,	**	**	**	2.7kΩ
G1090149	MC14510BCP							
G1090364	MN1201A							
G1090367	MN9005	5141,5143,5145,						
G1090365	SN7406N	5147,5149,5151						
G1090378	TBP18SA030N-0378	R5086	J02245332	250	22.	220		3.3kΩ
	(BPF SELECT)	R5101-5106	The policy of the second		**	**	.,	3.9kΩ
G1090379	TBP18SA030N-0379	R5055	J02245472	.,.	**			
	(TX BAND SELECT)	R5058	J02245562	**			.,	5.6kΩ
G1090380	TBP18SA030N-0380 (VCO SELECT)	R5136,5138,5140, 5142,5144,5146,	J02245822	,,	990	900	,,	
		R5002,5003,5005,	J02245103	90.				10kΩ
	TRANSISTOR	5006,5008,5009,						
G3107190R	2SA719R							
G31073310								
14441,		5024,5026,5027, 5029,5030, 5034-5039, 5111-5113						
G3309451P	25C945AP	CONTRACTOR CONSTRUCTION OF THE PARTY OF THE	102245122		76.	227	5	12kΩ
033074311	25074374	5119,5121,5123,	302243123	200	20,	(45.5)	2.0	12846
G3313170R	25C1317D	5125,5127,5129,						
G5515170K	25C1317K	5131,5133,5135						
		DEOSC	102245152	947	1991	997		161.0
								15kΩ
		174.332.77.22.2		1000	1000			18kΩ
C2402000V	2002001/		302243333	350	2550	1056	55	33kΩ
G3402880K	2SD288K			6289		0.000	San .	
		R5065	J10246333	**				
			J. 184			211	7-7-10-1	Carlo Charles
			J02245473	**	Film	***	SJ	$47k\Omega$
The second secon								
G2090027	Si 1SS53	0071,0075,0115						
- 1-44-11		R5082	J02245563		3.5	**	**	56kΩ
- 1		R5075-5078	J02245823	•	**	**		82kΩ
		R5043,5062,5072, 5074,5081,5084, 5085,5114	J02245104	,,	**	*	,,	100ks
G2090201	Zener PD2 2FD2	D5069 5070	102245224	991		1220	22	220ks
CANCEL STREET, CO.						_		
32090193	W KD3.0EB3	T. 3 (9/2 (5.0))				_		270ks
C2000101	Подраг		1.20 March 48/70 (4.20 MORE)	100	192	- 52	1.4	470ks
		The second second	The second secon				- /40	JOOK-
G2090155	" KD9.1EB2	R5052	J02245105		**	**		1MΩ
	10.000455							
P2000000				-				
	The state of the s		2.22.32				\$11000000	
P3090036	116-40-30-114 40P	RB5002-5004	J40900025	100000000000000000000000000000000000000			16W	100000000000000000000000000000000000000
		RB5001	J40900024	RK1/1	16B5R10K		<b>M</b>	10kΩx
	1 1 27	RB5005	J40900011	RK1/1	16B6R10K	S 8	40	10kΩx
	RES fOR							
J02245569	Carι Film 1/4W SJ 5.6Ω							
							_	
	G1090126 G1090053 G1090149 G1090364 G1090367 G1090365 G1090379 G1090380  G3107190R G3107331Q  G3309451P  G3313170R  G3402880K  G2090029 G2090027  G2090193 G2090155  P3090033 P3090036	G1090068 MC14011BCP G1090176 MC14012BCP G1090067 MC14013BCP G1090257 MC14066BCP G1090053 MC14081BCP G1090053 MC14081BCP G1090364 MN1201A G1090365 SN7406N G1090378 TBP18SA030N-0378 (BPF SELECT) G1090379 TBP18SA030N-0379 (TX BAND SELECT) G1090380 TBP18SA030N-0380 (VCO SELECT)  TRANSISTOR G31071301Q 2SA733AQ  G3309451P 2SC945AP G3313170R 2SC1317R  G2090029 Ge 1N60 G2090027 Si 1SS53  G20900201 Zener RD3.3EB3 G2090181 "HZ7B1L G2090155 "RD9.1EB2  IC SOCKET P3090036 116-16-30-114 16P P3090036 116-40-30-114 40P	IC	IC	IC	IC	C	C

2000	224917500	CAPACITOR		PLL I	
C5045	K00175101	Ceramic Disc 50WV SL 100pF	Symbol No.	Part No.	Description
		(DD105SL101J50V02)	PB-2257A	F0002257A	Printed Circuit Board
C5043	K00175221	" " " 220pF		C0022570	P.C.B. with Components
05042	W0017577	(DD107SL221J50V02)			
C5042	K00175271	" " 270pF			
C5027 5040	V10176103	(DD107SL271J50V02)	06060	C1000206	IC HD10661B
C5037-5040	K10176102	" " " 0.001μF	Q6060 Q6055	G1090296	HD10551P
CENNI ENEN ENEN	V14190102	(DD104B102K50V02) " " 63WV 0.01"F	Q6022,6034	G1090153 G1090087	MB8718M MC4044P
C5001,5050-5052	K14180103	" " 63WV 0.01μF (RD871-1FZ-103Z63V)	Q6022,6034 Q6036	G1090087 G1090257	MC14066BCP
C5018-5029	K13170473	" " 50WV 0.047μF	Q6059	G1090237 G1090108	MC14518B
C3016-3029	K13170473	(DB207YF473Z5L5)	Q6035	G1090108	SN74LS26N
C5030,5049	K19149021	Semiconductor Ceramic	Q6013,6015	G1090033	SN74LS196N (T.I)
00000,0017	117117021	25WV 0.047µF	Q6033	G1090109	SN74LS390N
517		(UAT08X473K-L45AE)	Q6012	G1090017	SN74S11N
C5032-5036,5041,	K19149025	" " 0.1μF	Q6011	G1090371	SN74S113N
5044,5046,5054	K17147025	(UAT13X104K-L46AE)	Q6038,6053	G1090012	SN16913P
C5013	K50177222	Mylar 50WV 0.0022μF	Q6043	G1090062	SN76514N
		(50F2U222M)	Q6014	G1090376	TBP18SA030N-0376
C5015	K50177223	" " 0.022μF	11000		(PLL DATA-1)
		(50F2U223M)			
C5002,5008	K50177104	" " 0.1μF			
garanteen Antonia		(50F2U104M)			TRANSISTOR
C5016,5048	K40179013	Electrolytic 50WV 1µF	Q6061,6063	G3090020	JF1033B
2000000		(50RE1)	Q6047	G3090005	MPS-A13
C5047	K40149001	" 25WV 4.7μF	Q6041,6051,6062	G3305350B	2SC535B
		(25RE4R7)	Q6023-6025,6046	G3307320B	2SC732TM-BL
C5005,5006,5010,	K40129004	" 16WV 10μF	Q6026,6027,6030,	G3309451Q	2SC945AQ
5012,5031	The second secon	(16RE10)	6037,6039,6042,		
C5011	K40129001	" " 330μF	6044,6050,6052, 6054,6056,6057,		
The state of the s		(16RE330)	6064		
C5017	K40109003	" 10WV 330μF	Q6001-6006,6008,	G3319230O	2SC1923-O
		(10RE330)	6018,6020,6029, 6032,6048		
C5003,5007	K40129006	" 16WV 470μF	7611-00-001		
		(16RE470)	Q6031,6040,6045,	G3319590Y	2SC1959Y
C5004,5009,5055	K40129019	" 1000μF	6058,6065		II
Nacial Mechanic		(16RC1000)	Q6007,6019	G3320260	2SC2026
C5014	K70167224	Tantalum 35WV 0.22μF	Q6021	G3324070	2SC2407
		(CS15E1VR22M)	Q6010	G3408820Q	2SD882Q
C5053	K70167474	0.47μF			
		(CS15E1VR47)			
			00010	G200000	FET CP
			Q6049	G3090035	2SK19TM-GR
		INDUCTOR	Q6016,6017	G3090052	2SK206-3
L5003	L2030068	1.8mH	Q6009,6028	G4800740L	3SK74L
L5001,5002	L2030067B	3mH			
					DIODE
		CONNECTOR	D6023	G2090029	Ge 1N60
J5002	P0090220	CONNECTOR 5045-04A 4P	D6003,6006,6008,	G2090029 G2090027	Si 18853
J5002 J5001	P0090220 P0090221	5045-05A 5P	6010,6012,6014,	G2090027	31 13333
J5005	P0090221 P0090222	5045-06A 6P	6021		
J5004	P0090222 P0090224	5045-08A 8P	D6017	G2090118	Schottky 1SS97
J5008	P1090224	3024-08CH 8P	D6017 D6027	G2090118 G2090043	Varactor MV104
J5003,5006	P1090230 P0090225	5045-09A 9P	D6027	G2090043 G2090107	varactor MV104
J5003,3006 J5009	P1090223	3024-09CH 9P	6005,6007,6009,	G2090107	1123
J5009 J5007	P1090231 P0090227	5045-11A 11P	6011,6013,6019,		
33001	10090227	5045-11A 11F	6020,6028		
			D6016,6022,6029,	G2090193	Zener RD5.6EB3
			6030	02070173	KD3.0LB3
			D6015,6018,	G2090155	" RD9.1EB2
					INDV.INDE
			6024-6026		54-1-6-174

		CRYST	AL				R6028,6029,6031,	J02245103	Carb	on Film	1/41	V SJ	10kΩ
X6003	H0102431	HC-1	8/U	20.0	MH:	Z.	6093,6106,6121,						
X6001	H0102432			48.6	15M	Hz	6122,6132,6138, 6139,6141,6152,						
X6002	H0102433	100	,	54.2	8MI	łz	6165,6173,6180,	P. Dales					
					-		6184,6185,6187,						
		RESIST	OR				6209,6210	NIO ELIU					
R6055	J10276339	THE SPECIAL SECTION	on Comp	ositio	n		R6201	J02245153	.,		.,	**	15kΩ
		N.E-Catalon		1/20		3.3Ω	R6079	J02245183					18kΩ
R6073	J02245479	"	Film	1/40			R6002,6004,6008.	J02245103		**		**	22kΩ
R6036,6039,6091,	J02245100	.,	"	**		10Ω	6010,6015,6020,	302243223	1555	25	55		22832
6110,6112,6117, 6153,6197						1022	6025,6030,6094, 6107,6133,6142, 6151,6163,6164,						
R6034	J02245180		**	**	**	18Ω	6172,6179,6188						
R6087,6115,6158	J02245220	- 17	**	**		22Ω	R6052,6100,6120,	J02245333		"	- ,,	2000	33kΩ
R6042,6045	J02245390	.,	**	**	"	39Ω	6169						551185
R6127	J10246680	"Co	mpositio	on "	G	Κ 68Ω	R6178	J02245393	.,		77		39kΩ
R6069,6198	J02245680	"	Film	"	-	68Ω	R6037,6049,6051.	J02245473		.,			47kΩ
R6082	J02245820	311	"	**	**		6099,6101,6206	302210173	8.52		- 55	3053	TINGS
R6006,6012,6017,	J02245101	.,,	"	,,		100Ω	R6068,6086	J02245563			**	**	56kΩ
6022,6027,6032,						10011	R6076,6168	J02245683		"		300	68kΩ
6040,6041,6043, 6063-6065,6071,							R6114,6177	J02245823	_				
6075,6077,6081,							R6050,6098,6104.		366		"		82kΩ
6095,6096,6103, 6109,6129,6130, 6134,6137,6143,							6105,6157,6161, 6162,6181	J02245104	3.55		155	5512	100kΩ
6145,6146,6148,							R6092,6192,6195	J02245124		ir	166		120kΩ
6150,6167,6171, 6174,6176,6182,							R6128	J10246124		Comp			120822
6189,6191,6204,								7102,012,		Comp			120kΩ
6212,6213							R6207	J02245334		Film	1/11		330kΩ
R6056	J02245151			**	**	150Ω	R6215	J02245394	144	,,		.,	390kΩ
R6054,6066,6067	J02245181	286	ee	,,	**	180Ω	R6126	J02245565	.,	**		**	5.6MΩ
R6044,6053,6074,	J02245221	**	"			220Ω	10120	302243303				55	J.0M32
6102						220			BI OCI	K RESIS	TOP		
R6033,6035	J02245271	999		,,	.,	270Ω	RB6001	J40900025		5B8R2,21		6W -	21.0.0
R6090,6135,6199	J02245331					330Ω	RB6002	J40900023	-	5B8R100			
R6070,6205,6214	J02245391	(40)		.,,	***	390Ω	KD0002	340300013	KK1/10	JDOKIOO	K 1/1	OW	OUKZZX
R6048,6072,6078.	J02245471	100	100	**	"	STATE OF THE STATE			DOTES	UT10115			
6097,6131,6144,	3 4 2 2 1 4 1 1 1 2					7,000	VDCOO2	151740501		NTIOME		_	500m
6149,6154							VR6002 VR6001	J51740501		B3AA00			500ΩB
R6190	J10246471		Comp	ocition			VK6001	J51752503	RGS	6-FAN 5	UKB		50kΩB
10170	310240471	6520	Comp			470Ω					_	_	
R6175	J02245561	377	Film	1/4 W		560Ω	00102	**********		CITOR	10000		
R6085.6155	J02245681		r mm		21		C6183	K00172010	\$100 mm	mic Disc			.1pF
R6170	J02245821		0			680Ω	06116	200220000000000000000000000000000000000	2777	104SL01			Description
A state of the second s				_		820Ω	C6115	K00172020	350	356			2pF
R6038,6047,6057, 6061,6088,6108.	J02245102	0.462	186	1365	**	lkΩ				104SL02		_	
6111,6113,6116,							C6062,6064,6122	K06172030	••	••			3pF
6123,6124,6136,							PARTE VICTOR SET SET SET	100 TOTAL ALICE SOCIETY IN	(DD	104UJ03	0J50V	702)	
6140,6166,6183, 6186,6196,6208							C6089,6172,6268,	K00172030	32	**		SL	3pF
MARINE STATES	201200 1						6269		(DD)	104SL03			
R6089	J10246102	800	Comp				C6214	K06172040	396	396		UJ	4pF
D. (10.0 (10	72219511211105		1000			lkΩ			(DD)	104UJ04	0J50V	(02)	
R6125,6193,6194	J02245152	26	Film	***	SJ	1.5kΩ	C6219	K00172050		**	**	SL	5pF
R6046,6058-6060,	J02245222	920	**	**	**	$2.2k\Omega$			(DD)	104SL050	0C501	V02)	
6062,6118,6119, 6156,6200,6211							C6063,6121,6124	K06172050		**		UJ	5pF
0150,0200,0211									(DD)	104UJ050	0J50V	(02)	
R6159	J10246222	**	Comp	ositior	1		C6112	K00173060	100		,,	SL	6pF
-41-21-22-3			-	1/4W	GK	2,2kΩ			(DD)	04SL06			
R6147	J02245392	20.	Film	/100	SJ	3.9kΩ	C6087	K00173090	••		,,	.,	9pF
R6202,6216	J02245472	VII.		**	ee.				(DD)	104SL09	D501	V02)	27
R6160	J02245562	••	•	**	"	5.6kΩ	C6185	K02173090		.,	Seattle State of the State of t	and the second	19pF
R6083,6084	J02245682	.,	**		**	6.8kΩ		netruma sta stelle	(DD1	104CH09			
R6080,6203	J02245822	**	***	36		8.2kΩ	C6005,6012,6019.	K06173100	"	,,	140 HOLES & ST.		10pF
R6001,6003,6005, 6007,6009,6011, 6013,6014,6016	J02245103	See:	700	599	**	10kΩ	6026,6034,6042 6171,6216,6218		0.000,000	104UJ100			. Opi
6013,6014,6016, 6018,6019,6021,							C6181,6203	K02173100	86.5	**		CH	10pF
0010,0017,0021,							150	53.00	70.000.000	04CH10			

C6191,6207,6212, 6220	K00173100	" " SL 10pF (DD104SL100D50V02)	C6186,6187,6190, 6192,6199,6201,	K14180103	Ceramic Disc 63WV (RD871-1FZ-103Z63	TOTAL STREET
C6004,6011	K06175120	" " UJ 12pF (DD104UJ120D50V02)	6206,6209,6210, 6213,6215,6217, 6221,6222,		(10071-112-105205	10
C6118	K02175120	" " CH12pF (DD104CH120J50V02)	6226-6228,6230, 6233,6234,6236,			
C6194	K00175120	" " SL 12pF (DD104SL120J50V02)	6238,6244,6245, 6247,6249,6250, 6254,6257,			
C6018,6033,6041, 6065,6202,6204	K06175150	" " " UJ 15pF (DD104UJ150J50V02)	6260-6265 C6068,6071-6077,	K13170473	CANA	0.045.5
C6085,6092	K00175150	" " SL 15pF (DD104SL150J50V02)	6097,6102,6103, 6109,6127,6130,	K131/04/3	" " 50WV (DB207YF473Z5L5)	7.55
C6025,6028,6036, 6044	K06175180	" " UJ 18pF (DD104UJ180J50V02)	6133,6138,6155, 6160,6165,6241, 6242,6258,6259,			
C6251	K00179005	" " SL 20pF (DD104SL200J50V02)	6266 C6104	K50177104	Mylar	01.5
C6006,6013,6020, 6253	K06175220	" " UJ 22pF (DD104UJ220J50V02)	C6110	K40179010	(50F2U104M)	0.1μF
C6223,6225	K00175220	" " SL 24pF (DD104SL240J50V02)	OXXII.000.77		Electrolytic " (50RE-R47)	0.47μF
C6053,6056,6084	K00175270	" " " 27pF	C6069,6081,6164, 6239	K40179013	,, (50RE1)	lμF
C6027,6035,6043	K06179006	(DD104SL270J50V02) " " UJ 30pF	C6150,6196,6197	K40179001	(ECE-A1HK010 50V	
C6123,6255,6256	K06175330	(DD104UJ300J50V02) " " 33pF (DD104UJ330J50V02)	C6003,6010,6017, 6024,6032,6040, 6046,6052,6106,	K40129004	" 16WV (16RE10)	10μF
C6211	K00175330	" " SL 33pF (DD104SL330J50V02)	6108,6128,6132, 6135,6141,6143, 6146,6148,6193,			
C6167,6168	K06179007	" " UJ 36pF (DD104UJ360J50V02)	6198,6235,6240, 6243			
C6184,6205	K02175390	" " CH39pF (DD105-257CH390J50V02)	C6126,6200,6208, 6237,6246,6248,	K40129008	" (16RE33)	33pF
C6054,6055	K00179009	" " SL 43pF (DD104SL430J50V02)	6267 C6270	K40129001	Carolinae Novem	220 5
C6086,6091,6188, 6189	K00175470	" " 47pF (DD104SL470J50V02)	C0270	K40129001	(16RE330)	330μF
C6088,6090,6224	K00175560	56pF				
C6047,6048	K00179011	(DD104SL560J50V02) " " 62pF (DD104SL620J50V02)	TC6001-6003	K91000075	TRIMMER CAPACITO TZ03R200E 20pF	)R
C6152,6154,6229, 6232	K00175680	" " 68pF				
C6272	K02175680	(DD104SL680J50V02) " " CH68pF	T6001-6003,6006	L0020869	TRANSFORMER	
C6153,6231	K00175121	(DD107CH680J50V02) 120pF	T6004,6005 T6007-6009	L0020868 L0020128		
		(DD105SL121J50V02)	T6010,6011	L0020883		
C6001,6008,6015, 6022,6030,6038,	K13170102	0.001μF	T6012	L0021131		
6057,6058,6061,		(DB200YF102Z5L2)	T6013	L0021132		
6078-6080,6114,			T6014	L0021133		
6137,6140,6170, 6195,6252			T6015	L0020345		
2 21361111	W14100100	1994 HOME 100 HOME 10	T6016	L0020867		
C6002,6007,6009, 6014,6016,6021,	K14180103	" " 63WV 0.01μF	T6017,6019,6021	L0020127		
6023,6029,6031,		(RD871-1FZ-103Z63V)	T6018	L0020110		
6037,6039,6045, 6049-6051,6059,			T6020	L0020866		
6060,6066,6067,			T6021	L0020127		
6070,6082,6083, 6093-6096 6098-6101,			T6022	L0020178		
6105,6107,6111,						
6113,6116,6117, 6119,6120,6125,			27072202		INDUCTOR	
6129,6131,6136,	707		L6032	L1190113	FL3H-R22M	0.22µH
6139,6142,6144,			L6012	L1190109	FL4H-R33M	0.33µH
6145,6147,6149, 6151,			L6013,6033,6034	L1190092	FL4H-R47M	0.47µH
6156-6159,			L6008,6009	L1190006	FL4H-1R2M	1.2µH
6161-6163,6166,	1		L6015	L1190014	FL4H-100K	10µH
6169,6173-6181			L6035,6036	L1190027	FL5H-390K	39µH

L6010,6011	L1190029	FL5H-470K 47µH	D7002,7004	G2090003	Si		V06B		4 5
L6018	L1190020	FL5H-151K 150µ	H D7001	G2090079	Si		S2VB	10	
L6016	L1190024	FL5H-221K 220µ		G2090155	Zener		RD9.		2
L6001-6007	L1190038	FL5H-271K 270µ	J11 J14-J17-14-14-14-1	G2090153	,,		RD10		
L6017,6019-6022,	L1190120	FL5H-471K 470µ		G2090199	,,		RD12		
6025-6027				02070177			11071		-
L6014,6024,6028, 6031	L1190017	FL5H-102K 1mH			RESIST	OR			
L6029,6030	L1190035	FL7H-392J 3.9m	H R7051	J02245100	Carbo	ATT A STEEL STEEL	1/4W	SJ	10Ω
L6023	L2030067B	SN8S-500	R7014,7016	J02245330	"			**	33Ω
			R7045	J02245151	**	**		**	150Ω
		111,127,18	R7012	J02245221	**	**		,,	220Ω
		CONNECTOR	R7006	J10276221		Comp	osition		
J6002	P0090250	5046-02A		3/58/40/69/69/6			1/2W	GK	220Ω
J6004-6007	P0090218	5045-02A	R7003,7005,7047	J02245331		Film	1/4W		330Ω
J6003	P0090219	5045-03A	R7011	J02245471	.,	.,		77	470Ω
J6008	P0090252	5046-04A	R7035	J02245561		100	196		560Ω
J6009	P0090253	5046-05A	R7008,7009,7042,	J02245102	**	(99)	36	**	lkΩ
J6001	P0090223	5045-07A	7053	302243102					INSS
J6010	P0090257	5046-09A	R7041	J01245102	***	**		TI	lkΩ
		33.10.03.1	R7038	J02245122	300	7007	366		1.2kΩ
		100-10-2	R7043	J01245332	21		41		3.3kΩ
	Q5000011	Wrapping terminal C	R7010,7013,7015,	J01245352 J02245472	.,		7.		4.7kΩ
	Q3000011	wrapping terminar C	7033	302243472	(69)	2777	1553	23	T. 1832
			R7025,7027	J02245562	848	**	•••		5.6kΩ
			R7046	J02245682	992	500	100	"	6.8kΩ
			R7024,7026	J02245822	100	((49))	1000		8.2kΩ
			R7002,7007,7020,	J02245103	1663	166	266	200	10kΩ
AND ASSESSED	REG	UNIT	7032,7034,7037,	Didde Better					
Symbol No.	Part No.	Description	7044	in the second					
PB-2258A	F0002258A	Printed Circuit Board	R7040	J02245273	.,	**	**	**	27kΩ
15-223014	C0022580	P.C.B. with Components	R7004,7023,7028, 7029,7049	J02245473	366				47kΩ
			7029,7049						
			R7036	J01245473	in a	100	See	-	$47k\Omega$
		IC	R7001,7017,7018,	J02245104	188	3,65	0955	SJ	100kΩ
Q7014	G1090126	MC14069UBCP	7030,7039,7050						
Q7013	G1090029	MC14071BCP	R7031	J02245184	**	LES .	100	••	180kΩ
Q7027	G1090084	μPC78L05	R7021,7022	J02245224		**	**	**	220kΩ
Q7010	G1090080	μPC78L08	R7019	J02245334			**		330kΩ
Q7024	G1090377	μРС7908Н	R7052	J02245474	300	"		n	470kΩ
		TRANSISTOR			POTEN	TIOME	TER		
Q7026	G3107190Q	2SA719Q	VR7001	J50749202	H081	2A003-	2KB		2KB
Q7001,7015,7016, 7020,7025	G3107331Q	2SA733AQ							
Q7006,7022	G3205360K	2SB536K			CAPAC	ITOR			
Q7019	G3207720Q	2SB772Q	C7021	K13170102	-	nic Disc	50W	V	0.001µF
Q7003,7005.	G3309451Q	2SC945AQ				00YF10			
7007-7009,7011, 7012,7017,7018, 7021	33307431Q	250773714	C7011,7016,7018, 7020,7023,7033, 7035,7037	K14180103		71-1FZ	63W	V	0.01μF
	G3320020L	2SC2002L	C7040	K19149013					50WV
Q7023	GUULUUL				(UAT	705X10	3KL05	AE)	0.01μF
Q7023 Q7004	G3325620Y	2SC2562Y				¥	**		0.01μF
		2SC2562Y 2SD882Q	C7039	K50177103	Myla				
Q7004	G3325620Y	CONTRACTOR	C7039	K50177103 K50177153		2U103N			0.015µF
Q7004	G3325620Y	2SD882Q			(50F)		ſ) 		0.015μF
Q7004	G3325620Y G3408820Q	2SD882Q INSULATOR	C7013		(50F)	2U103N	ſ) 		
Q7004	G3325620Y G3408820Q Q9000033	2SD882Q INSULATOR B-17 (for 2SB536K)		K50177153	(50F) (50F)	2U103N	M)		
Q7004	G3325620Y G3408820Q	2SD882Q INSULATOR	C7013	K50177153	(50F) (50F) (50F)	2U103N 2U153N 2U223N	M) M)		0.022μF
Q7004	G3325620Y G3408820Q Q9000033	2SD882Q  INSULATOR  B-17 (for 2SB536K)  AC316A (for 2SC2562Y)	C7013 C7012,7014 C7028,7030	K50177153 K50177223 K50177333	(50F) (50F) (50F) (50F)	2U103N 2U153N 2U223N 2U333N	M) M) M)	6	0.015μF 0.022μF 0.033μF
Q7004	G3325620Y G3408820Q Q9000033 Q9000125	2SD882Q INSULATOR B-17 (for 2SB536K)	C7013 C7012,7014	K50177153 K50177223	(50F) (50F) (50F) (50F) Elect	2U103N 2U153N 2U223N	M) M)	6	0.022μF

C7008	K40179013	Electrolytic 50WV 1μF			RESISTOR
		(50RE1)	R7104	J10276560	Carbon Composition
C7002,7005,7007,	K40129004	" 16WV 10µF			1/2W TJ 56Ω
7009,7010,7015, 7017,7019,7029,		(16RE10)	R7107,7122	J02245101	" Film 1/4W SJ 100Ω
7031,7032,7034,		September 1990	R7121	J02245221	220Ω
7036			R7114	J02245471	" " 470Ω
C7022,7024,7025	K40129016	" 22μF	R7102,7118	J02245561	560Ω
		(16RE22)	R7109	J01245561	" " TJ 560Ω
C7004,7006	K40129002	" 47μF	R7101	J02245681	" " SJ 680Ω
		(16RE47)	R7106	J02245821	" " 820Ω
C7026	K40149008	" 25WV 10μF	R7120,7124	J02245102	" " " 1kΩ
		(25RE10)	R7125	J01245102	" " " TJ 1kΩ
C7027	K40149003	" 100μF	R7110	J02245152	" " SJ 1.5kΩ
		(25RE100)	R7127	J01245152	" " TJ 1.5kΩ
C7001	K40149017	" 1000μF	R7123	J02245182	" " " SJ 1.8kΩ
		(25RC1000)	R7128	J01245222	" " TJ 2.2kΩ
C7038	K70167474	Tantalum 35WV 0.47µF	R7112	J02245222	" " SJ 2.2kΩ
		(CS15E1VR47M)	R7119,7126	J02245272	" " " 2.7kΩ
C7041	K70167105	1μF	R7103,7108,7129	J02245472	" " 4.7kΩ
	Pills	(CS15E1V010M)	R7115,7116	J02245103	" " " 10kΩ
			R7105	J02245123	" " 12kΩ
			R7111,7130	J02245223	" " " 22kΩ
		INDUCTOR	R7113	J02245104	" " " 100ks
L7001	L2030068		R7117	J02245155	" " " 1.5MS
L7002	L1190036	FL11H-683J 68mH			POTENTIOMETER
			VR7103	J50749102	H0812A002-1KB 1kΩB
			VR7101,7102	J50749202	H0812A003-2KB 2kΩB
		TRANSFORMER	VR7105	J50710103	V10K8-1-2 10KB 10KB
PT7001	L3030094		VR7104	J50710105	V10K8-1-2 1MB 1MΩB
		RELAY			CAPACITOR
RL7001	M1190015	G2V-2	C7106	K00175120	Ceramic Disc 50WV SL 12pF
RL7002	M1190032	G2E	- CONTRACTOR		(DD104SL120J50V02)
			C7124	K00179006	24pF
			1	2102012007	(DD104SL240J50V02)
		CONNECTOR	C7110	K00179011	62pF
J7001	P0090186	EMCS0352M	1		(DD104SL620J50V02)
P7001	P1090249	EMCM0201	C7109	K00179013	" " " 91pF
			7	1100113010	(DD105SL910J50V02)
			C7101	K00175471	470pF
			1	- APACE 2 APRIC 2	(DD109SL471J50V02)
用が見るです	ALC	UNIT	C7111,7112,7114,	K13170102	" " 0.001µI
Symbol No.	Part No.	Description	7120,7121		(DB200YF102Z5L2)
PB-2260	F0002260	Printed Circuit Board	C7104,7105,7115,	K14180103	" " 63WV 0.01µI
	C0022600	P.C.B. with Components	7117,7122	111100103	(RD871-1FZ-103Z63V)
	00022000	Treast with components	C7102,7103,7107,	K13170473	" " 50WV 0.047µI
	No. in contrast		7108	K13170473	(DB207YF473Z5L5)
		TRANSISTOR	C7113,7116,7118,	K40129004	Electrolytic 16WV 10µF
Q7101,7102,7105	G3107331P	2SA733AP	7123	KT0127004	(16RE10)
Q7101,7102,7103 Q7103	G3107331P G3309451P	2SC945AP	C7119	K70167474	Tantalum 35WV 0.47µl
21103	03303431F	20071371	1 (/119	K/010/4/4	(CS15E1VR47)
					(CS13E1VK4/)
		FET			
Q7104	G3090035	2SK19TM-GR			TRIMMER CAPACITOR
Q/104	03030033	25K171M-GK	TC7101	K91000019	ECV-1ZW10x40 10pF
			10/101	K31000019	LC V-12W10X40. 10pr
		DIODE			
D7105 7100	C2000027	DIODE			INDUCTOR
D7105-7108	G2090027	Si 1SS53	17101	1,0020201	INDUCTOR
D7101-7104	G2090118	Schottky 1SS97	L7101	L0020301A	DIGITION 100
D7109	G2090015	Zener RD6.2EB3	L7102	L1190020	FL5H-151K 150µI
	12130				
					TD / WOED
			7210:		TRANSFORMER
			T7101	L0021159A	

CONNECTOR			RELAY	C7249	K30275161	Dipped mica 500WV 160p
CONNECTOR	RL7101	M1190015	G2V-2 DC12V			
				C7204,7242,7252	K30275201	200p
P17101-7103	J7101	P0090186	Control of the Contro	C7218,7230,7245	K30275241	240p
P7101-7103   P1090255				C7254	K30275271	2700
PLUS	PJ7101-7103	P1090255	TMP-JA	C7223,7237,7247	K30275301	" " 300p
P1090249			PLUG	C7235	K30275331	" " 330 <sub>I</sub>
PL7101	P7101	P1090249		C7222	K30275361	" " 360p
PL   PL   PL   PL   PL   PL   PL   PL			LAMP		K30275391	" " 390p
FH7101	PL7101	Q1000034	BF311-04080A 14V 0.2A	C7208	K30275431	" " 430p
CP210	FH7101	P2000003		C7231,7240	K30275471	470p
Symbol No.         Pert No.         Description         C7228,7233         K30275561         " (LCQ18561J5)           PB-2259A         F0002259A         Printed Circuit Board         C7201,7221         K30275681         (LCQ18681J5)           PB-2259A         Printed Circuit Board         C7201,7221         K30275681         (LCQ18681J5)           DF201-7218         G2090027         Si ISS53         C7219         K30279093         (LCQ1911J5)           C7257         K30275120         CAPACITOR         C7210         K3027905         (DM19D122J5)           C7262         K30275120         CAPACITOR         C7210         K30279125         (DM19D122J5)           C7262         K30275120         CPAPACITOR         C210         K30275120         CR201180J5         C7205         K3027520         CR201180J5         C7205         CR201220015         CR2022005         CR2022005         CR2022005 <td></td> <td></td> <td></td> <td>C7216</td> <td>K30275511</td> <td>" " 510p</td>				C7216	K30275511	" " 510p
PB-2259A         F0002259A         Printed Circuit Board (P.C.B. with Components)         C7201,7221         K30275681         " (LCQ1868115)           C0022590         P.C.B. with Components         C7207,7209,7214, 7224         K30275911         " " " (LCQ191115)           D7201-7218         G2090027         Si 18S53         C7217,7226         K30279093         " " " (LCQ219115)           D7201-7218         G2090027         Si 18S53         C7219         K30279093         " " " (DM19D10215)           C7257         K30275120         Dipped mica S0WV (LCQ112015)         2 F         C7210         K30279125         " (DM19D13215)           C7262         K30275180         Dipped mica S0WV (LCQ118015)         1 Rsp         C7203,7212         K30279124         " (DM19D15215)           C7248,7255         K30275240         " " 20pF (LCQ1220015)         C7205         K30279124         " (DM19D16215)           C7234,7241         K30275240         " " 20pF (LCQ124015)         C7264-7283         K13170473         Ceramic Disc S0WV (DM19D14215)           C7224,7241         K30275390         " " 47pF (LCQ124015)         L7225         L0021115         Ceramic Disc S0WV (DM204)           C7224,7253         K30275500         " " 50pF (LCQ124015)         L7225         L0021115         O15µH           <	Symbol No.			C7228,7233	K30275561	" " 560p
DIODE		F0002259A	Printed Circuit Board	C7201,7221	K30275681	" " 680p
D7201-7218   G2090027   Si 1SS53   C7217,7226   K30279093   " (DM19D10215)					K30275911	" " 910p
CAPACITOR	D7201-7218	G2090027	TOTAL SAME AND	C7217,7226	K30279093	" " 1000
C7257   K30275120   Dipped mica   S00W   12pF   (LCQ1210JS)   (LCQ11180JS)   (C7203,7212   K30279124   (DM19D132JS)   (DM19D152JS)   (DM19D162JS)   (DM19				C7219	K30279095	1200
C7262   K30275180   "   18pF   C7203,7212   K30279124   " (DM19D152J5)	C7257	K30275120		C7210	K30279125	" " 1300]
C7248,7255   K30275200   "	C7262	K30275180		C7203,7212	K30279124	. " 15001
K30275240	C7248,7255	K30275200	(LCQ11180J5)	C7205	K30279103	" " 1600
C7234,7241   K30275390			(LCQ12200J5)		K30279127	2400]
C7243,7263   K30275470   " 47pF   C7225   L0021115   0.15µH	C7234.7241		(LCQ12240J5)	C7264-7283	K13170473	Ceramic Disc 50WV 0.047
C7227   K30275510   "   "   "   51pF   L7226   L0021115   0.15μH			(LCQ12390J5)			
C7227         K30275510         " " " " " " " " " " " " " " " " " " "		54.519.594.5V4.856.514.54.53.		L7225	L0021115	
C7246,7253         K30275560         " (LCQ12560J5)         " 56pF         L7219,7223,7224         L0021112         0.44μH           C7206         K30275680         " 68pF         L7220,7221         L0021113         0.68μH           C7220         K30275820         " 82pF         L7218         L0021101         0.95μH           C7236,7258-7260         K30275910         " 91pF         L7207         L0021107         1.3μH           C7261         K30275101         " 100pF         L7211,7212         L0021102         1.7μH           C7232         K30275111         " 110pF         L7205         L0021103         2.8μH           C7239,7244         K30275121         " 120pF         L7201         L0021100         3.3μH           C7213,7251         K30275131         " 130pF         L7201         L0021100         3.3μH           C7213,7251         K30275131         " 130pF         L7201         L0021101         4.6μH	C7227	K30275510		L7226		
C7206   K30275680   "   "   68pF   L7220,7221   L0021113   0.68μH     (LCQ12680J5)   L7213,7217   L0021109   0.85μH     (C7220   K30275820   "   "   82pF   L7218   L0021111   0.95μH     (LCQ12820J5)   L7210,7214,7215   L0021107   1.3μH     (LCQ12820J5)   L7207   L0021105   1.5μH     (LCQ12910J5)   L7204   L0021102   1.7μH     (LCQ12101J5)   L7204   L0021102   1.7μH     (LCQ12101J5)   L7208,7209   L0021108   1.9μH     (LCQ12101J5)   L7208,7209   L0021106   2.3μH     (LCQ17111J5)   L7206   L0021104   3.1μH     (LCQ17111J5)   L7206   L0021104   3.1μH     (LCQ17121J5)   L7207,7203   L0021101   3.3μH     (LCQ17121J5)   L7202,7203   L0021101   4.6μH     (LCQ17121J5)   L7202,7203   L7202   L7202   L7202     (LCQ17121J5)   L7202,7203   L7202   L7202   L7202   L7202   L7202     (LCQ17121J5)   L7202,7203   L7202	THE STATE OF THE S		(LCQ12510J5)		L0021114	0.25μH
C7206         K30275680         " (LCQ12680JS)         " 68pF         L7220,7221         L0021113         0.68µH           C7220         K30275820         " 82pF         L7218         L0021111         0.95µH           C7236,7258-7260         K30275910         " 91pF         L7207         L0021107         1.3µH           C7261         K30275101         " 100pF         L7211,7212         L0021102         1.7µH           C7232         K30275111         " 110pF         L7205         L0021103         2.8µH           C7239,7244         K30275121         " 120pF         L7201         L0021100         3.1µH           C7213,7251         K30275131         " 130pF         L7201         L0021101         4.6µH	C7246,7253	K30275560	Jopi			
C7220	C7206	¥30275690				
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	C/200	K30273680	Oopi			
C7236,7258-7260   K30275910   " " 91pF   L7207   L0021105   1.5μH     (LCQ12910J5)   L7210,7214,7215   L0021105   1.5μH     (LCQ12910J5)   L7204   L0021102   1.7μH     (LCQ12101J5)   L7204   L0021108   1.9μH     (LCQ12101J5)   L7208,7209   L0021106   2.3μH     (LCQ17111J5)   L7205   L0021103   2.8μH     (LCQ17111J5)   L7206   L0021104   3.1μH     (LCQ17121J5)   L7207   L7208   L7208   L7208     (LCQ17121J5)   L7208   L7208   L7208   L7208     (LCQ17121J5)   L7208   L7208     (LCQ17121J5)   L7208   L7208   L7208     (LCQ17121J5)   L7208   L7208   L7208     (LCQ17121J5)   L7208     (LCQ17121J5)   L7208     (LCQ17121J5)   L7208     (LCQ17121J5)   L7208   L7208     (LCQ17121J5)   L7208   L7208	C7220	K30275820		_		
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$		27 * 20 25 10 2 10 3 12 40 12	The state of the s			
C7261       K30275101       " 100pF (LCQ12101J5)       L7211,7212       L0021108       1.9μH         C7232       K30275111       " 110pF (L7208,7209)       L0021106       2.3μH         C7239,7244       K30275121       " 120pF (L7206)       L0021104       3.1μH         C7213,7251       K30275131       " 130pF       L7202,7203       L0021101       4.6μH	C7236,7258-7260	K30275910	The second secon		L0021105	
C7232   K30275111   "   "   110pF   L7205   L0021106   2.3μH     C7239,7244   K30275121   "   "   120pF   L7201   L0021101   3.1μH     C7213,7251   K30275131   "   130pF   L7202,7203   L0021101   4.6μH     C7213,7251   K30275131   "   130pF   L7202,7203   L0021101   4.6μH     C7213,7251	C7261	V20275101				7-313-4-4-1-1
C7232     K30275111     " 110pF     L7205     L0021103     2.8μH       (LCQ17111J5)     L7206     L0021104     3.1μH       C7239,7244     K30275121     " 120pF     L7201     L0021100     3.3μH       (LCQ17121J5)     L7202,7203     L0021101     4.6μH       C7213,7251     K30275131     " 130pF     L0021101     4.6μH	C/201	K302/3101	10001			
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	C7232	K30275111				
(LCQ17121J5) L7202,7203 L0021101 4.6μH  C7213,7251 K30275131 " " 130pF	12000 2000				L0021104	
C7213,7251 K30275131 " " 130pF	C7239,7244	K30275121			The second secon	The state of the s
The second secon	C7213,7251	K30275131		L/202,7203	L0021101	4.6μH
(LCQ12131J5) RELAY	Control of Action		TOTAL RESIDENCE AND ADMINISTRATION OF THE PROPERTY OF THE PROP			RELAY
C7225,7256 K30275151 " " 150pF RL7201-7218 M1190032 G2E (LCQ1715J5)	C7225,7256	K30275151	" " 150pF	RL7201-7218	M1190032	

	THE LINE OF	PLUG			DIODE
P7201	P0090075	P7015	D7501	G2090027	Si 1SS53
P7202	T9301703	TMP15DP			
					RESISTOR
			R7501-7507	J01245561	Carbon Film 1/4W TJ 560s
To The Dire	VFO	UNIT			SWITCH
Symbol No.	Part No.	Description	S7501,7505-7508	N3090004	SLE62251
PB-2265	F0002265	Printed Circuit Board	\$7503,7504	N3090002	SLE62301
	C0022650	P.C.B. with Components	S7502	N3090007	SLE72301
		eritti (III			
	4-115-21	TRANSISTOR			CONNECTOR
Q7303,7304	G3309451P	2SC945AP	J7502	P0090219	5045-03A
			J7501	P0090220	5045-04A
			J7504	P0090224	5045-08A
	Jan 18 Julia	PHOTO INTERRUPTER	J7503	P0090228	5045-12A
Q7301,7302	G0090001	ON-1105		The state of	
	14	RESISTOR			
R7301,7302	J02245221	Carbon Film 1/4W SJ 220Ω			
R7303,7304	J02245682	6.8kΩ		KEYBOA	RD UNIT
R7305,7306	J02245103	" " " 10kΩ	Symbol No.	Part No.	Description
			PB-2262	F0002262	Printed Circuit Board
				C0022620	P.C.B. with Components
		CAPACITOR			
C7301	K40129004	Electrolytic 16WV 10μF			
		(16RE10)			DIODE
			D7601-7609	G2090027	Si 1SS53
		CONNECTOR			
J7301	P0090252	5046-04A			SWITCH
			S7601-7619	N4090049	KHC10901
					CONNECTOR
			J7601	P0090222	5045-06A
	PUSH SI	W UNIT	J7602	P0090223	5045-07A
Symbol No.	Part No.	Description			
PB-2264	F0002264	Printed Circuit Board			
The second secon	C0022640	P.C.B. with Components			
	10.00 (20	ge - HA STANDESSTONE, COLD COME A STANDESSTON STANDARD ST			
63	Metrica I	DIODE	TO YES THE SE	DISPLA	Y UNIT
D7401-7404	G2090027	Si 1SS53	Symbol No.	Part No.	Description
			PB-2261	F0002261	Printed Circuit Board
				C0022610	P.C.B. with Components
	The Table 1 and the King	SWITCH			
S7401(a-e)	N4090050	SUH52H			
					LED
		And all the second	D7708-7719	G2090202	LN410YP
		CONNECTOR			
J7401	P0090247	5046-08A			
With John Commence					LED DISPLAY
			D7707	G2090110	5082-7415
		Limited and the	D7701-7706	G2090069	5082-7623
				7.	
	LEVER S	W UNIT			CONNECTOR
Symbol No.	Part No.	Description	J7702	P0090222	5045-06A
PB-2263	F0002263	Printed Circuit Board	J7703	P0090224	5045-08A
1 D-2203					

J7701	P0090227	5045-11A		10.00	CAPACITOR
			C8035	K30279024	Dipped Mica 500WV 56pF (DM15D560K5)
			C8044	K30275910	" " 91pF (LCQ12910J5)
	DIODE	SW UNIT	C8032,8034	K30279122	" " 470pF (DM15D471J5)
Symbol No.	Part No.	Description	C8043	K30279045	" " 560pF
PB-2266	F0002266 C0022660	Printed Circuit Board P.C.B. with Components	C8033	K30279046	(DM19D561K5) " " 620pF
	C0022000	r.c.b. with Components		A ANGLES OF COMMUNICATION	(DM19D621K5)
		DIODE	C8028	K30279092	" " 750pF (DM19D751J5)
D7801-7810	G2090003	Si V06B	C8027,8029	K30279097	" " 5000pF (DM19D502J5)
			C8005,8006	K10179017	Ceramic 50WV 0.0047μF (DB205YB472M5L5)
		Parameter Comment	C8010,8011,8016, 8036	K10177103	" " 0.01μF (DB205YB103M5L5)
THE RESERVE	A PART OF THE PART	A UNIT	C8002	K10176103	0.01μF
Symbol No. PB-2321	Part No. F0002321	Description Printed Circuit Board	C8001,8003,8007,	K13170473	(DB205YB103K5L5) " " 0.047µF
10-2721	C0023210	P.C.B. with Components	8008,8012,8014, 8017,8019,8021, 8023,8026,8030, 8031	K131/04/3	(DB207YF473Z5L5)
Q8006	G1090294	IC μPC7808H	C8037	K14179003	" " ". 500WV 0.1μF (DB209YZ104Z5L0)
		TRANSISTOR	C8004,8009	K23170002	Ceramic Chip " 0.1μF (GR43Y5V104Z50V09)
Q8001	G3315890	2SC1589	C8040,8041	K50177683	Mylar 0.068μF
Q8004,8005	G3322900	2SC2290			(50F2U683M)
Q8002,8003 Q8007	G3323950 G3402880K	2SC2395 2SD288K	C8039	K50177104	" " 0.1μF (50F2U104M)
			C8038	K40169003	Electrolytic 35WV 330μF (35RE330)
D8002-8005	G2090002	Si 10D10	C8022	K70127335	Tantalum 16WV 3.3μF (CS15E1C3R3M)
D8001	G2090021	Zener YZ033	C8013,8015,8018, 8020,8024,8025, 8042	K70127106	" 10μF (CS15E1C100M)
		RESISTOR			
R8026,8027	J02245010	Carbon Film 1/4W 1Ω			POTENTIOMETER
R8009,8011,8016, 8018	J10276159	" Composition 1/2W 1.5	VR8001 Ω	J51727222	CR19R2.2KB 2.2kΩ
R8006	J10276479	4.7			
R8007,8019,8020	J10276180	" " " 189		1,000,000	TRANSFORMER
R8012,8013 R8002	J10276240 J02245330	" " " 248	The state of the s	L0020289A L0020631B	
R8010	J10276390	" Composition	T8003	L0020631B	
R8017,8021,8022	J21335390	1/2W 399 Metallic Film 2W 399			INDUCTOR
R8023	J21335680	" " 688		L1020035A	
R8001	J02245121	Carbon " 1/4W 120	DΩ L8005	L1020015	
R8014,8015	J10276121	" Composition 1/2W 120	L8006 0Ω L8007	L1020395A L1020015	
R8024	J02245271	" Film 1/4W 270			
R8003,8004	J10276331	" Composition	οΩ	Q5000011	Wrapping terminal C
R8008	J10276102	" " " 1k;		Q5000006	Lighthouse terminal STK-97
R8005	J01245152	" Film 1/4W 1.5	kΩ	Q9000029 R4056950B	BUSH 66 HEAT SINK
		La la companya de la companya del companya de la companya del companya de la comp			COOLING MOTOR

		RADIAL FAN		PER PART TOTAL						
	R3056970			NIE GALL						
						RESIST	OR			
		PLUG		R9003,9005,9006, 9009	J02245220	Carbo	n Film	1/4W	SJ	22Ω
P8001(with wire)	T9204321	3191-06P1	15-11-15-1	R9167	J02245330		,,	77		33Ω
P8002	P0090075	P-7015		R9161,9193	J02245560	,,	"	,,		56Ω
J8001	P1090111	J-7015	1.0	R9013,9027,9029,	J02245300		"		100	100Ω
20001	11070111			9041,9056,9065, 9067,9077,9078, 9098,9102,9106,	302243101					10042
	IF U	NIT		9112,9115,9118,		100				
Symbol No.	Part No.		ription	9120,9159,9171,						
PB-2255B	F0002255B	Printed Circui	it Board	9174,9175,9179, 9188,9200						
	C0022550	P.C.B. with C	omponents							
				R9033-9036,9070, 9075,9080	J01245101	1555		**	TJ	100Ω
		IC		R9206	J02245121			••	51	120Ω
Q9025	G1090077	MC3403P		R9048,9049,9124,	J02245151	,,	**	**		150Ω
Q9030	G1090063	TA7060AP		9185,9207	202210101	.45.			ciói	10000
	G1090077	μA3403P		R9072,9073	J01245151		,,		TI	150Ω
		31		R9044,9045	J02245181		***	**	SJ	730400000
		TRANSISTOR		R9060,9089,9092,	J02245221		"	***	"	220Ω
Q9026,9027	G3107331Q	2SA733AQ		9104,9169						
Q9005-9007,9013,	G3309451P	2SC945AP		R9204,9205	J02245271	22	700	W.		270Ω
9018-9024,9028, 9031,9033		TO THE PROPERTY OF THE POPULATION OF		R9007,9008	J02245391	"	n.	**	**	390Ω
9031,9033				R9014,9025,9031,	J02245471			**		470Ω
Q9012,9014	G3319230O	2SC1923-O		9066,9101,9105						
				R9016,9053,9055,	J02245561		**		**	560Ω
		FET		9058,9099,9103,						
Q9010,9011	G3090034	2SK19TM-Y		9109,9110,9119						
Q9004	G3800610G	2SK61GR		R9046,9050,9088,	J02245681				**	680Ω
Q9001-9003,9008,	G4800730G	3SK73GR		9186,9197						
9009,9015-9017, 9029,9032,				R9074	J01245821		**	**	TJ	820Ω
9034-9036				R9096,9097,9198	J02245821		(4)	"	SJ	820Ω
790000000000000000000000000000000000000				R9040,9061,9079,	J02245102	1.05	200		i.e.	1kΩ
				9091,9114,9122, 9154,9162,9180,						
		DIODE		9182,9191,9192,						
D9034-9036,9047	G2090029	Ge	1N60	9194,9210-9212						
1272-230-272-272-27			WE NAME AND	R9173	J02245152	"	726	**	**	$1.5k\Omega$
D9045,9046	G2090093		1N270	R9028,9051,9068,	J02245182		**	**	**	1.8kΩ
D9024	G2090165	Varactor	FC52M-5	9095,9127,9156, 9189,9190						
D9002-9023, 9025-9033,9037.	G2090027	Si	1SS53	FARENCES.						
9038,9040-9044.				R9023,9037,9158,	J02245222	""	200	330	"	$2.2k\Omega$
9048-9051				9176						
D0054	C2000150	70	DD4 7FB2	R9131,9170,9177	J02245272	, a	**		**	2.7kΩ
D9054	G2090158	Zener	RD4.7EB2	R9001,9201	J02245332		<b>10</b> 0	"	"	3.3kΩ
D9001,9052	G2090197	,,	RD9.1EB3	R9145	J02245392	n	***	**	•	3.9kΩ
D9039 D9053	G2090021 G2090118	Schottky bar	YZ033	R9019,9032,9057, 9123,9132,9148	J02245472					4.7kΩ
D9033	G2090118	Schottky bar	Her 15597	- 7123,7132,7146						
		CRYSTAL		D0043 0043 0045	102245552	- G	1000	625	035	
X9001	H0102470	HC-18/U	19.7475MHz	R9042,9043,9047, 9052,9071,9076.	J02245562				**	5.6kΩ
7,7001	110102470	110-10/0	19.1713MIL	9081,9108,9111,						
		CRYSTAL FIL	TER	9187,9199						
XF9001	H1102036A	XF-8,9JE		R9064,9069,9143,	J02245822	"		90	nee	8.2kΩ
XF9005	H1102030A	XF-8.9KS		9157	302243022	**	-0000	ver/	sucidit.	U. Z.Kuz
XF9007	H1102042	XF-10.7KS		R9004,9011,9017,	J02245103			.,		10kΩ
XF9002(OPTION)	H1102037	XF-8.9KCN	CW(N)	9082,9084,9093, 9094,9116,9128,	202210103	-				TOKAS
XF9003( " )	H1102038	XF-8.9KC	CW(M)	9094,9116,9128,						
XF9004( " )	H1102039	XF-8.9KA	AM	9133,9135,9137, 9153,9163,9164,						
XF9006( " )	H1102041	XF-10.7KC	CW(M)	9166,9168,9181,						
		THERMISTOR		R9086,9107	J02245123		200	- 0.	335	12kΩ
TH9001	G9090002	D22A		R9021,9059,9085,	J02245153					15kΩ
TH9002	G9090011	SDT1000		9129,9134,9136,						101136
TH9003,9004	G9090021	D91A		9202		1				

R9002,9087,9140	J02245183	Carbon Film 1/4W SJ 18kΩ	C9049,9057,9074,	K13170102	Ceramic Disc 50WV S	Ĺ
R9012,9054,9063, 9165,9172,9178, 9183,9184,9203	J02245223	" " " 22kΩ	9091,9092,9097, 9098,9102,9103, 9107,9125,9129, 9167,9169,9181, 9186,9187,		(DB200YF102Z5L2)	0.001µF
R9018,9022	J02245273	27kΩ	9194-9196		Land Street	
R9026	J02245333	" " " 33kΩ	C9005,9007,9009,	K14180103	" " 63WV	0.01µF
	J02245393	" " " 39kΩ	9010,9012-9014,		(RD871-1FZ-103Z63V	
R9015,9125,9213	J02245473	47kΩ	9017,9018,9020, 9021,9024-9032,			r.
R9038,9160,9208	J02245563	56kΩ	9036-9048,			
R9039	J02245683	" " " 68kΩ	9050-9055,			
R9195,9209	J02245823	82kΩ	9058-9061, 9071,9073,			
R9010,9030,9062, 9090,9138,9139, 9142,9149	J02245104	100kΩ	9075-9090, 9094-9096, 9099-9101, 9104-9106,			
R9117	J02245154	150kΩ	9108-9110,9112,			
R9144,9151	J02245184	180kΩ	9114,9115,9119, 9122,9128,9130,			
R9126,9147	J02245224	220kΩ	9132,9136-9138,			
R9113,9121	J02245274	270kΩ	9141,9144-9154.			
R9155	J02245474	470kΩ	9156,9157,9159, 9161–9166,9168,			
R9020,9146,9150, 9152	J02245105	" " " 1ΜΩ	9170-9180, 9182-9185,			
R9130	J02245225	2.2ΜΩ	9188-9190,9192, 9193,9200			
		POTENTIOMETER				
VR9001	J50749501	H0812A001-500B 500ΩB	C9063,9133,9197	K13170473	" " 50WV	0.047µF
VR9002,9005	J51740501	EVNB3AA00B52 500ΩB			(DB207YF473Z5L5)	010117
VR9003,9004	J50749502	H0812A004-5KB 5kΩB	C9015	K50177102	Mylar "	0.001µF
VR9006	J50749203	H0812A006-20KB 20kΩB	C7010	REGITTEE	(50F2U102M)	0.00141
		CAPACITOR	C9019,9142	K50177223	" "	0.022µF
	K02179004	Ceramic Disc 50WV CH 3pF	05015,5142	K50177225	(50F2U223M)	0.022#1
		(DD104CH030C50V02)	C9124,9143	K40179013	Electrolytic "	1μF
	K06173060	" " UJ 6pF	C7124,7143	K40173013	(50RE1)	141
		(DD104UJ060J50V02)	C9123	K40179011	(SORET)	3.3µF
	K06173080	" " 8pF			(50RE3R3)	
		(DD104UJ080D50V02)	C9127	K40149001	" 25WV	4.7µF
C9056,9118	K00173100	SL 10pF			(25RE4R7)	
		(DD104SL100D50V02)	C9006,9016,9093,	K40129004	" 16WV	10µF
C9008,9111	K00175220	" " 22pF (DD104SL220J50V02)	9113,9116,9131, 9139,9140,9191		(16RE10)	
	K02179010	" " CH 24pF (DD104CH240J50V02)	C9120	K40129016	(16RE22)	22μF
C9155	K00175270	" " 27pF (DD104SL270J50V02)	C9126	K40129002		47μF
C9034	K02175390		00146		(16RE47)	
C9034	K021/3390		C9143	K40109002	,, 10WV	47μF
C9068	K02175470	(DD105-257CH390J50V02) " " 47pF	C0160	17.401.2000.7	(10RE47)	100
C9008	K021/34/0	(DD106CH470J50V02)	C9160	K40129007	(16RE100)	100µF
C9070,9072	K00175470	SL 47pF	C9135	K70167684	Tantalum 35WV	0.68µF
C9033	K02175680	(DD104SL470J50V02) " " CH 68pF	C9134	K70167105	(CS15E1VR68M)	1µF
	2222222222222	(DD107CH680J50V02)	- Day 190 je	our-construction of Policies	(CS15E1V010M)	pr <b>s2</b> 000000
C9069	K02175101	" " " 100pF	THE PARTY OF THE P		TRIMMER CAPACITOR	
		(DD107CH101J50V02)		K91000087	ECV1ZW10x60	10pF
C9121	K00175101	" " " SL 100pF		an animus		
60150	V. 1017/101	(DD105SL101J50V02)				
C9158	K10176101	" " " B 100pF			INDUCTOR	
00000		(DD104B101K50V02)	L9002	L1190111	FL4H-5R6K	5.6µH
C9062	K06175101	" " UJ 100pF (DD106UJ101J50V02)	L9042,9043,9047, 9048	L1190023	FL5H-220K	22µH
C9198,9199	K06175121	" " 120pF	L9001,9003-9038,	L1190020	FL5H-151K	150µH
		(DD107UJ121J50V02)	9041,9044-9046,			of the L
C9117	K00175221	" " SL 220pF	9049-9059			
		(DD107SL221J50V02)	L9039,9040	L1190017	FL5H-102K	1mH
C9001-9004,9011,	K13170102	0.001μF				
9022,9023,9035		(DB200YF102Z5L2)				

		TRANSFORMER	R2212,2216	J01245105	Carbon film 1/4W TJ 1MΩ
T9001	L0021090A				
T9002	L0021092A				J401 S 10 10 10 10 10 10 10 10 10 10 10 10 10
T9003	L0021087B			CHEST TOUT	POTENTIOMETER
T9004	L0021086A		VR2201	J51739102	EVMG0GA01B13 1kΩB
T9005	L0021088A		VK2201	331739102	EVMG0GA01B13 1K12B
T9006	L0021088A				
	L0021091 L0020141				
T9007,9013-9015, 9018			C2202,2203	K13170102	CAPACITOR  Ceramic Disc 50WV 0.001µF
T9008	L0021089				(DB200YF102Z5L2)
T9009	L0021093		C2205,2206,2208	K14180103	" " 63WV 0.01μI
	L0021119A				(RD871-IFZ103Z)
T9011	L0021099A		C2201	K70167684	Tantalum 35WV 0.68µl
T9012	L0020883				(CS15E1VR68M)
T9016	L0021098A	17 - 12	C2204,2207	K70120001	" 16WV 4.7μF
T9017,9019	L0020140			\$5500000000000000000000000000000000000	(489D475X0016B1)
T9020	L0021097A	0140			(103011011011)
T9021	L0021096A			The second	
T9022	L0021095			Q5000036	TP Terminal G
17022	20021073			Q3000030	Tr Tellimai G
		CONNECTOR		TX CARRIE	R OSC UNIT
J9001-9008	P0090248	EMCS0252M	Symbol No.	Part No.	Description
	LIST STATE OF THE		PB-2400	F0002400	Printed Circuit Board
			TD-2400	C0024000	P.C.B with Components
		PLUG		C0024000	F.C.B with Components
D0001 0004	D1000240	THE THEORY			
P9001-9004	P1090249	EMCM0201			
					TRANSISTOR
			Q2305	G3107331P	2SA733AP
	Q500011	Wrapping terminal C	Q2301-2304,2306	G3309451P	2SC945AP
	100W P	S UNIT			DIODE
Symbol No.	Part No.	Description	Q2303	G2090027	Si 1SS53
PS1	Q9000135	HHB-3001 100-117 VAC	Q2301,2302	G2090118	Schottky Barrier 1SS97
PS1	Q9000136	HHB-3002 200-234 VAC	Q2301,2302	02070110	Schottay Barrier 18897
101	Q7000120	11110 0000 200 201 1110			
					CRYSTAL
EV	FERNAL CO	NTROL UNIT	X2301	H0102462	
		Control and the second	A2301	H0102462	NR-2 15.514MHz
Symbol No.	Part No.	Description			
PB-2367A	F0002367A	Printed Circuit Board			
	C0023670	PCB with components			RESISTOR
			R2309,2313	J02245101	Carbon Film 1/4W SJ 100Ω
			R2310	J02245102	" " " 1kΩ
		IC	R2305	J02245152	" " " 1.5ks
Q2203	G1090246	AN6552	R2306	J02245392	3.9ks
		000 000 V 000 V 0	R2301,2303,2307, 2314,2315	J02245103	10kΩ
		TRANSISTOR	R2308	J02245123	12kΩ
Q2201,2202,2204	G3309451P	2SC945AP	R2308	J02245123 J02245183	
Q2201,2202,2204	033094311	23C343AI			
			R2312	J02245223	" " " 22kΩ
			R2302,2304	J02245473	" " 47kΩ
		DIODE			
D2201	G2090118	Schottky Barrier 1SS97			
					CAPACITOR
			C2303	K06173060	Ceramic Disc 50WV UJ 6pF
	0// 100000	RESISTOR			(DD104UJ060J50V02)
R2213,2214	J01245101	Carbon film 1/4W TJ 100Ω	C2312	K02175120	" " CH 12pF
R2204,2205	J01245472	" " 4.7kΩ	the state of the state of		(DD104CH120J50V02)
R2206,2208	J01245562	" " " 5.6kΩ	C2304	K06175150	" " UJ 15pF
R2202,2215	J01245103	10kΩ	1 52501	1001/3130	(DD104UJ150J50V02)
R2207,2209	J01245153	" " " 15kΩ			(DD1040313030 V02)
R2210,2211	J01245183	" " " 18kΩ			
D 2202		" " 47kΩ		1	I .
R2203 R2201	J01245473 J01245563	" " 47kΩ " " 56kΩ	<del> </del>		

C2306	K06179006	Ceramic Disc 50WV UJ 30pF (DD104UJ300J50V02)	C2706,2707	K70167334	Tantalum 35WV 0.33μF (CS15E1VR33M)
C2309	K02179016	" " CH 51pF (DD106CH510J50V02)	C2704	K40120226	Electrolytic 16WV 22μF (16RL22)
C2310	K02179027	" " " 270pF (DD112CH271J50V02)			(TOKE)
C2301,2302,2305,	K14180103	" " 63WV 0.01μF			0011150705
2307,2308,2311,	K14100103	(RD871-1F2-103Z)	M12701	D0000002	CONNECTOR
2313,2314	TC-IIV C	(RD671-1F2-1032)	MJ2701	P0090037	5048-8A
		AND ALLE A TRANS			
TC2201		TRIMMER CAPACITOR			I defeated to the second
TC2301 TC2302	K91000028	ECV-1ZW 10x53N 10pF			
	K91000059	ECV-1ZW 04x53N 4pF			UNIT (OPTION)
TC2303	K91000029	ECV-1ZW 20x53N 20pF	Symbol No.	Part No.	Description
			PB-2267	F0002267	Printed Circuit Board
				C0022670	P.C.B with Components
L2301-2303	1 11000000	INDUCTOR			
Physical Company of the Company of t	L1190029	FL5H-470K 47μH			
L2304,2305	L1190020	FL5H-151K 150µH		1	IC
			Q7901,7902	G1090368	MN1203
	Q5000036	TP terminal G			
			D7001	000000	DIODE
			D7901	G2090027	Si 1SS53
				urusu	THE RESERVE TO THE PERSON OF T
SHIP AND AND	KEYER UNI	T (OPTION)	D7001 7002	Y01045004	RESISTOR
Symbol No.	Part No.	Description	R7901,7902	J01245224	Carbon Film 1/4W TJ 220kS
PB-1728A	F0001728A	Printed Circuit Board			
1 D-1 / 20A	C001728A	P.C.B with Components			2. 22./ 22./22.
	C0017280	1.C.B with Components	RB7901	140000007	BLOCK RESISTOR
			KB/901	J40900027	RA1/16 220KΩ7A 1/16W
		IC			220kΩx7
Q2701	G1090223	8044			
Q2701	01070223	8044			00111170700
			J7901	P0090092	CONNECTOR
		TRANSISTOR	J7901 J7902	P0090092 P0090090	3022-08A 3022-09A
Q2702	G3318150Y	2SC1815Y	31902	F0090090	3022-09A
20102	023101301	25010151			
		DIODE			
D2701-2706	G2090029	Ge 1N60			
20101	02070027	1100		EM HAUT	(OPTION)
			Symbol No.	Part No.	Description
		RESISTOR	PB-2254	F0002254	Printed Circuit Board
			- D DDUT	10002234	
R2705	J02245102	Carbon Film 1/4W SJ 1kΩ		C0022540	P ( R with Components
LIA-SOCIAL MANAGEMENT	J02245102 J02245332	Carbon Film 1/4W SJ 1kΩ " " " 3.3kΩ		C0022540	P.C.B with Components
R2704	CONTRACTOR SERVICES	AND DESCRIPTION OF A PARTY AND A PARTY		C0022540	P.C.B with Components
R2704 R2709,2710	J02245332	" " " 3.3kΩ		C0022540	
R2704 R2709,2710	J02245332 J02245103	" " " 3.3kΩ " " " 10kΩ	O2109	Self-France 1 - 11	IC
R2704 R2709,2710	J02245332 J02245103	" " " 3.3kΩ " " " 10kΩ	Q2109 Q2118	G1090246 G1090080	IC AN6552
R2705 R2704 R2709,2710 R2701,2702,2707	J02245332 J02245103	" " " 3.3kΩ " " " 10kΩ	Q2118	G1090246 G1090080	IC AN6552 µPC78L08
R2704 R2709,2710	J02245332 J02245103	" " " 3.3kΩ " " 10kΩ " " 100kΩ		G1090246	IC AN6552
R2704 R2709,2710 R2701,2702,2707	J02245332 J02245103 J02245104		Q2118	G1090246 G1090080	IC AN6552 µPC78L08
R2704 R2709,2710 R2701,2702,2707 VR2702	J02245332 J02245103 J02245104		Q2118 Q2104	G1090246 G1090080	IC AN6552 μPC78L08 μPC577H
R2704 R2709,2710 R2701,2702,2707	J02245332 J02245103 J02245104	" " " 10kΩ " " 100kΩ  POTENTIOMETER  SR19R 100kΩB	Q2118 Q2104	G1090246 G1090080 G1090072	IC AN6552 μPC78L08 μPC577H TRANSISTOR
R2704 R2709,2710 R2701,2702,2707 VR2702	J02245332 J02245103 J02245104 J51723104	" " " 10kΩ " " 100kΩ  " " 100kΩ  POTENTIOMETER  SR19R 100kΩB	Q2118 Q2104	G1090246 G1090080 G1090072	IC AN6552 μPC78L08 μPC577H TRANSISTOR
R2704 R2709,2710 R2701,2702,2707 VR2702	J02245332 J02245103 J02245104 J51723104	" " " 10kΩ " " 100kΩ  " " 100kΩ  POTENTIOMETER  SR19R 100kΩB  CAPACITOR  Ceramic Dics 50WV 0.047μF	Q2118 Q2104 Q2103,2105,2107, 2110-2117 Q2108	G1090246 G1090080 G1090072 G3309451P	IC AN6552 μPC78L08 μPC577H  TRANSISTOR 2SC945AP
R2704 R2709,2710 R2701,2702,2707 VR2702	J02245332 J02245103 J02245104 J51723104 K13170473	" " " 10kΩ " " 100kΩ " " 100kΩ  POTENTIOMETER  SR19R 100kΩB  CAPACITOR  Ceramic Dics 50WV 0.047μF (DB207YF473Z5L5)	Q2118 Q2104 Q2103,2105,2107, 2110-2117	G1090246 G1090080 G1090072 G3309451P	IC AN6552 μPC78L08 μPC577H  TRANSISTOR 2SC945AP 2SC945AQ
R2704 R2709,2710 R2701,2702,2707 VR2702	J02245332 J02245103 J02245104 J51723104 K13170473	" " " 10kΩ " " 100kΩ " " 100kΩ  " " 100kΩ  POTENTIOMETER  SR19R 100kΩB  CAPACITOR  Ceramic Dics 50WV 0.047μF (DB207YF473Z5L5)  Mylar " 0.1μF	Q2118 Q2104 Q2103,2105,2107, 2110-2117 Q2108 Q2101	G1090246 G1090080 G1090072 G3309451P G3309451Q G3316740L	IC AN6552 μPC78L08 μPC577H  TRANSISTOR 2SC945AP  2SC945AQ 2SC1674L

		FET				R2144,2168,2173,	J02245223	Carbo	on Film	1/47	/ SJ	$22k\Omega$
Q2102	G3090035	2SK19TM-GI	?			2175,2180,2182 R2109,2131,2140,	J02245273	.,	,,	,,	**	27kΩ
		DIODE				2179 R2136	J02245473	**	,,	,,	.,	47kΩ
D2101 2102 2106	G2001880F	Ge	1S188	EM					.,			68kΩ
D2101,2102,2105, 2106	G2001880F	Ge	15100	FM		R2150	J02245683				TJ	
1000.200	C2000027	Si	1SS53			R2145	J01245683 J02245823		"	.,	SJ	82kΩ
D2107,2108	G2090027	10.00	FC63-			R2146 R2107,2124,2141,	J02245823 J02245104	17.55	1705/		23	100ks
D2109	G2090210	Varactor		_		R2107,2124,2141, 2163	302245104		,,		**	100K2
D2110	G2090006	7	MV13		2		102245274		570		1,10	2701.4
D2104	G2090042	Zener	RD8.2			R2138	J02245274	**		**	**	270ks
D2103	G2090155	.,	RD9.	LEB	3	R2165	J02245334	.,	,		,,	330KS
		CRYSTAL		-		Tumor Levil	2211111	-	MISTOR	V_		
X2101	H0102275	HC-18/U	9442.	-		TH2101	G9090001	SDT-	250			
X2102	H0100440	HC-18/U	8987.	5kF	Iz		1 A Security					
		CERAMIC FIL	TER			VR2107	J50716201		TIOME FAS200			200Ω
CF2101	H3900200	CFW455E				VR2106	J51740501		-B3AA0	141519-1-50		500Ω
NA BIVI	11000000	C. 11 100L				VR2105	J51740102		-B3AA0			1kΩE
						VR2104	J51740502		-B3AA0			5kΩE
		CERAMIC DIS	CRIMI	NA7	TOR	VR2102	J50716502	100000000000000000000000000000000000000	FAS5KE	E-2,11-17/17/2	_	5kΩE
CD2101	H7900040	SFD455S4				VR2102	J50716103		FAS10K	-		10kΩ
CDEIVI	11/200010	0. 5.10001				VR2101	J50716104		FAS100	10.00		100kΩ
						TRETOT	330110101					
	*******	RESISTOR		c.	100				0170-			
R2127	J02245100	Carbon Film		1000-	10Ω		***************************************		CITOR			7 -
R2153,2158	J02245330		"	"	33Ω	C2110	K00173070	1200000	mic Disc			0.000
R2149	J02245470	" "		"	47Ω		*****	-	104SL07		- 11	
R2101,2171	J02245560		"	**	56Ω	C2166	K06175150					J 15pF
R2154,2172	J02245680		**	••	68Ω				104UJ1	-		
R2120	J02245820	" "	"	**	82Ω	C2171	K00179005					L 20pF
R2106,2110,2117, 2125,2160,2162, 2186	J02245101		"		100Ω	C2126	K06175220	125	104SL20 		· U	J 22pF
D2166	J02245221	,, ,,		.,	220Ω	C2170,2172	K00175121	(DD	104032.			L 120p
R2166 R2134	J02245221 J02245271		"	"	270Ω	C2170,2172	K001/3121		104SL12			
R2104,2116,2118, 2128,2184	J02245271 J02245471	" "	"	_	470Ω	C2128,2129	K06175151		1043L1. .,		. U	J 150p
R2130	J01245471	,, ,,		TI	470Ω	C2127	K00175221	(DD	107031.		100	L 220p
R2130	J01245471 J02245561		"	-	560Ω	C2127	K001/3221	1	107SL2			11.00 Care Ca.
Charge of Europe Control	CONTRACTOR CONTRACTOR	,, ,,		21	1kΩ	C2148 2152	K19149005		iconduct			
R2111,2126,2135, 2142,2152,2170, 2181	J02245102			"	1 K32	C2148,2152	K131+3002	27/2000	T04X22	25V	VV (	0.0022
R2108	J10246102	Carbon Com	· Control of the Control		IkΩ	C2101,2122	K13170102	Cera	mic Dis 200YF1	c 50V	VV	
R2112,2143,2148, 2167	J02245152	Carbon Film			1.5kΩ	C2136,2145,2150	K19149009	Sem	iconduc			: 0.0047 <sub>1</sub>
R2133	J02245182				1.8kΩ	1		(UA	T05X47			Commence of the second
R2119,2123 2129	J02245222	" "	•	"	2.2kΩ	C2102-2106, 2108,2109,2112,	K14180103	Linksing	mic Dis 871-1F2			0.01
R2155,2176 R2185	J02245272		••		2.7kΩ	2115,2130,2131, 2158,2164,2165, 2169,2173						
R2156,2157,2169	J02245332		••	••	3.3kΩ	C2122,2124,2134,	K19149017	Sem	iconduc	tor Ce	ramio	2
R2105,2113,2132, 2183	J02245472		••		4.7kΩ	2142		(UA	T06X22			0.022
R2102,2121,2122, 2161,2164	J02245562		).**	••	5.6kΩ	C2116-2118, 2125,2144,2161, 2162	K19149021		T08X47			0.047
R2151	J02245822				8.2kΩ	2102						
R2115,2147,2178	J02245103				10kΩ	C2107,2111,2114,	K19149025	**				0.1μ
R2174	J02245123				12kΩ	2119,2120		(UA	T13X10	4K-L	6AE	()
R2139,2177	J02245153			.,	15kΩ	C2123	K70167224	Tan	talum	351	VV	0.22,
AND THE PERSON OF THE PERSON O							<ul> <li>CONTROL CARDON EDITOR STUDIO CONTROL</li> </ul>	mail: Marca 6536				

	·			
C2132,2133,2135,	K40179013	Electrolytic 50WV 1µF		
2137,2141,2143, 2147,2163		(50RE1)		
2147,2103				
C2167	K40179009	" 2.2μF		
		(50RE2R2)		78.716-61
C2139,2140,2155	K40149001	" 25WV 4.7μF		
		(25RE4R7)		
C2138,2153,2157,	K40129004	" 16WV 10μF		
2160,2168	3.5.1.1.1.5.5.5.5.5.5.1	(16RE10)		
C2113,2146,2149	K40129008	33μF		
		(16RE33)		
C2151,2154,2156	K40129002	., , 47μF		
		(16RE47)		
C2159	K40109001	" 10WV 100μF		
		(10RE100)		
		TRIMMER CAPACITOR		
TC2101	K91000075	TZ03R200E		
	AND THE STREET STATE OF THE STA	and the control of the provide Association	-	Terra Aria
				1 -
		INDUCTOR		
L2101-2104	L1190017	FL5H-102K 1mH		
L2105	L1190041	181LY-104K 100mH		V 107 1 10 100
		Toomit.		
AL DE				
		TRANSFORMER		
T2101	L0020140	R12-4170		
T2102,2103	L0190002	7MC-312162NO		-brains
T2104	L0020319	L0020319		THE PERSON
T2105	L0020313	R12-9406A		W. T. T. T.
12105	L0021000A	K12-9400A		
	100			
	1911			
	ACCES	CODIFC		
Symbol No.	The second secon	SORIES		
Symbol No.	ACCES Part No.	Description		
Symbol No.	Part No.	Description AC POWER CORD		
Symbol No.	The second secon	Description AC POWER CORD 2 wire, 2 prong plug		
Symbol No.	Part No. T9013280	Description AC POWER CORD 2 wire, 2 prong plug (DC-546-007)		
Symbol No.	Part No.	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug		
Symbol No.	Part No.  T9013280  T9013282	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)		
Symbol No.	Part No. T9013280	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug)		
Symbol No.	Part No.  T9013280  T9013282  T9013283	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)		
Symbol No.	Part No.  T9013280  T9013282	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K)		
Symbol No.	Part No.  T9013280  T9013282  T9013283	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)		
The second	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)		
Symbol No.	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002  C3001120	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG		
P37	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002  C3001120  P1090256	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)		
The second	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002  C3001120  P1090256  C3001119	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)  RX JUMPER CABLE		
P37	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002  C3001120  P1090256	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)		
P37	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002  C3001120  P1090256  C3001119	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)  RX JUMPER CABLE		
P37	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000002  C3001120  P1090256  C3001119	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)  RX JUMPER CABLE		
P37	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000005  Q0000002  C3001120  P1090256  C3001119  P0090075	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)  RX JUMPER CABLE		
P37	Part No.  T9013280  T9013282  T9013283  T9013285  S3000023  Q0000007  Q0000005  Q0000005  Q0000002  C3001120  P1090256  C3001119  P0090075	Description  AC POWER CORD  2 wire, 2 prong plug (DC-546-007)  3 wire, 3 prong UL plug (UC-904-016)  3 wire, 3 prong Australian plug) (SC-411-001)  3 wire, 2 prong EU plug (YFC-14K) (Cord Band)  FUSE  10A (100-117 VAC)  5A (200-234 VAC)  1A (Backup)  DUMMY PLUG (QS-P8FK)  RX JUMPER CABLE (P-7015)		

